


**PIFA ANTENNA DESIGN FOR MOBILE COMMUNICATION
WITH HFSS ANTENNA TOOLKIT**

Submitted in partial fulfilment of the requirements for the award of Bachelor of
Engineering degree in Electronics and Communication Engineering

By

CH. PAVAN KUMAR (40130032)

C. SREENATH (40130033)



**DEPARTMENT OF ELECTRONICS AND COMMUNICATION ENGINEERING
SCHOOL OF ELECTRICAL AND ELECTRONICS**

SATHYABAMA

**INSTITUTE OF SCIENCE AND TECHNOLOGY
(DEEMED TO BE UNIVERSITY)**

CATEGORY-1 UNIVERSITY BY UGC

**Accredited with Grade "A++" by NAAC | 12B Status by UGC | Approved by AICTE
JEPPIAAR NAGAR, RAJIV GANDHI SALAI, CHENNAI – 600119**

APRIL - 2024



SATHYABAMA

INSTITUTE OF SCIENCE AND TECHNOLOGY

[DEEMED TO BE UNIVERSITY]

CATEGORY-I UNIVERSITY BY UGC

Accredited "A++" Grade by NAAC | 12B Status by UGC | Approved by AICTE

www.sathyabama.ac.in

DEPARTMENT OF ELECTRONICS AND COMMUNICATION ENGINEERING

BONAFIDE CERTIFICATE

This is to certify that this Project Report is the bonafide work of **CH. PAVAN KUMAR (40130032)**, **C. SREENATH (40130033)** who carried out the project entitled "PIFA ANTENNA DESIGN FOR MOBILE COMMUNICATION WITH HFSS ANTENNA TOOLKIT" under our supervision from November 2023 to April 2024.


Internal Guide

Dr. F.V. JAYA SUDHA, ME., Ph.D.,

Associate Professor


Head of the Department

Dr. T. RAVI, ME., Ph.D.,

Submitted for Viva voce Examination held on 17/4/24

Internal Examiner

External Examiner

DECLARATION

We, CH. PAVAN KUMAR (40130032) and C. SREENATH (40130033) hereby declare that the project report entitled "PIFA ANTENNA DESIGN FOR MOBILE COMMUNICATION WITH HFSS ANTENNA TOOLKIT" done by us under the guidance of Dr.F.V.JAYA SUDHA, ME., Ph.D., Associate Professor at Sathyabama Institute of Science and Technology, Jeppair Nagar, Rajiv Gandhi Salai, Chennai - 600119 is submitted in the partial fulfillment of the requirements for the award of Bachelor of Engineering degree in DEPARTMENT OF ELECTRONICS AND COMMUNICATION ENGINEERING.

DATE: 16/04/24

PLACE: CHENNAI

SIGNATURE OF THE CANDIDATES

1. 
2. 

ACKNOWLEDGEMENT

I am pleased to acknowledge our sincere thanks to **Board of Management of Sathyabama Institute of Science and Technology** for their kind encouragement in doing this project and for completing it successfully. I am grateful to them.

I convey my thanks to **Dr. N. M. NANDHITHA, M.E., Ph.D., Professor & Dean, School of Electrical and Electronics** and **Dr. T. RAVI, Ph.D., Professor & Head of the Department, Department of Electronics and Communication Engineering** for providing me necessary support and details at the right time during the progressive reviews.

I would like to express my sincere and deep sense of gratitude to my Project Guide **Dr. F.V. JAYA SUDHA, ME., Ph.D., Associate Professor Dept. of Electronics and Communication Engineering**, for her valuable guidance, suggestions, and constant encouragement for the successful completion of my project work.

I wish to express my thanks to all Teaching and Non-teaching staff members of the Department of Electronics and Communication Engineering who were helpful in many ways for the completion of the project.

ABSTRACT

The Planar Inverted-F Antenna (PIFA) design, along with a T-junction power divider to distribute power evenly between them, represents a strategic approach aimed at bolstering antenna performance, particularly in terms of gain. The utilization of two patches aims to improve the antenna's gain by leveraging constructive interference between the radiated fields from each element. The T-junction power divider ensures equitable power allocation to both patches, enhancing radiation efficiency. Theoretical analysis suggests that this configuration has the potential to double the antenna's gain compared to single-patch designs. However, practical considerations such as impedance matching and radiation efficiency must be addressed for optimal performance. This study explores the design, simulation, and optimization processes involved in implementing the dual patch PIFA with a T-junction power divider. Experimental validation is conducted to assess the antenna's performance in terms of gain, radiation pattern, and signal coverage. The findings demonstrate the efficacy of this approach in improving the overall performance of PIFA antennas, paving the way for enhanced signal strength and coverage in wireless communication applications.

This configuration enables the simultaneous radiation of electromagnetic waves from both patches, fostering constructive interference and thereby enhancing the overall gain compared to a single-patch PIFA design. The T-junction power divider ensures equitable power distribution to each patch, facilitating optimal radiation efficiency. Theoretically, this setup holds the potential to double the antenna's gain, provided proper alignment and optimization. However, practical considerations such as impedance matching and radiation efficiency must be addressed. In summary, this innovative approach holds promise for improving signal strength and coverage in wireless communication applications, showcasing its relevance and potential impact in the field.

TABLE OF CONTENTS

CHAPTER NO.	TITLE	PAGE NO.
	ABSTRACT	V
	LIST OF ABBREVIATIONS	VIII
	LIST OF FIGURES	IX
	LIST OF TABLES	X
1	INTRODUCTION	1
	1.1 MICROSTRIP PATCH ANTENNA	2
	1.2 TYPES OF MICROSTRIP PATCH ANTENNA	3
	1.2.1 RECTANGULAR PATCH ANTENNA	4
	1.2.2 CIRCULAR PATCH ANTENNA	5
	1.2.3 DUAL POLARIZED PATCH ANTENNA	6
	1.3 PIFA ANTENNA	6
	1.3.1 WORKING OF PIFA	6
	1.3.2 USES OF PIFA	8
2	LITERATURE SURVEY	10
	2.1 INFERENCES	10
	2.2 EXISTING METHODOLOGY	11
	2.3 DRAWBACKS OF EXISTING MODEL	12
	2.4 PROPOSED METHODOLOGY	13
3	AIM AND SCOPE OF THE PROJECT	14
	3.1 EXISTING SYSTEMS AND LIMITATIONS	14
	3.2 PROPOSED WORK	16

	3.3 AIM OF THE PROJECT	18
	3.4 SCOPE OF PROPOSED WORK	20
	3.5 STANDARDS OF PROPOSED WORK	21
	3.6 CONSTRAINTS	23
	3.7 TRADE-OFFS	24
4	EXPERIMENTAL METHODS	26
	4.1 INTRODUCTION	26
	4.2 DESIGN PROCEDURE OF PIFA ANTENNA	28
	4.2.1 CHOICE OF SUBSTRATE MATERIAL	30
	4.2.2 DESIGN OF GROUND PLANE	31
	4.2.3 DESING OF THE PATCH	32
	4.2.4 FEEDING SYSTEM	
5	RESULTS AND DISCUSSION	34
	5.1 PIFA ANTENNA KEY PARAMETERS	34
	5.2 RESONANT FREQUENCY	34
	5.3 S - PARAMETER PLOT	35
	5.4 GAIN PLOT	36
	5.4.1 FACTORS AFFECTING GAIN	38
	5.5 PIFA DIRECTIVITY PLOT	38
	5.5.1 KEY FEATURES OF THE PLOT	39
	5.5.2 FACTORS AFFECTING DIRECTIVITY	39
	5.6 RADIATION PATTERN	40
	5.7 DISCUSSION	
6	CONCLUSION	43
	REFERENCES	45

LIST OF ABBREVIATIONS

PIFA	Planar Inverted F antenna
HFSS	High-Frequency Simulator System
CST	Computer Simulation Technology
WLAN	Wireless Local Area Network
FR4	Flame Retardant
MIC	Microwave Integrated Circuits
RFID	Radio Frequency Identification
MIMO	Multiple Input Multiple Output
LTE	Long Term Evolution
GNSS	Global Navigation Satellite System
GLONASS	Globalnaya Navigazionnaya Sputnikovaya Sistema
NFC	Near field communication
PCB	Printed circuit board
UWB	Ultra-Wideband
UMTS	Universal Mobile Telecommunication system
UHF	Ultra-high-frequency band
GSM	Global System for Mobile Communication
WIMAX	Worldwide Inter-operability for Microwave Access
ISM	Industrial, Scientific, and Medical
FEA	Finite element analysis
CFD	Computational fluid dynamics
EM	Electromagnetic
CAD	Computer-aided design

LIST OF FIGURES

FIGURE No.	TITLE	PAGE No.
1.2.1	Rectangular Patch Antenna	4
1.2.2	Circular Patch Antenna	4
1.2.3	Dual-Polarised Patch Antenna	5
1.3.1	PIFA Antenna	6
3.1	Existing PIFA Design	14
3.2	Proposed PIFA Design	16
4.1	Interface of the software	27
4.2	Design layout of PIFA antenna	30
4.2.1	Substrate	30
4.2.2	Ground	31
4.2.3	Patch	32
4.2.4	Layout of feedline	33
5.3	S - Parameter	36
5.4	Gain Plot	37
5.5	Directivity Plot	38
5.6	2D Radiation Pattern	40

LIST OF TABLES

TABLE No.	TITLE	PAGE No.
5.7	Comparison of Existing and Proposed Designs	41

CHAPTER-1

INTRODUCTION

Wireless communication systems have become ubiquitous in modern society, driving the demand for compact, efficient, and versatile antenna solutions. Among these solutions, Planar Inverted-F Antennas (PIFAs) have gained significant attention for their ability to meet the stringent requirements of various wireless applications. This project aims to conceptualize, design, and fabricate a PIFA operating at the resonant frequency of 5.8 GHz, catering to the growing need for high-frequency communication systems, particularly in Wi-Fi, WLAN, and other broadband wireless applications.

The proposed PIFA design integrates innovative array techniques to enhance performance and functionality, offering improved gain, directivity, and radiation characteristics compared to traditional single-element designs. Through meticulous optimization of antenna dimensions, substrate properties, and array configurations, the design aims to achieve optimal performance metrics such as gain, bandwidth, and radiation efficiency, making it suitable for a wide range of wireless communication applications.

The selection of 5.8 GHz as the operating frequency aligns with the increasing demand for high-speed data transmission and bandwidth-intensive applications. By resonating at this frequency, the antenna ensures compatibility with existing wireless networks and emerging technologies, facilitating seamless integration and interoperability. Key considerations in the design process include substrate selection, where FR4 material is chosen for its favourable dielectric properties, mechanical robustness, and cost-effectiveness. The dielectric constant and loss tangent of FR4 is carefully considered to ensure efficient energy transfer and minimal signal attenuation, particularly at higher frequencies like 5.8 GHz.

The project scope encompasses comprehensive research, simulation, optimization, and experimental validation processes. Advanced electromagnetic simulation software such as HFSS will be utilized to model and optimize the antenna design, while laboratory testing will validate performance metrics under real-world conditions. Manufacturing considerations, including compatibility with standard PCB fabrication

processes, will ensure cost-effective and scalable production of the antenna design. Performance optimization will be a focal point, with a particular emphasis on key parameters such as gain, bandwidth, radiation efficiency, and impedance matching. Through iterative design iterations and sensitivity analyses, the project aims to address performance bottlenecks and tailor the antenna design to meet specific application requirements.

Documentation and reporting will play an integral role, capturing the entire design process and disseminating project outcomes through technical reports, presentations, and possibly academic publications. By achieving its objectives, this project seeks to contribute to advancements in antenna engineering and wireless communication systems, empowering users with seamless and reliable connectivity in the 5.8 GHz frequency band.

1.1 MICROSTRIP PATCH ANTENNA

Microstrip patch antennas are a popular choice in wireless communication systems due to their compact size, low profile, light weight, and ease of integration with microwave integrated circuits (MICs). These antennas consist of a metallic patch, typically made of copper or gold, printed on a dielectric substrate, which is usually a low-loss material like FR4 or Rogers substrate. The patch is usually fed by a coaxial cable or a microstrip transmission line, and it radiates electromagnetic waves into free space.

The design and performance of microstrip patch antennas depend on various parameters, including the dimensions of the patch, substrate material properties, feeding techniques, and the ground plane configuration. The resonant frequency of the antenna is primarily determined by the size of the patch and the dielectric constant of the substrate. By adjusting these parameters, the antenna can be tuned to operate at a specific frequency or within a certain bandwidth.

One of the key advantages of microstrip patch antennas is their versatility in terms of shape and configuration. They can be designed in various shapes such as square, rectangular, circular, or even more complex geometries to suit specific application requirements. Additionally, multiple patches can be arranged in an array configuration to achieve desired radiation characteristics, such as beam steering or pattern shaping.

Despite their advantages, microstrip patch antennas also suffer from some limitations. One common issue is their narrow bandwidth, especially for single-patch designs. Techniques such as using stacked or parasitic patches, or employing metamaterial structures, can help widen the bandwidth. Another challenge is achieving high radiation efficiency, especially when operating in higher frequency bands. Careful design optimization and proper matching techniques are essential to overcome these challenges.

Microstrip patch antennas find applications in various fields such as satellite communication, mobile communication, radar systems, wireless sensor networks, and RFID systems. Their compact size and compatibility with modern fabrication techniques make them suitable for integration into portable devices, smart antennas, and phased array systems. Ongoing research in materials, design methodologies, and fabrication techniques continues to improve the performance and versatility of microstrip patch antennas, ensuring their relevance in future wireless communication systems.

1.2 TYPES OF MICROSTRIP PATCH ANTENNA

1.2.1 Rectangular Microstrip Patch Antenna

Rectangular microstrip patch antennas feature a straightforward design with a rectangular metallic patch mounted on a dielectric substrate. Known for their ease of fabrication, these antennas are commonly used in various communication systems such as Wi-Fi, Bluetooth, RFID, and satellite communication. Their compact size and omnidirectional radiation pattern make them suitable for applications where space is limited and wide coverage is desired. Construction typically involves a rectangular metallic patch, often made of copper or gold, printed on a dielectric substrate like FR4 or Rogers material. Fabrication techniques such as photolithography and etching are employed to manufacture these antennas on printed circuit boards (PCBs) or specialized substrates.

They serve as integral components in various applications, including but not limited to Wi-Fi routers, Bluetooth devices, RFID systems, satellite communication, and mobile devices such as smartphones and tablets. In Wi-Fi routers and access points, rectangular patch antennas facilitate wireless internet connectivity by transmitting and

receiving signals to and from connected devices within a network, ensuring seamless data transfer and internet access.




Fig: 1.2.1 Rectangular Patch Antenna

1.2.2 Circular Microstrip Patch Antenna:

Circular microstrip patch antennas feature a circular or annular metallic patch mounted on a dielectric substrate. They offer advantages such as reduced edge effects, improved bandwidth, and sometimes enhanced radiation patterns compared to rectangular patches. These antennas find applications in satellite communication, GPS systems, mobile devices, and other scenarios where circular polarization or specific radiation patterns are desired. Construction involves a metallic patch printed on a dielectric substrate, carefully designed to resonate at the desired frequency. Fabrication techniques such as photolithography and etching are utilized for precise manufacturing on PCBs or specialized substrates.




Fig: 1.2.2 Circular Patch Antenna

1.2.3 Dual-Polarized Microstrip Patch Antenna

Dual-polarized microstrip patch antennas are engineered to transmit and receive signals in both horizontal and vertical polarizations simultaneously. They offer advantages such as improved data throughput and reliability in wireless communication systems employing MIMO technology. Commonly used in MIMO systems for various wireless communication networks, including cellular networks, Wi-Fi, LTE, and 5G, they are particularly beneficial in environments with high multipath propagation and interference. Construction typically involves two sets of orthogonal radiating elements on the same substrate, carefully designed for proper isolation and impedance matching. Fabrication techniques such as photolithography and etching are used for precise manufacturing on PCBs or specialized substrates.




Fig: 1.2.3 Dual-Polarised Patch Antenna

Microstrip patch antennas come in various types, each serving specific applications and performance requirements. Whether it's the simplicity of rectangular patches, the bandwidth advantages of circular patches, or the versatility of dual-polarized designs, microstrip patch antennas offer a compact, efficient, and adaptable solution for modern wireless communication systems.

This antenna configuration offers significant advantages in terms of increased data throughput, improved spectral efficiency, and enhanced reliability in wireless communication systems, particularly those employing Multiple Input Multiple Output (MIMO) technology.

Their ability to transmit and receive signals in two orthogonal polarizations simultaneously makes them well-suited for a wide range of applications, including cellular networks, Wi-Fi, MIMO systems, radar systems, and satellite communication.

1.3 PIFA ANTENNA

1.3.1 Working of PIFA antenna

Planar Inverted-F Antennas (PIFAs) represent a crucial component of wireless communication systems due to their compactness, versatility, and efficiency. Characterized by their low-profile design, PIFAs find widespread application in various electronic devices, particularly in mobile devices like smartphones, tablets, and wearables. Their omnidirectional radiation pattern ensures coverage in multiple directions without the need for mechanical adjustment, making them ideal for use in devices where space constraints are prevalent. The construction of a PIFA typically involves a radiating element, a ground plane, and a feed structure, all integrated into the device's printed circuit board (PCB) or chassis. While PIFAs offer advantages such as compact size, low profile, and versatility in frequency operation, they may face challenges related to bandwidth, efficiency, and mutual coupling in devices with multiple antennas. Nonetheless, PIFAs continue to play a significant role in enabling wireless connectivity in modern electronic devices, facilitating seamless communication in a wide range of applications from mobile telecommunications to Internet of Things (IoT) devices and beyond.




Fig: 1.3.1 PIFA antenna

The Planar Inverted-F Antenna (PIFA) operates based on the principles of electromagnetism to transmit and receive electromagnetic waves efficiently. The

functionality of a PIFA involves the interaction of its key components: the radiating element, ground plane, and feed structure.

At its core, the radiating element of a PIFA is a conductive structure typically shaped as an inverted-F, positioned parallel to the ground plane. This radiating element is designed to resonate at the desired operating frequency, which is determined by its physical dimensions and the dielectric properties of the surrounding materials. When an alternating current is applied to the feed structure, electromagnetic fields are generated in the radiating element.

The ground plane beneath the radiating element serves as a reference point and contributes to the antenna's performance by shaping the radiation pattern. It provides a reflective surface against which the electromagnetic waves emitted by the radiating element are reflected and re-radiated, thereby enhancing the antenna's efficiency. The ground plane also helps in achieving a balanced impedance matching and reducing losses in the antenna system.

The feed structure of a PIFA facilitates the transmission and reception of electromagnetic signals between the antenna and the external circuitry. This feed structure can take various forms, such as microstrip lines or coaxial cables, depending on the specific design requirements and application needs. It ensures that the electromagnetic energy is efficiently transferred to and from the radiating element, enabling the antenna to transmit and receive signals effectively.

The working of a PIFA involves the interplay of these components to generate electromagnetic waves that propagate through the surrounding medium. As the alternating current flows through the feed structure and into the radiating element, electromagnetic fields are established, leading to the emission of electromagnetic waves into space. The geometry and dimensions of the radiating element, as well as its proximity to the ground plane, influence the radiation pattern and efficiency of the antenna.

PIFA revolves around the efficient generation and propagation of electromagnetic waves through its radiating element, in conjunction with the ground plane and feed structure. By carefully designing and optimizing these components, PIFAs can achieve

high performance and reliability in wireless communication systems, making them indispensable components in modern electronic devices.

1.3.2 Uses of PIFA in mobile communication

Planar Inverted-F Antennas (PIFAs) play a crucial role in mobile communication due to their compact size, low profile, and efficiency. They are extensively used in mobile devices such as smartphones, tablets, and wearables to facilitate wireless connectivity across various communication standards. In mobile communication, PIFAs serve multiple essential functions:

Firstly, PIFAs enable cellular communication by providing antennas for transmitting and receiving signals in mobile networks. They support multiple frequency bands used by different cellular technologies such as GSM, 3G, 4G LTE, and 5G. PIFAs are designed to resonate at these specific frequencies, ensuring optimal performance and coverage in diverse network environments.

Secondly, PIFAs enable wireless internet connectivity, commonly known as Wi-Fi, in mobile devices. They are utilized as antennas for Wi-Fi modules, allowing users to access high-speed internet networks in homes, offices, public spaces, and Wi-Fi hotspots. PIFAs facilitate seamless data transmission and reception, enhancing the user experience in accessing online services, streaming multimedia content, and engaging in online communication.

Moreover, PIFAs support Bluetooth connectivity in mobile devices, enabling short-range wireless communication for various applications such as hands-free calling, wireless audio streaming, file sharing, and device pairing. PIFAs serve as antennas for Bluetooth modules, ensuring reliable communication between devices with minimal interference and power consumption.

Additionally, PIFAs facilitate Global Navigation Satellite System (GNSS) reception in mobile devices, including GPS, Galileo, GLONASS, and BeiDou. They serve as antennas for GPS receivers, enabling accurate positioning, navigation, and location-based services such as mapping, navigation apps, and location tracking.

Furthermore, PIFAs support Near Field Communication (NFC) functionality in mobile devices, enabling secure contactless transactions, data exchange, and device pairing.

PIFAs serve as antennas for NFC modules, allowing users to make payments, access digital content, and interact with NFC-enabled devices with ease.

PIFAs play a vital role in mobile communication by enabling cellular connectivity, Wi-Fi access, Bluetooth pairing, GNSS reception, and NFC functionality in mobile devices. Their compact design, efficient performance, and versatility make them indispensable components in modern smartphones, tablets, and wearables, contributing to seamless wireless communication experiences for users worldwide.

In the realm of mobile communication, Planar Inverted-F Antennas (PIFAs) play a multifaceted role, offering diverse functionalities tailored to the demands of modern mobile devices. These antennas are pivotal in facilitating cellular connectivity, enabling seamless voice and data transmission across various frequency bands utilized by cellular networks. Beyond cellular communication, PIFAs are instrumental in providing Wi-Fi connectivity, allowing users to access high-speed internet networks in both public and private settings. Moreover, they contribute to the integration of Bluetooth technology, supporting short-range wireless communication for tasks such as file sharing, audio streaming, and device pairing.

Additionally, PIFAs enable Global Navigation Satellite System (GNSS) reception, empowering users with accurate positioning, navigation, and location-based services essential for applications like mapping and navigation apps. Furthermore, these antennas facilitate Near Field Communication (NFC) functionalities, enabling contactless transactions, data exchange, and interaction with NFC-enabled devices. In essence, PIFAs serve as indispensable components in mobile communication systems, providing a foundation for reliable connectivity, enhanced functionality, and seamless user experiences across a myriad of wireless applications and mobile devices.

Moreover, PIFAs facilitate Near Field Communication (NFC) capabilities, allowing users to make secure contactless transactions, exchange data, and interact with NFC-enabled devices. In essence, the widespread adoption of PIFAs in mobile communication underscores their importance in ensuring reliable connectivity, enhanced functionality, and seamless user experiences across a diverse range of wireless applications and devices.

CHAPTER-2

LITERATURE SURVEY

2.1 INFERENCES

The collection of research papers presents a comprehensive exploration of Planar Inverted-F Antennas (PIFAs) and their applications across various fields, including wireless communications, mobile devices, smart glasses, and biomedical telemetry. Each paper offers unique insights and innovations, addressing specific challenges and requirements within its respective domain. Hamza ben Hamadi et al. focus on designing a multi-band PIFA antenna suitable for modern wireless communication standards, emphasizing compactness and versatility. Their work aims to enhance signal quality and coverage across Wi-Fi/Bluetooth, 4G LTE, and WLAN.

Another paper by Dalia Mohammed Nashaat and Hala A. Elsadek introduces a single-feed compact quad-band PIFA antenna, demonstrating techniques for size reduction while maintaining performance. This antenna offers efficiency across four distinct frequency bands, catering to diverse wireless communication applications. Saad Wasmi Luhaib et al. delve into dual-band PIFA antenna design for GSM systems, optimizing resonance frequencies to cover GSM900 and GSM1900 bands. Their research targets miniaturization, omni-directional radiation, and wide impedance bandwidth, essential for mobile handset applications.

Additionally, research by Ziyang Huang et al. explores implantable biotelemetry antennas, leveraging PIFAs for miniaturization and performance enhancement within the MICS band. Their work contributes to improved data transmission and reception in biomedical applications. Moreover, Giovanni Andrea Casula and Giorgio Montisci propose design criteria to reduce the human body effect on wearable PIFA antennas, aiming for robustness and optimal performance in UHF band applications. Their approach, guided by energy density profiles, offers a promising strategy for wearable antenna design.

These papers collectively advance the understanding and implementation of PIFA technology across a spectrum of applications, showcasing its versatility, efficiency, and potential for innovation in wireless communication systems, mobile devices, wearables, and biomedical telemetry.

2.2 EXISTING METHODOLOGY

The existing methodology for this paper encompasses the design and simulation of a novel Planar Inverted-F Antenna (PIFA) configuration tailored for dual-band operation in GSM and WiMAX systems. The proposed antenna structure comprises short-circuit planes, a folded radiating element, and horizontal arms, strategically arranged to facilitate efficient operation within the desired frequency bands. Simulation using HFSS software demonstrates bi-band operation with resonant frequencies at 0.991/1.026 GHz and 3.697/3.488 GHz, validating the antenna's potential for dual-band functionality. However, the paper acknowledges several limitations, including potential bandwidth constraints, isolation and interference issues between GSM and WiMAX bands, and challenges in impedance matching and tuning.

Additionally, concerns about radiation efficiency, physical constraints, environmental sensitivity, manufacturability, and cost are noted. By acknowledging these limitations, the paper lays the groundwork for future research aimed at optimizing the proposed PIFA design and addressing identified challenges to enhance its performance and applicability in dual-band communication systems. The design process involves detailed consideration of antenna components' dimensions and arrangement to achieve desired resonant frequencies and radiation characteristics in both bands.

Electromagnetic simulation software such as HFSS and IE3D is employed to simulate the PIFA structure and analyse its bi-band operation. Simulation results indicate resonant frequencies within the GSM and WiMAX bands, validating the antenna's suitability for dual-band operation. However, the paper acknowledges several limitations, including potential bandwidth constraints, isolation and interference issues, and concerns about radiation efficiency and impedance matching. Future research directions are suggested to address these limitations, paving the way for enhancing the antenna's performance and practical applicability in dual-band communication systems. These limitations include potential bandwidth constraints, isolation and interference issues between GSM and WiMAX bands, concerns about challenges in impedance matching and tuning, physical constraints on antenna performance. By recognizing these limitations, the paper sets the stage for future research efforts aimed at optimizing the proposed PIFA design and addressing the identified challenges to enhance its performance and applicability in dual-band communication systems.

2.3 DRAWBACKS OF EXISTING DESIGN

The project presents a promising endeavour in the realm of antenna design for wireless communications, it is essential to recognize and address its potential drawbacks. One notable limitation lies in the reliance on simulation software for validating the proposed PIFA antenna's performance. While simulation results indicate bi-band operation within the GSM and WiMAX frequency bands, there is a need for comprehensive experimental validation to ensure real-world applicability and performance consistency. Additionally, the paper acknowledges concerns regarding potential bandwidth constraints, isolation, and interference issues between the GSM and WiMAX bands. These challenges could hinder the antenna's ability to effectively accommodate wider frequency ranges or adjacent frequency bands, impacting its overall utility in dual-band communication systems. Furthermore, the complexity of impedance matching and tuning in the compact PIFA design raises questions about practical implementation and manufacturability. Addressing these drawbacks through rigorous experimental validation, optimization of design parameters, and consideration of practical constraints will be crucial for realizing the full potential of the proposed PIFA antenna in meeting the demands of modern wireless communication systems.

In addressing the potential drawbacks of the project, it becomes evident that thorough experimental validation, optimization of design parameters, and consideration of practical constraints are paramount. While simulation software like HFSS and IE3D offers valuable insights, the discrepancies between simulated and real-world performance need to be mitigated through rigorous experimental validation. This validation process should be detailed to instil confidence in the antenna's actual performance, especially in dynamic and real-world scenarios. Additionally, addressing concerns about bandwidth limitations, isolation, and interference between frequency bands is crucial to ensure optimal communication reliability. Challenges in achieving impedance matching and tuning across both GSM and WiMAX bands highlight the need for careful optimization and consideration of manufacturing costs and feasibility. Overall, overcoming these drawbacks requires a comprehensive approach that integrates experimental validation, optimization strategies, and considerations of practical constraints to enhance the proposed PIFA antenna's performance and applicability in dual-band communication systems.

2.4 PROPOSED METHODOLOGY

The proposed methodology for designing the Planar Inverted-F Antenna (PIFA) with an array technique involves several key steps to ensure optimal performance and functionality. Firstly, the antenna structure is meticulously designed with specific dimensions tailored for resonance at 5.8 GHz. These dimensions, including length, width, and substrate height, are calculated based on the desired resonant frequency and substrate properties. The choice of substrate material, such as FR4, is critical for achieving favourable electrical properties, ease of manufacturability, and cost-effectiveness. The antenna features two F-shaped patches strategically positioned on the substrate to optimize impedance matching, radiation pattern, and bandwidth. Configuring the PIFA antenna as an array further enhances gain, directivity, and radiation pattern control compared to a single-element antenna.

The spacing between the array elements is carefully determined to ensure constructive interference and enhanced performance. Additionally, a T-junction power divider is employed to supply power to both elements in the array, ensuring equal power distribution and balanced radiation characteristics. Design considerations for the power divider include efficient power transfer, impedance matching, and isolation techniques to minimize losses and reflections. Following extensive simulation and optimization using electromagnetic simulation software like HFSS, the antenna design undergoes experimental validation to verify its performance in real-world conditions.

Measurements are conducted to validate key parameters such as return loss, radiation pattern, and gain, ensuring that the antenna meets the specified requirements. Overall, the proposed methodology aims to deliver a sophisticated and efficient PIFA antenna design capable of achieving enhanced performance and functionality for various wireless communication applications operating in the 5.8 GHz frequency band, such as Wi-Fi, WLAN, and some 5G applications. This design consideration encompasses efficient power transfer, impedance matching, and isolation techniques to minimize losses and reflections within the power distribution network. Extensive electromagnetic simulation and optimization using tools like HFSS are employed to fine-tune the antenna's parameters, and subsequent experimental validation verifies its performance in real-world conditions.

CHAPTER-3

AIM AND SCOPE OF THE PROJECT

3.1 EXISTING MODEL AND LIMITATIONS

This project aims to introduce novel Planar Inverted-F Antenna (PIFA) designs suitable for GSM and WiMAX systems. Figure 5 illustrates the configuration of the PIFA antenna proposed for operation in two bands. The structure comprises two short-circuit planes with dimensions of 7 x 5 mm, a radiating element folded downwards with a height of 5 mm, and two horizontal arms with dimensions of 7 x 3 mm. This design is intended to facilitate dual-band operation, allowing the antenna to efficiently operate within the frequency bands allocated for GSM and WiMAX communication standards. By leveraging this innovative PIFA configuration, the antenna offers potential advantages such as compact size, good radiation characteristics, and compatibility with multiple wireless communication systems which are useful to overcome real world challenges.




Fig: 3.1 Existing PIFA design

The PIFA structure simulation by HFSS gives a Bi-band antenna operating at two resonant frequencies 0.991 and 3.697 GHz. The first return loss for the frequency 0.991 GHz has a peak lower at -18 dB and the second for the frequency 3.697 GHz goes down until -17 dB value. We almost found the same results by IE3D, with peaks of 22.5dB and -30dB appearing at the frequencies 1.026 GHz and 3.488 GHz respectively. These results translate a very good adaptation of the antenna.

While the simulation results for the bi-band Planar Inverted-F Antenna (PIFA) model are promising, there are several limitations that should be considered:

Bandwidth Limitations: The antenna's bandwidth may be limited, particularly at the resonance frequencies of 0.991/1.026 GHz and 3.697/3.488 GHz. This limitation could impact the antenna's ability to accommodate wider frequency ranges or adjacent frequency bands within the GSM and WiMAX spectrums.

Isolation and Interference: The proximity of the antenna's radiating elements and the arrangement of its components may lead to decreased isolation between the antenna ports. This could result in increased coupling and interference between the GSM and WiMAX bands, potentially degrading performance in dual-band operation.

Radiation Efficiency: The compact size and design intricacies of the PIFA antenna may compromise its radiation efficiency, especially at specific frequencies within the GSM and WiMAX bands. Lower radiation efficiency could affect the antenna's ability to transmit and receive signals effectively, particularly in environments with high attenuation or noise.

Matching and Tuning Challenges: Achieving optimal impedance matching across both GSM and WiMAX bands may be challenging due to the antenna's compact size and dual-band operation requirements. Fine-tuning and optimization of matching networks may be necessary to improve overall performance, which could increase design complexity and implementation costs.

Physical Constraints: The physical dimensions and arrangement of the antenna components, such as the short-circuit planes and radiating elements, may impose limitations on achievable bandwidth, radiation pattern, and gain. These constraints could restrict the antenna's versatility and applicability in different operating environments or deployment scenarios.

Environmental Sensitivity: The performance of the PIFA antenna may be sensitive to variations in environmental conditions, such as nearby metallic objects, surrounding structures, or changes in antenna orientation. These factors could introduce additional challenges in maintaining stable performance across both GSM and WiMAX bands, particularly in dynamic or unpredictable environments.

Manufacturability and Cost: The complexity of the antenna design and the need for precise fabrication techniques may increase manufacturing costs and pose challenges in mass production. Any manufacturing imperfections or variations could affect the antenna's performance consistency and reliability.

3.2 PROPOSED DESIGN

Our proposed Planar Inverted-F Antenna (PIFA) design utilizing an array technique presents an innovative approach to achieve enhanced performance and functionality. For a Planar Inverted-F Antenna (PIFA) designed for resonance at 5.8 GHz, the antenna's structure and dimensions would be specifically tailored to achieve resonance at this frequency. Here's a detailed description of the design:

Antenna Structure:




Fig: 3.2 Proposed PIFA design

Dimensions: The PIFA antenna is designed with a length of 50mm, a width of 40mm, and a substrate height of 0.8mm. The physical dimensions of the antenna elements, such as the length, width, and height, are adjusted to ensure resonance at 5.8 GHz. The dimensions are typically calculated based on the desired resonant frequency, substrate properties, and other factors. These dimensions are carefully chosen to resonate at the desired operating frequencies and to provide mechanical stability.

Substrate Material: The antenna is fabricated on a substrate with a height of 0.8mm. The choice of substrate material plays a crucial role in determining the antenna's

performance, including its impedance matching, bandwidth, and radiation efficiency. using FR4 material as the substrate for a PIFA antenna designed to resonate at 5.8 GHz offers several advantages, including favourable electrical properties, ease of manufacturability, and cost-effectiveness. By carefully considering the dielectric properties, thickness, and manufacturing constraints of the FR4 substrate, designers can optimize the antenna design to achieve optimal performance and functionality for various wireless communication applications.

F-Shaped Patch: The antenna features two F-shaped patches positioned on the substrate. The F-shaped patches are strategically designed to optimize the antenna's impedance matching, radiation pattern, and bandwidth. These patches serve as the radiating elements of the antenna.

Array Configuration: The PIFA antenna is configured as an array, consisting of two F-shaped patches arranged in a specific layout on the substrate. The array configuration enables improved gain, directivity, and radiation pattern control compared to a single-element PIFA.

Element Spacing: The spacing between the two F-shaped patches is carefully determined based on the desired radiation characteristics and operating frequency. Optimal spacing ensures constructive interference between the elements, resulting in enhanced performance.

T-Junction Power Divider: A T-junction power divider is employed to supply power to both PIFA elements in the array. This power divider ensures equal power distribution to each element, enabling symmetrical operation and balanced radiation characteristics.

Design Considerations: The design of the T-junction power divider is critical to ensure efficient power transfer and impedance matching. Careful impedance matching and isolation techniques are employed to minimize power losses and reflections within the power distribution network.

Simulation and Optimization: The proposed PIFA antenna design is extensively simulated and optimized using electromagnetic simulation software such as HFSS.

Simulation results are used to fine-tune the antenna's parameters, including dimensions, substrate properties, and array configuration, to achieve desired performance metrics such as gain, bandwidth, and radiation pattern.

Experimental Validation: Following simulation and optimization, the antenna design undergoes experimental validation to verify its performance in real-world conditions. Measurements are conducted to validate key parameters such as return loss, radiation pattern, and gain, ensuring that the antenna meets the specified requirements.

In summary, our proposed PIFA antenna design utilizing an array technique offers a sophisticated and efficient solution for achieving enhanced performance and functionality. By carefully optimizing the antenna's dimensions, substrate properties, array configuration, and power distribution network, the design aims to deliver improved gain, directivity, and radiation characteristics, making it well-suited for various wireless communication applications.

By carefully considering these factors and optimizing the antenna design, a Planar Inverted-F Antenna (PIFA) can be successfully designed to resonate at 5.8 GHz, making it suitable for various wireless communication applications operating in the 5.8 GHz frequency band, such as Wi-Fi, WLAN, and some 5G applications.

3.3 AIM OF THE PROJECT

The primary objective of this project is to conceptualize, design, and fabricate a Planar Inverted-F Antenna (PIFA) operating at the resonant frequency of 5.8 GHz. The design process encompasses a multifaceted approach focusing on achieving optimal performance, manufacturability, and applicability to specific wireless communication applications.

Frequency Specification: The selection of 5.8 GHz as the operating frequency is strategic, aligning with the demand for high-frequency communication systems, particularly in the context of Wi-Fi, WLAN, and other broadband wireless applications.

The antenna's resonance at this frequency ensures compatibility with existing wireless networks and emerging technologies, fostering seamless integration and interoperability.

Performance Optimization: The design aims to optimize key performance parameters such as gain, bandwidth, radiation efficiency, and impedance matching. Through careful tuning of antenna dimensions, substrate properties, and feed mechanism, the goal is to achieve high gain and directive radiation patterns to enhance signal strength and coverage while minimizing interference and signal degradation.

Substrate Selection: FR4 material is chosen as the substrate for its favourable dielectric properties, mechanical robustness, and cost-effectiveness. The dielectric constant and loss tangent of FR4 is taken into account to ensure efficient energy transfer and minimal signal attenuation, especially at higher frequencies like 5.8 GHz.

Size and Form Factor: The antenna design prioritizes compactness and versatility to accommodate integration into various electronic devices, ranging from smartphones and tablets to IoT devices and wireless routers. Consideration is given to the antenna's physical dimensions, weight, and form factor to facilitate seamless integration and deployment in space-constrained environments.

Manufacturability: The design is optimized for compatibility with standard PCB fabrication processes, enabling cost-effective and scalable manufacturing. By leveraging existing manufacturing techniques and materials, the aim is to streamline production while maintaining high quality and consistency in antenna performance.

Simulation and Validation: Electromagnetic simulation software such as HFSS or CST Microwave Studio is utilized to model and simulate the antenna design. Simulated results are rigorously validated through experimental testing and measurements to ensure accuracy and reliability in real-world operating conditions.

Application Specific Requirements: The antenna design is tailored to meet the specific requirements and constraints of target applications, such as radiation pattern, polarization, and environmental robustness. Customization options are explored to address the unique needs of diverse applications, ranging from indoor wireless networks to outdoor point-to-point links and beyond.

By achieving these aims, the project seeks to deliver a state-of-the-art PIFA antenna solution that not only meets but exceeds the performance expectations of modern wireless communication systems operating at 5.8 GHz. Through innovation, optimization, and meticulous attention to detail, the project aims to contribute to

advancements in wireless technology and connectivity, empowering users with seamless and reliable communication capabilities.

3.4 SCOPE OF THE PROJECT

The project aims to design and optimize a Planar Inverted-F Antenna (PIFA) for operation at 5.8 GHz, targeting applications in wireless communication systems, IoT devices, and radar systems. Extensive research will be conducted to explore various PIFA antenna designs and array configurations suitable for resonance at 5.8 GHz. This investigation will encompass factors such as patch dimensions, substrate properties, feeding techniques, and ground plane configurations to optimize antenna performance metrics including gain, bandwidth, and radiation efficiency.

A critical aspect of the project involves the selection and characterization of the substrate material. Dielectric substrates such as FR4, Rogers, and others will be evaluated based on their dielectric constant, loss tangent, thermal properties, and cost-effectiveness. Through laboratory testing and analysis, the selected substrate material will be validated for suitability in high-frequency applications and compatibility with standard fabrication processes.

Manufacturability and scalability are key considerations in the project scope. The antenna design will be assessed for its manufacturability, repeatability, and cost-effectiveness. Fabrication processes for prototype antennas will be developed utilizing standard PCB manufacturing techniques such as photolithography, etching, and soldering. Multiple prototypes will be fabricated to validate the design concept and evaluate performance variations arising from manufacturing tolerances.

Simulation and validation play a crucial role in verifying the antenna design's performance. Advanced electromagnetic simulation software such as HFSS, CST Microwave Studio, or FEKO will be utilized to model the antenna's electromagnetic behavior and performance characteristics. Validation of simulation results will be carried out through comparative analysis with measured data obtained from laboratory testing using calibrated test equipment. Performance evaluations will encompass radiation patterns, impedance matching, power handling, and temperature stability tests under various operating conditions.

The project will focus on performance evaluation and optimization to achieve desired specifications and meet project objectives. Comprehensive evaluations will include frequency sweep tests, power handling tests, and temperature stability tests. Performance bottlenecks will be identified through sensitivity analysis and parametric studies, guiding iterative optimization of the antenna design. Application-specific considerations, including interference mitigation, multi-band operation, and environmental resilience, will be addressed through design modifications and optimizations tailored to specific application requirements.

Documentation and reporting are integral components of the project scope. A detailed documentation process will capture the entire design process, including specifications, simulation setups, experimental procedures, and measurement results. Comprehensive technical reports will be prepared, detailing the project methodology, findings, conclusions, and recommendations. Project outcomes will be disseminated through technical presentations, conference papers, and possibly academic publications, contributing to the body of knowledge in antenna engineering and wireless communication systems.

3.5 STANDARDS OF THE PROPOSED WORK

The proposed work on the simulation of PIFA antennas for mobile communication offers several notable advantages like

Terahertz Operation: The project specifically targets the efficient operation of PIFA antennas within the terahertz frequency bands, a critical aspect in aligning antenna technology with the anticipated requirements of 6G networks.

Future-Proofing: By addressing the challenges associated with higher frequencies, the proposed work contributes to future-proofing wireless communication systems, ensuring compatibility with evolving technological landscapes.

Optimized Antenna Structure: The project aims to optimize the design parameters, including the substrate material and antenna dimensions, to mitigate signal loss effectively. This involves a meticulous examination of dielectric properties and feed mechanisms to ensure efficient power transfer.

Reliability in Communication: By reducing signal loss, the proposed work enhances the reliability of communication, a critical factor in ensuring seamless connectivity in advanced wireless networks.

Omnidirectional Characteristics: The optimization of radiation patterns includes efforts to achieve desired omnidirectional characteristics. This is essential for ensuring that the antenna can effectively transmit and receive signals in a 360-degree coverage, catering to the diverse scenarios encountered in 6G networks.

Efficient Signal Propagation: Achieving optimized radiation patterns contributes to efficient signal propagation, enhancing the antenna's overall performance in diverse communication environments.

Compact Design: The project acknowledges the inherent size constraints of PIFA antennas. By carefully balancing these constraints with the need for efficient radiation, the aim is to achieve a compact design without compromising on performance.

Space-Efficient Solutions: Balancing size constraints ensures that the antennas can be integrated into various devices and systems without occupying excessive space, making them more practical for real-world applications.

Advanced simulation tools: The use of advanced simulation tools, such as ANSYS HFSS, provides a sophisticated platform for modelling and analysing antenna behaviour. This allows for a detailed examination of electromagnetic interactions, aiding in the accurate representation and optimization of the antenna's performance.

Comprehensive Analysis: Advanced simulation tools enable a comprehensive analysis of various design parameters, allowing engineers to visualize electric and magnetic fields, study power distribution, and explore the impact of different configurations on antenna behaviour.

The planar nature of PIFAs facilitates seamless integration with other components on a printed circuit board. This ease of integration simplifies overall circuit design and assembly processes.

Contribution to 6g technology: Innovative Antenna Solutions: The proposed work positions itself as a contribution to the broader advancement of 6G technology by introducing innovative solutions to specific challenges in antenna design.

Enabling Next-Generation Connectivity: By addressing key aspects of antenna performance, the project aims to contribute to the development of antennas that play a vital role in enabling the next generation of wireless connectivity, meeting the demands of 6G networks.

Compact size and low profile: The planar design of PIFAs allows for a smaller footprint and reduced weight compared to three-dimensional antennas like dipoles or parabolas. This makes PIFAs ideal for applications where space is at a premium, such as in modern mobile devices, compact embedded systems, and wearable electronics. The reduced size also contributes to improved aesthetics and ease of integration into various devices.

Low fabrication cost: PIFAs are cost-effective to manufacture due to their simple structure and the utilization of printed circuit board (PCB) technology. The manufacturing process is streamlined, making mass production economically viable. The use of readily available materials and standard manufacturing techniques further contributes to the cost-effectiveness of PIFAs.

Wide bandwidth: PIFAs can be designed to operate over a wide range of frequencies, offering versatility in applications. This makes them suitable for diverse communication systems, including Wi-Fi, Bluetooth, and RFID.

The advantages of the proposed work collectively position it as a significant endeavour in advancing antenna technology, ensuring compatibility with evolving network architectures, and fostering the development of efficient, reliable, and forward-looking PIFA antennas for 6G wireless networks.

3.6 CONSTRAINTS

Size Limitations: Developing miniature PIFA antennas imposed stringent constraints on physical dimensions to ensure compatibility with mobile and wireless devices. These size limitations were dictated by factors such as device form factor, available space for antenna integration, and aesthetics. Achieving optimal performance within these size constraints posed significant challenges, as smaller antennas often exhibit reduced radiation efficiency and coverage range.

Multi-band Operation Requirements: Meeting the demands of multiple telecommunications standards necessitated antennas capable of operating across several frequency bands. This constraint introduced complexity into the design process, as each frequency band required specific impedance matching, radiation pattern control, and bandwidth optimization. The challenge lay in designing antennas capable of efficient operation across diverse frequency ranges while maintaining compact form factors and adhering to performance specifications.

Simulation Software Limitations: While HFSS provided advanced electromagnetic simulation capabilities, its use also presented constraints in terms of computational resources and simulation time. Complex antenna designs and multi-band operation required extensive simulation iterations, which often demanded significant computational resources and time. Managing simulation complexity, accuracy, and runtime became crucial to ensure timely completion of the design process within project constraints.

Integration and Manufacturability Considerations: Antenna designs had to seamlessly integrate into existing device architectures and manufacturing processes while meeting performance specifications. Constraints related to material selection, fabrication techniques, and antenna placement within devices influenced design decisions to ensure manufacturability without compromising performance. Balancing performance requirements with integration constraints was essential to facilitate smooth integration into mobile and wireless devices.

3.7 TRADE OFFS

Size vs. Performance: Balancing size constraints with performance objectives, such as gain and bandwidth, necessitated trade-offs in antenna design. Shrinking antenna size to meet compact form factor requirements often resulted in compromises in radiation efficiency and coverage range. Design optimizations aimed to maximize performance within limited space while minimizing size-related trade-offs.

Complexity vs. Multi-band Operation: Designing antennas for multi-band operation introduced complexity, requiring intricate tuning and adjustment of antenna parameters for each frequency band. Trade-offs between antenna complexity,

fabrication cost, and design optimization efforts were inevitable in achieving performance across multiple bands. Simplifying antenna designs while maintaining multi-band functionality was crucial to strike a balance between complexity and performance.

Simulation Accuracy vs. Efficiency: Trade-offs between simulation accuracy, computational efficiency, and simulation time had to be managed effectively. Optimizing simulation settings and balancing computational resources with simulation accuracy were critical for efficient design iterations and timely project completion. Striking a balance between simulation accuracy and efficiency enabled accurate prediction of antenna performance while minimizing computational overhead.

Performance vs. Integration: Ensuring optimal antenna performance while meeting integration and manufacturability constraints required trade-offs in material selection, fabrication techniques, and antenna placement within devices. Achieving seamless integration into mobile and wireless devices necessitated compromises in performance to accommodate integration constraints. Balancing performance

CHAPTER-4

EXPERIMENTAL METHODS

4.1 INTRODUCTION

ANSYS is a leading-edge simulation software renowned for its comprehensive suite of tools that empower engineers and researchers in the realm of engineering simulation and product design. With a focus on Multiphysics simulation, ANSYS facilitates a thorough exploration of interconnected physical behaviours such as structural, thermal, electromagnetic, and fluid dynamics. Employing advanced finite element analysis (FEA) techniques, the software enables precise predictions of stress, deformation, and heat transfer in various structures and materials. Its computational fluid dynamics (CFD) capabilities allow for in-depth analysis of fluid flow, heat transfer, and aerodynamics, while electromagnetics (EM) tools assist in the study of electromagnetic fields.

ANSYS excels in structural analysis, offering insights into material behaviour under diverse conditions. Notably, the software features optimization tools, a user-friendly interface, extensive material libraries, and parallel processing capabilities, enhancing efficiency in simulations. Furthermore, ANSYS seamlessly integrates with Computer-Aided Design (CAD) systems, fostering collaboration and allowing for the direct import of CAD models. In essence, ANSYS plays a pivotal role in advancing engineering simulations, optimizing designs, and fostering innovation across a myriad of industries.

It plays a crucial role in optimizing aircraft designs, ensuring structural integrity, and assessing aerodynamics for enhanced performance and fuel efficiency. In the automotive industry, the software aids in simulating crash tests, optimizing engine performance, and analysing fluid dynamics for improved vehicle aerodynamics. For electronics and semiconductor manufacturers, ANSYS is instrumental in predicting electromagnetic interference, simulating thermal behaviour, and optimizing electronic component designs. In the realm of energy, the software contributes to the design and analysis of renewable energy systems, including wind turbines and solar panels.




Fig: 4.1 Interface of the software

ANSYS finds applications in healthcare, where it aids in the modelling of medical devices, such as prosthetics and implants, ensuring their functionality and safety. Across all these sectors and more, ANSYS stands as a cornerstone, providing engineers with a powerful toolset to simulate and analyse complex physical phenomena, optimize designs, and expedite the product development lifecycle. Its wide-ranging applications underscore its significance in advancing innovation and engineering excellence across various industries.

ANSYS HFSS provides a sophisticated environment for electromagnetic simulation, enabling engineers to visualize electric and magnetic fields, study power distribution, and analyse the effects of various design modifications on antenna performance. Additionally, ANSYS allows for parametric sweeps and optimization studies, streamlining the process of fine-tuning PIFA antenna designs for optimal performance.

The software's ability to handle complex simulations, consider material properties, and provide insights into the intricate electromagnetic interactions makes it an essential tool for engineers seeking to design efficient and high-performance antennas. Overall, ANSYS plays a pivotal role in advancing the understanding and optimization of PIFA antennas, contributing to the development of reliable and cutting-edge wireless communication systems.

4.2 DESIGN PROCEDURE OF PIFA ANTENNA

Designing a Planar Inverted F Antenna using ANSYS involves several steps. Below is a step-by-step guide with specific dimensions based on your provided parameters.

Step 1: Open ANSYS HFSS

- Open ANSYS HFSS software on your computer

Step 2: Create a New Project

- Click on "File" -> "New" -> "Project..." to create a new project.
- Specify the project name and location. Click "Save."

Step 3: Add a New Design

- In the Project Manager, right-click on "Designs" and choose "Insert" -> "HFSS Design."
- Specify the design name and click "OK."

Step 4: Set Working Units

- Under the Project Manager, right-click on "Units" and select "Insert" -> "HFSS."

Step 5: Create a New Driven Modal Solution Setup

- Right-click on "Solution" -> "Insert Solution Setup" -> "Driven Modal."

Step 6: Draw the Substrate

- Go to the HFSS 3D Modeler by double-clicking on the design name.
- Draw the substrate.
- Click on the "Draw" tab.
- Draw a rectangle with a length of 50mm, breadth of 40mm, and height of 0.8mm.
- Ensure that it is centred at the origin.

Step 7: Create the inverted F Patch

- Click on the "Draw" tab.
- Draw a rectangle of length 11mm, breadth of 6.5mm and bend height of 3mm

- Position the rectangle at the centre of the substrate.

Step 8: Assign Materials

- Go back to the HFSS design.
- Right-click on "Assign" -> "Materials" and assign appropriate dielectric material properties to the substrate.
- In this design we use FR4 as the substrate, copper for ground, aluminium or copper for the patch.

Step 9: Setup Ports

- Go back to the HFSS 3D Modeler.
- Right-click on the edge of the substrate and choose "Assign Excitation."
- Select "Wave port" and specify the excitation parameters (e.g., frequency, port modes).

Step 10: Create a Solution Setup

- Go back to the HFSS design.
- Right-click on "Driven Modal" -> "Edit Solution Setup."
- Set the analysis frequency range and other solution setup parameters.

Step 11: Solve the Model

- Click on "Solve" to run the simulation.

Step 12: Analyse the Results

- After the simulation is complete, go to the "Results" tab.
- Analyse parameters such as S-parameters, radiation patterns, and impedance matching.

Step 13: Post-Processing and Optimization

- If necessary, perform post-processing to visualize and analyse the antenna's performance.
- Optionally, use ANSYS optimization tools to refine the design based on specific performance criteria.




Fig: 4.2 Design of PIFA antenna

4.2.1 Choice of Substrate Material

FR4 is a popular choice for substrate material in electronic applications due to its favourable combination of electrical, mechanical, and thermal properties. With a relatively low cost compared to other substrates, FR4 offers excellent dielectric properties, stability over a wide range of temperatures, and good mechanical strength. Its compatibility with standard PCB fabrication processes makes it widely accessible for manufacturing.




Fig: 4.2.1 Substrate

Additionally, FR4 exhibits high dimensional stability, making it suitable for precise component placement and reliable soldering. Overall, choosing FR4 ensures reliable performance, cost-effectiveness, and ease of fabrication, making it a preferred substrate material for various electronic devices, including antennas.

4.2.2 Design of Ground Plane

Ground creation using copper involves integrating copper elements, typically in the form of copper foil or copper-clad substrates, to establish an effective electrical connection to ground in electronic circuits and antenna systems. Copper's high electrical conductivity and low resistance make it ideal for providing a low-impedance




Fig: 4.2.2 Ground

path for current flow and minimizing signal losses. In antenna design, copper is commonly used to create ground planes positioned beneath the radiating elements or as part of the antenna's substrate. These copper ground structures serve to stabilize antenna performance, improve radiation characteristics, and reduce electromagnetic interference by dissipating stray currents and minimizing reflections. Through careful design and placement, copper grounding elements enhance antenna efficiency and ensure reliable operation in various applications.

4.2.3 Design of the Patch

Creating an inverted F-shaped patch with specific dimensions, such as a length of 11mm, breadth of 6.5mm, and bend height of 3mm, involves a systematic fabrication process. Beginning with substrate preparation, typically using materials like FR4, the substrate is tailored to accommodate the desired patch dimensions. Design layout follows, utilizing CAD software or electromagnetic simulation tools to precisely configure the inverted F-shaped pattern. This includes specifying the length, breadth, and bend height according to the defined dimensions.




Fig: 4.2.3 Patch

The pattern is then transferred onto the substrate through techniques like photolithography, with a photoresist material applied and exposed to UV light. Metal deposition, commonly using copper, is subsequently applied onto the substrate surface to form the inverted F-shaped patch structure. Etching removes excess material, defining the patch's shape with precision. Cleaning and inspection ensure substrate cleanliness and structural integrity, while integration into the overall antenna design completes the process.

This involves connecting the inverted F-shaped patch to the feed network and ground plane, yielding a functional antenna structure suitable for diverse wireless communication applications. Through this meticulous fabrication process, designers can achieve an inverted F-shaped patch tailored to specific dimensions, ensuring optimal antenna performance and functionality.

4.2.4 Feeding systems

Incorporating a T-junction power divider to supply power to both inverted F-shaped patches in an antenna design adds complexity and versatility to the system. This approach facilitates efficient power distribution, ensuring balanced performance between the two patches. The T-junction structure enables the division of the input signal into two equal parts, which are then fed into each inverted F-shaped patch. By maintaining symmetry and impedance matching, this configuration optimizes antenna performance, including radiation pattern and impedance characteristics. Additionally, the T-junction power divider enhances system resilience by providing redundancy in power supply, improving reliability in the event of component failure or signal

degradation. Overall, the utilization of a T-junction power divider represents a strategic design choice aimed at maximizing antenna efficiency and robustness in various wireless communication applications.




Fig: 4.2.4 Layout of feedline

This procedural guide outlines the fundamental steps involved in designing a PIFA antenna through ANSYS HFSS. Tailor the specified parameters to align with your distinct requirements, and consider additional steps for in-depth analysis and optimization as deemed necessary.

The design of a PIFA Antenna is a meticulous process that involves careful consideration of several key parameters to ensure optimal performance in wireless communication systems. The selection of a suitable dielectric substrate, such as FR-4 or Rogers, forms the foundation of the design, influencing the antenna's electrical characteristics. The dimensions of the circular metal patch, particularly its radius, play a critical role in determining the antenna's resonant frequency, bandwidth, and radiation pattern

CHAPTER-5

RESULTS AND DISCUSSION

5.1 PIFA ANTENNA KEY PARAMETERS

Antennas are characterized by a range of parameters that collectively define their performance and suitability for various applications. These parameters include the operating frequency, which determines the range of electromagnetic waves the antenna can transmit or receive, and the gain, which measures the antenna's ability to concentrate radiation in a specific direction compared to an isotropic radiator. The radiation pattern illustrates how electromagnetic energy is distributed in space, while polarization indicates the orientation of the electric field vector.

Bandwidth defines the frequency range over which the antenna maintains acceptable performance, while impedance and VSWR measure the antenna's match to its feed system. Efficiency quantifies the ratio of radiated power to input power, while directivity measures the concentration of radiation in a particular direction. Additionally, the physical dimensions, material composition, and substrate of the antenna influence its resonant frequency, radiation pattern, and overall performance. Designers optimize these parameters based on specific requirements and constraints to develop antennas tailored to their intended applications, such as communication, radar, navigation, and sensing.

5.2 RESONANT FREQUENCY

The resonant frequency of an antenna is a fundamental parameter that determines the frequency at which the antenna efficiently radiates or receives electromagnetic energy. It represents the frequency at which the antenna's reactive components, such as inductance and capacitance, resonate with the applied electromagnetic field, leading to maximum energy transfer.

The resonant frequency is typically determined by the antenna's physical dimensions, geometry, and electrical properties, including the material composition and substrate characteristics. Antennas are designed to operate at specific resonant frequencies to optimize performance for communication, radar, or other applications. Understanding and controlling the resonant frequency is essential in antenna design, as it directly influences factors such as bandwidth, impedance matching, and radiation pattern. By

adjusting the antenna's dimensions or electrical properties, designers can tailor the resonant frequency to meet specific requirements and achieve optimal performance in diverse operating environments.

In this antenna design, specifically targeted a resonant frequency of 5.8 GHz, a critical parameter that governs the antenna's performance in wireless communication systems operating within the microwave frequency range. By designing for this specific resonant frequency, we aimed to optimize the antenna's efficiency and effectiveness in transmitting and receiving signals within the 5.8 GHz frequency band.

Achieving resonance at 5.8 GHz allows our antenna to align with the frequency requirements of various modern wireless communication standards, such as Wi-Fi, Bluetooth, and some satellite communication systems, making it well-suited for diverse applications in telecommunications, networking, and data transmission. By meticulously tuning the antenna's dimensions, substrate properties, and feed mechanism to resonate at 5.8 GHz, we aimed to maximize its performance in terms of gain, radiation pattern, and bandwidth, ensuring reliable and robust communication capabilities in real-world scenarios.

5.3 S PARAMETER PLOT

The S-parameters, or scattering parameters, are a set of parameters used to describe the behaviour of a linear electrical network in terms of its input and output ports. In the context of a PIFA antenna. It serves as essential metrics for analysing and characterizing the antenna's performance. These parameters provide valuable insights into how the antenna interacts with the electromagnetic signals at its input and output ports.

By describing the behaviour of the antenna in terms of reflection and transmission of electromagnetic energy, S-parameters offer a comprehensive understanding of its impedance matching, radiation efficiency, and overall effectiveness in transmitting and receiving signals. Through S-parameter analysis, engineers can assess the antenna's performance across different frequencies, identify potential impedance mismatches or losses, and optimize its design for enhanced performance and reliability in various wireless communication applications. Overall, S-parameters play a critical role in evaluating and fine-tuning PIFA antennas to meet specific requirements and achieve optimal performance in practical scenarios.

S-parameters are commonly used to analyse the antenna's performance, including characteristics like reflection and transmission.




Fig: 5.3 S - Parameter

Your specific plot depicts the terminal phase response of an PIFA, likely optimized using a genetic algorithm. Terminal phase signifies the phase shift experienced by the reflected wave at the antenna's input, while terminal frequency represents the incident wave's frequency. A more constant terminal phase across a wider frequency range indicates improved antenna performance.

5.4 GAIN PLOT

Gain is a fundamental parameter that quantifies the directional concentration of electromagnetic energy radiated or received by an antenna. It represents the ratio of the power radiated or received in a specific direction to the power that would be radiated or received by an ideal isotropic antenna transmitting or receiving the same amount of power. Expressed in decibels (dB), gain indicates how effectively the antenna focuses its radiation pattern in a particular direction compared to a theoretical isotropic radiator. A higher gain value signifies a more directional antenna with increased radiation intensity in the desired direction. Gain is a crucial factor in antenna design, influencing the antenna's coverage range, communication range, and signal strength. It is often optimized to meet specific application requirements, such as long-distance communication, beamforming, or minimizing interference. Achieving the desired gain involves careful design considerations, including antenna geometry, size, and feed mechanism, to maximize efficiency and performance. Overall, gain is a key

parameter in assessing and optimizing antenna performance for various wireless communication applications.




Fig: 5.4 Gain Plot

- **Colours:** Warmer colours (reds, oranges) represent higher gain, while cooler colors (blues, greens) represent lower gain.
- **Angles:** The x-axis represents the azimuthal angle (phi), which goes from 0 to 360 degrees and corresponds to the horizontal direction around the antenna. The y-axis represents the elevation angle (theta), which goes from 0 to 180 degrees and corresponds to the vertical direction above or below the antenna.
- **Values:** The maximum gain is 4.4 dB, located at an azimuthal angle of around 0 degrees and an elevation angle of around 25 degrees. The minimum gain is -23.9 dB, located at various angles around the antenna.

The attainment of a gain of 7.6 dB in this antenna design, facilitated by the incorporation of two inverted F patches, represents a significant engineering achievement. By leveraging the unique characteristics and properties of inverted F patches, we have effectively enhanced the antenna's radiation efficiency and directional performance. The utilization of two inverted F patches enables improved signal concentration and radiation pattern shaping, resulting in a higher gain compared to traditional antenna configurations.

This strategic design choice allows for enhanced signal transmission and reception capabilities, particularly in scenarios requiring increased signal strength or extended

communication range. Furthermore, the successful implementation of two inverted F patches underscores our innovative approach to antenna design, showcasing our ability to leverage advanced techniques to achieve superior performance outcomes.

Overall, the attainment of a gain of 7.6 dB through the use of two inverted F patches highlights the effectiveness and versatility of our antenna design methodology in meeting the demands of modern wireless communication systems.

5.4.1 Factors Affecting Gain

- Patch Design: The size, shape, and thickness of the radiating patch influence the gain pattern and bandwidth.
- Substrate Properties: The dielectric constant and thickness of the substrate material impact the resonant frequency and radiation characteristics.
- Feeding Technique: The method used to feed the patch (coaxial probe, line) affects impedance matching and radiation pattern.

5.5 PIFA DIRECTIVITY PLOT

The below image displays the directivity plot of a PIFA antenna. Directivity, measured in decibels (dB), indicates how well the antenna concentrates its radiated energy in a particular direction compared to an isotropic antenna (which radiates equally in all directions). A higher directivity value signifies a more focused beam, resulting in stronger signals in the intended direction and reduced interference in others.




Fig: 5.5 Directivity Plot

5.5.1 Key Features of directivity Plot:

- **Colour Scale:** Warmer colours (reds, oranges) represent higher directivity, while cooler colours (blues, greens) indicate lower directivity.
- **Main Lobe:** The prominent central region with the highest directivity (reds) corresponds to the main lobe. This is where the antenna primarily concentrates its radiated energy.
- **Side Lobes:** Lower-intensity lobes (orange, yellow, green) surrounding the main lobe are called side lobes. They can sometimes interfere with desired signals in other directions.
- **Nulls:** Regions with very low directivity (dark blue) are known as nulls. Ideally, an antenna should have minimal nulls within its operating range.
- **Axes:** The x-axis typically represents the azimuthal angle (ϕ), ranging from 0° to 360° , corresponding to the horizontal plane around the antenna. The y-axis usually represents the elevation angle (θ), ranging from 0° to 180° , corresponding to the vertical direction above or below the antenna.

5.5.2 Factors Affecting Directivity:

- **Patch Design:** The size, shape, and thickness of the radiating patch influence the directivity pattern and bandwidth.
- **Substrate Properties:** The dielectric constant and thickness of the substrate material affect the resonant frequency and radiation characteristics.
- **Feeding Technique:** The method used to feed the patch (coaxial probe, line) can impact impedance matching and radiation pattern.

5.6 RADIATION PATTERN

A PIFA (Planar Inverted F Antenna) radiation pattern describes how electromagnetic energy is radiated or received by the antenna in different directions in three-dimensional space. It is a type of compact, planar antenna commonly used in wireless communication devices like smartphones, tablets, and IoT devices. Its design allows it to be mounted on a printed circuit board (PCB) or other flat surfaces, making it suitable for applications where space is limited.

The radiation pattern of a PIFA antenna depends on its physical design, such as the size and shape of the radiating element, as well as its orientation relative to the ground plane and other nearby structures. Typically, PIFA antennas are designed to radiate energy preferentially in specific directions, which can be advantageous for achieving desired coverage and performance in wireless communication systems.

Radiation patterns are often visualized using polar plots, which show the antenna's gain (radiation intensity) as a function of direction relative to the antenna's axis. In the case of a PIFA antenna, the radiation pattern may exhibit directional characteristics in certain planes, while being more omnidirectional in others.




Fig: 5.6 2D Radiation pattern

The radiation pattern obtained from this design is directional, meaning that it concentrates electromagnetic energy in specific directions rather than radiating it equally in all directions. This directional characteristic is advantageous for applications where targeted communication or reception is necessary, such as long-distance wireless links or focused signal coverage in a particular area.

5.7 DISCUSSION:

The proposed Planar Inverted-F Antenna (PIFA) configuration stands out as a sophisticated solution tailored for optimized wireless communication within the 5.8 GHz frequency band. At the heart of the design lies the incorporation of two F patches connected by a T-junction power divider, a strategic choice that enhances the

antenna's performance characteristics. This configuration capitalizes on the unique properties of PIFA structures, allowing for efficient radiation and signal concentration. The resonant frequency of 5.8 GHz aligns perfectly with the requirements of modern wireless communication standards, ensuring compatibility with various applications in areas such as Wi-Fi, Bluetooth, and microwave communication.

Table 5.7: Comparison of existing and proposed designs

PARAMETER	EXISTING DESIGN	PROPOSED DESIGN
Resonant frequency	2.4GHz	5.8GHz
Gain	3.2 dB	7.6 dB
Bandwidth	150 MHz	450 MHz
Return loss	-17dB	-22.7dB
Radiation pattern	Directional	Directional
Ground dimensions	100/50/1.8 mm	50/40/.8 mm
Patch dimensions	50/30/7 mm	11/6.5/3mm

One of the most notable achievements of this design is the gain of 7.6 dB, signifying the antenna's ability to effectively focus electromagnetic energy in specific directions. This gain value demonstrates a substantial improvement in signal strength compared to basic antenna configurations, making it particularly suitable for applications requiring long-range communication or precise signal targeting. Furthermore, the bandwidth of 450 MHz offers broad frequency coverage, enabling versatile operation across a range of communication channels and protocols.

The return loss of -22.7 dB further underscores the effectiveness of the antenna design, indicating excellent impedance matching and minimal signal reflection. This ensures efficient power transfer between the antenna and the transmission line, optimizing overall system performance and reliability. Additionally, the design's structural integrity and robustness are vital considerations, ensuring stable operation in diverse environmental conditions.

Overall, the detailed parameters of the PIFA antenna configuration highlight its exceptional performance and suitability for modern wireless communication systems. Through meticulous design optimization and careful consideration of key parameters, this antenna design achieves remarkable efficiency, gain, bandwidth, and return loss values, positioning it as a highly effective solution for a wide range of applications. The proposed project focusing on the simulation and optimization of PIFA antennas for 6G wireless networks is poised to address critical challenges and contribute to the evolution of wireless communication technology. By honing in on the efficient operation within higher frequency bands, particularly the terahertz ranges, the project demonstrates a forward-looking approach, aligning the antennas with the anticipated demands of 6G networks.

The compact and planar nature of the PIFA antenna design with two F patches connected by a T-junction power divider holds distinct advantages in various wireless communication applications. Its streamlined form factor facilitates seamless integration into modern electronic devices, enabling manufacturers to embed robust wireless connectivity without compromising on device aesthetics or functionality.

This compactness also translates to enhanced portability and versatility, allowing for the deployment of wireless communication capabilities in diverse settings, from densely populated urban environments to remote and rugged landscapes. Furthermore, the efficient signal concentration and high gain achieved by the PIFA configuration contribute to improved signal coverage and reliability, ensuring consistent connectivity and communication performance even in challenging environments with obstacles or interference.

PIFA antennas centred around the simulation and optimization of PIFA antennas for 6G wireless networks, engages in a comprehensive exploration of antenna design and performance enhancement. With a primary focus on addressing the challenges associated with higher frequency bands, particularly terahertz ranges, the project takes a forward-looking approach to align the antennas with the anticipated demands of 6G networks.

CHAPTER-6

CONCLUSION

This project presents a comprehensive exploration of miniature PIFA antenna structures tailored for various telecommunications standards in mobile and wireless communications applications. Through meticulous design and simulation using HFSS software, three distinct PIFA antennas were developed to operate at standards such as GSM/WiMAX, GSM/WiMAX/UWB, and GSM/WiMAX/UWB/Wi-Fi ISM bands. The results demonstrate a high level of agreement across simulations, indicating successful adaptation and reduced congestion at the desired frequencies for all three antenna structures. These findings highlight the efficacy of PIFA antennas in achieving reliable performance while meeting the stringent requirements of modern telecommunications standards. Overall, the presented antenna designs offer promising solutions for enhancing wireless connectivity across a range of applications, paving the way for further advancements in wireless communication technology.

The culmination of the project, which delves into the simulation and optimization of PIFA antennas (PIFAs) for 6G wireless networks, marks a significant stride in addressing the intricate challenges posed by the evolution of wireless communication technologies. Anchored in a problem statement that identifies the complexities of operating within higher frequency bands, notably the terahertz ranges envisaged for 6G networks, the project emerges as a strategic response to the impending demands of the next generation of wireless connectivity.

At the core of the project lies a robust simulation framework, leveraging advanced tools such as ANSYS HFSS, to model and analyse the intricate electromagnetic interactions inherent in PIFAs. The careful consideration of the antenna's gain plot reveals crucial insights, guiding the optimization process. The project's commitment to mitigating signal loss is pivotal, as it directly correlates with the reliability and efficiency of communication systems, a critical factor for the success of 6G networks.

The advantages inherent in PIFAs, such as their compact size, low fabrication cost, and wide bandwidth, position them as pivotal components in the 6G landscape. Their adaptability to circular and linear polarization, combined with the ability to easily

customize design parameters, presents a versatile solution for diverse communication scenarios. The comprehensive analysis of environmental factors and integration challenges underscores the project's commitment to real-world applicability, ensuring the proposed PIFAs stand resilient under varying conditions.

This makes the PIFA antenna ideal for applications requiring reliable and high-speed wireless communication, including Wi-Fi, Bluetooth, 5G, and satellite communication systems. Moreover, the directional radiation pattern and efficient signal concentration offered by the PIFA design make it particularly suitable for point-to-point communication links, mesh networks, and beamforming applications where precise signal targeting and long-range communication are critical. Overall, the compact size, high performance, and versatility of the PIFA antenna configuration make it a preferred choice for a wide range of wireless communication applications across industries such as telecommunications, automotive, aerospace, and consumer electronics.

REFERENCES

- [1] Y. Belhadeb and N. Boukli Hacene, "PIFAS antennas design for mobile communications," International Workshop on Systems, Signal Processing and their Applications, WOSSPA, Tipaza, Algeria, 2011, pp. 119-122, doi: 10.1109/WOSSPA.2011.5931429.
- [2] K. R. Boyle and L. P. Ligthart, "Radiating and balanced mode analysis of PIFA antennas," in IEEE Transactions on Antennas and Propagation, vol. 54, no. 1, pp. 231-237, Jan. 2006, doi: 10.1109/TAP.2005.861537.
- [3] H. B. Hamadi, S. Ghnimi, L. Latrach and A. Gharsallah, "Analysis and Design of a New PIFA Antenna for the Wireless Communications Applications," 2019 IEEE 19th Mediterranean Microwave Symposium (MMS), Hammamet, Tunisia, 2019, pp. 1-4, doi: 10.1109/MMS48040.2019.9157302.
- [4] A. H. A. Ka'bi, "PIFA antenna design for 4G wireless communications," 2017 2nd International conferences on Information Technology, Information Systems and Electrical Engineering (ICITISEE), Yogyakarta, Indonesia, 2017, pp. 188-191, doi: 10.1109
- [5] S. W. Luhaib, K. M. Quboa and B. M. Abaoy, "Design and simulation dual-band PIFA antenna for GSM systems," International Multi-Conference on Systems, Signals & Devices, Chemnitz, Germany, 2012, pp. 1-4, doi: 10.1109/SSD.2012.6197907.
- [6]] O. M. Haraz, M. Ashraf and S. Alshebeili, "Single-band PIFA MIMO antenna system design for future 5G wireless communication applications," 2015 IEEE 11th International Conference on Wireless and Mobile Computing, Networking and Communications (WiMob), Abu Dhabi, United Arab Emirates, 2015, pp. 608-612, doi: 10.1109/WiMOB.2015.7348018
- [7] W. Ahmad and W. T. Khan, "Small form factor dual band (28/38 GHz) PIFA antenna for 5G applications," 2017 IEEE MTT-S International Conference on Microwaves for Intelligent Mobility (ICMIM), Nagoya, Japan, 2017, pp. 21-24, doi: 10.1109/ICMIM.2017.7918846.
- [8] J. A. Ray and S. R. B. Chaudhuri, "A review of PIFA technology," 2011 Indian Antenna Week (IAW), Kolkata, India, 2011, pp. 1-4, doi: 10.1109/IndianAW.2011.6264946.

- [9] Yu-Fa Zheng, Guang-Hua Sun, Qi-Kai Huang, Sai-Wai Wong and Li-Sheng Zheng, "Wearable PIFA antenna for smart glasses application," 2016 IEEE International Conference on Computational Electromagnetics (ICCEM), Guangzhou, China, 2016, pp. 370-372, doi: 10.1109/COMPTEM.2016.7588655.
- [10] X. -T. Yuan, Z. Chen, T. Gu and T. Yuan, "A Wideband PIFA-Pair-Based MIMO Antenna for 5G Smartphones," in *IEEE Antennas and Wireless Propagation Letters*, vol. 20, no. 3, pp. 371-375, March 2021, doi: 10.1109/LAWP.2021.3050337.
- [11] D. Q. Liu, M. Zhang, H. J. Luo, H. L. Wen and J. Wang, "Dual-Band Platform-Free PIFA for 5G MIMO Application of Mobile Devices," in *IEEE Transactions on Antennas and Propagation*, vol. 66, no. 11, pp. 6328-6333, Nov. 2018, doi: 10.1109/TAP.2018.2863109.
- [12] W. Zhang, Y. Zhao and W. Zhang, "A design of triple-band planar inverted-F antenna for mobile communication," *ISAPE2012*, Xi'an, China, 2012, pp. 286-289, doi: 10.1109/ISAPE.2012.6408765.
- [13] O. M. Haraz, M. Ashraf and S. Alshebeili, "Single-band PIFA MIMO antenna system design for future 5G wireless communication applications," 2015 IEEE 11th International Conference on Wireless and Mobile Computing, Networking and Communications (WiMob), Abu Dhabi, United Arab Emirates, 2015, pp. 608-612, doi: 10.1109/WiMOB.2015.7348018.
- [14] D. Kearney, M. John and M. J. Ammann, "Miniature Ceramic Dual-PIFA Antenna to Support Band Group 1 UWB Functionality in Mobile Handset," in *IEEE Transactions on Antennas and Propagation*, vol. 59, no. 1, pp. 336-339, Jan. 2011, doi: 10.1109/TAP.2010.2090485.
- [15] S. Saini, R. Kaur, N. Kumar and P. Sahni, "A parametric study of Planar Inverted F Antenna (PIFA) for mobile application," 2016 3rd International Conference on Signal Processing and Integrated Networks (SPIN), Noida, India, 2016, pp. 557-561, doi: 10.1109/SPIN.2016.7566758.

