


A slotted microstrip patch antenna for wideband wireless applications with circular polarization

Submitted in partial fulfillment of the requirements for the award of Bachelor of Engineering / Technology Degree in **ELECTRONICS AND COMMUNICATION ENGINEERING**

by

GAJJALA ARUN KISHORE REDDY(Register No. 37130130)



**DEPARTMENT OF ELECTRONICS AND COMMUNICATION
ENGINEERING
SCHOOL OF ELECTRICAL AND ELECTRONICS ENGINEERING**

SATHYABAMA

**INSTITUTE OF SCIENCE AND TECHNOLOGY
(DEEMED TO BE UNIVERSITY)**

Accredited with Grade "A" by NAAC

JEPPIAAR NAGAR, RAJIV GANDHI SALAI, CHENNAI - 600 119

APRIL 2021



SATHYABAMA

**INSTITUTE OF SCIENCE AND TECHNOLOGY
(DEEMED TO BE UNIVERSITY)**

Accredited "A" Grade by NAAC | 12B Status by UGC | Approved by AICTE

www.sathyabama.ac.in

DEPARTMENT OF ELECTRONICS AND COMMUNICATION ENGINEERING

BONAFIDE CERTIFICATE

This is to certify that this Project Report is the bonafide work of **GAJJALAARUN KISHORE REDDY** (Reg. No. 37130130) who carried out the project entitled **A SLOTTED MICROSTRIP PATCH ANTENNA FOR WIDEBAND WIRELESS APPLICATIONS WITH CIRCULAR POLARIZATION** under our supervision from December 2020 to April 2021.

Dr. I.REXILINE SHEEBA M.E.,ph.D
Internal Guide

Dr. T.RAVI, M.E,ph.D
Head of the Department

Submitted for Viva voce Examination held on _____

Name:

Signature:

Internal Examiner

External Examiner

DECLARATION

I GAJJALA ARUN KISHORE REDDY (Reg. No. 37130130) hereby declare that the Project Report entitled **“A SLOTTED MICROSTRIP PATCH ANTENNA FOR WIDEBAND AND WIRELESS APPLICATIONS WITH CIRCULAR POLARIZATION”** done by me under the guidance of **DR. I.REXILINE SHEEBA M.E, Ph.D** at sathyabama institute of science and technology is submitted in partial fulfillment of the requirements for the award of Bachelor of Engineering / technology degree in **ELECTRONICS AND COMMUNICATION ENGINEERING**.

DATE:

GAJJALA ARUN KISHORE REDDY

PLACE:

SIGNATURE OF THE CANDIDATES

ACKNOWLEDGEMENT

We are pleased to acknowledge our sincere thanks to the Board of Management of **SATHYABAMA** for their kind encouragement in doing this project and for completing it successfully. We are grateful to them.

We convey our thanks to **Dr. N. M. Nanditha.**, Dean, School of **ELECTRICAL AND ELECTRONICS ENGINEERING** and **Dr. T.RAVI, M.E,Ph.D**, Head of the Department, Dept. of **ELECTRONICS AND COMMUNICATION ENGINEERING** for providing us necessary support and details at the right time during the progressive reviews.

We would like to express our sincere and deep sense of gratitude to our Project Guide **Dr. I.REXIINE SHEEBA M.E,Ph.D** for her significant direction, ideas and steady consolation prepared for the fruitful consummation of our task work.

We wish to express our thanks to all Teaching and Non-teaching staff members of the Department of **ELECTRONICS AND COMMUNICATION ENGINEERING** who were helpful in many ways for the completion of the project.

TABLE OF CONTENTS

ABSTRACT	IV
TABLE	V
LIST OF FIGURES	VI

CHAPTER.NO	TITLE	PAGE. NO
1	INTRODUCTION	8
	1.1 ANTENNA	10
	1.2 ANTENNA PARAMETERS	11
	1.2.1 POWER GAIN	11
	1.2.2 EFFICIENCY	11
	1.2.3 DIRECTIVITY	12
	1.2.4 RETURN LOSS	12
	1.2.5 VSWR	12
	1.2.6 AXIAL RATIO	13
	1.2.7 RADIATION PATTERN	13
2	LITERATURE SURVEY	14
	2.1 DESIGN OF 16 ELEMENT RECTANGULAR PATCH ANTENNA ARRAY FOR 5G APPLICATIONS	
	2.2 DESIGN METHODS	14
	2.3 THE MICROSTRIP PATCH ANTENNA CALCULATION PROCESS	15
	2.4 ADVANTAGES AND DISADVANTAGES OF MICROSTRIP PATCH ANTENNA	16
		16
3	AIM AND SCOPE	
	3.1 EXISTING SYSTEM	18
	3.2 PROPOSED WORK	18
	3.3 ABOUT SLOT, CIRCULAR POLARISATION	18
	3.4 PATCH	19
	3.5 GROUND	20
	3.6 SUBSTRATE	20
	3.7 PORT	21
	3.8 FEED LINE	21
4	RESULT	
	4.1 ANTENNA WITHOUT SLOT	27
	4.1.1 VSWR	28
	4.1.2 RADIATION PATTERN	29
	4.1.3 3D PATTERN	29

	4.2 ANTENNA WITH SLOT 4.2.1 VSWR 4.2.2 RADIATION PATTERN 4.2.3 3D POLAR PLOT	30 31 31 32
5	CONCLUSION 5.1 REFERENCES	45

LIST OF FIGURES

FIGURE NO	TITLE	PAGE NO
1.1	Antenna	10
4.1	Antenna without slot	27
4.1.1	VSWR	28
4.1.2	Radiation Pattern	29
4.1.3	3D Polar lot	29
4.2	Antenna with slot	30
4.2.1	VSWR	31
4.2.2	Radiation Pattern	32
4.2.3	3D pattern	32

LIST OF SYMBOLS

Σ	-	Efficiency
ϕ	-	azimuth
θ	-	altitude
Δl	-	length Extension
GHz	-	Gigahertz
Σr	-	Relative Permittivity
h	-	Thickness
L_{eff}	-	Effective Length
c	-	Speed of Light
f_0	-	Resonant Frequency
w	-	Width
dB	-	Decibel

ABSTRACT:

Circularly polarized diagonally regular slotted microstrip-patch antennas area unit planned with compact size. The compact circularly polarized (CP) diagonally regular slotted microstrip- patch (DSSMP) antenna style rules are summarized. Circularly polarized radiation is achieved victimization at random formed slots in diagonal directions on the sq. microstrip-patch antenna. totally different shapes for the slots area unit studied and compared, supported the fastened overall volume of the antenna for circularly polarized diagonally regular slotted microstrip-patch antennas. The cross-formed opening corner to corner symmetric opened microstrip-fix radio wire is smaller when contrasted and the round , square-, and roundabout ring-molded skew symmetric opened microstrip-fix receiving wires. A deliberate 3 dB pivotal proportion (AR) data transfer capacity of around 0.7% (6.0 MHz) with 2.0% (18.0 MHz) impedance data transmission was accomplished. The deliberate boresight acquired was more than 3.3 dBic over the operating band, while the overall antenna size was $0.272\lambda_0 \times 0.272\lambda_0 \times 0.0138\lambda_0$ at 0.905 GHz.


CHAPTER 1

INTRODUCTION

The microstrip antenna has a number of useful properties such as small size, low-cost fabrication, low profile, light weight, ease of installation and integration with feed networks.

Microstrip receiving wire in its easiest structure comprises a transmitting patch which consists of a directing material like Copper or Gold on one side of a dielectric substrate and a ground plane on the opposite side. There are various states of receiving wire contingent upon its application. When all is said in done, the microstrip radio wire has numerous remarkable and alluring properties. These properties incorporate low profile, light weight, being conservative and comparable to mounting structure, simple creation and coordination with strong state gadgets. There are various and notable strategies to expand the transmission capacity of radio wires, including increment of the substrate thickness, the utilization of a low dielectric substrate, and the utilization of numerous resonators. Hence, the interest in multiband radio wires is expanding, particularly to decrease the quantity of receiving wires inserted in consolidating various applications on a solitary receiving wire.

1.1 ANTENNA



In radio engineering, associate degree antenna or aerial is that the interface between radio waves propagating through space and electrical currents occupancy metal conductors, used with a transmitter or receiver.[1] In transmission, a sender provides an electrical current to the radio wire's terminals, and along these lines the receiving wire transmits the energy from the current as attraction waves(radio waves). In gathering, a receiving wire captures some of the force of a electromagnetic radiation to deliver an electrical flow at its terminals, that's applied to a collector to be intense. Receiving wires are elementary segments of all radio gear.

A receiving wire could be a sort of channel (components), electrically related to the recipient or transmitter. Receiving wires is meant to send and acquire radio waves all told even ways in which equally (omnidirectional radio wires), or specially a particular means (directional, or high-gain, or "shaft" radio wires). A receiving wire could incorporate segments not related to the transmitter, allegorical reflectors, horns, or parasitic

components that serve to coordinate the radio waves into a bar or alternative needed radiation style. Receiving wires are required by any radio beneficiary or transmitter and its electrical association with the magnetism field.[8] Radio waves are magnetism waves that facilitate signals through the air (or through space) at the speed of lightweight with virtually no transmission loss. associate degree automobile's whip antenna, a standard example of associate degree omnidirectional

antenna. Antennas will be classified as omnidirectional, diverging energy or so equally all told directions, or directional, wherever energy radiates a lot of on one direction than others. (Receiving wires are corresponding, thus an identical impact happens for gathering of radio waves.) a completely uniform omnidirectional receiving

wire is not actually conceivable. Some radio wire sorts have an even radiation style within the flat plane, however send very little energy upward or raining. A "directional" radio wire unremarkably is predicted to amplify its coupling to the magnetism field toward the opposite station.

1.2 ANTENNA PARAMETERS

An associate degreetenna is an electrical conductor or system of conductors Transmitter- Radiates magnetic force energy into house Receiver - Collects magnetic force energy from house

1.2.1 POWER GAIN

Power gain (or simply **gain**) is a Gain measure of the ability of the antenna to direct the input power into radiation in a particular direction and is measured at the peak radiation intensity. Consider the force thickness emanated by an isotropic radio wire with input power P_0 a good way off R which is given by $S = P_0/4\pi R^2$. An isotropic antenna radiates equally in all directions, and its radiated power density S is found by dividing the radiated power by the area of the sphere $4\pi R^2$.

1.2.2 EFFICIENCY

The efficiency Σ antenna of an antenna is the total radiated power P_0 divided by the input power at the feedpoint.

A transmitting antenna is supplied power by a feedline, a transmission line connecting the antenna to a radio transmitter. The **input power** P_{in} to the antenna is typically defined to be the power supplied to the antenna's terminals (the *feedpoint*), so antenna power losses do not include power lost due to joule heating in the feedline and reflections back down the feedline because of receiving wire/line impedance crisscrosses. The electromagnetic reciprocity theorem guarantees that the electrical properties of an antenna, such as efficiency, directivity, and gain, are the same when

the antenna is used for receiving as when it is transmitting.

1.2.3 DIRECTIVITY

A radio wire's directivity is controlled by its radiation design, how the transmitted force is appropriated with heading in three measurements. All radio wires are directional to a more prominent or lesser degree, implying that they emanate more force in certain ways than others. The course is determined here in circular directions (θ, ϕ) where θ is the elevation or point over a predefined reference plane (like the ground), while ϕ is the azimuth as the point between the projection of the provided guidance onto the reference plane and a predetermined reference bearing (like north or east) in that plane with indicated sign (either clockwise or counterclockwise).

The dissemination of yield power as a component of the potential headings (θ, ϕ) is given by its radiation force $U(\theta, \phi)$ (in SI units: watts per steradian, $\text{W}\cdot\text{sr}^{-1}$). The yield power is acquired from the radiation force by incorporating the last over all strong points $d\omega = \cos\theta \, d\theta \, d\phi$

1.2.4 RETURN LOSS

Return misfortune is a significant boundary when testing a receiving wire. It is identified with impedance coordinating and the greatest exchange of force hypothesis. It is also a measure of the effectiveness of an antenna to deliver power from source to antenna. The return loss (RL) is defined by the ratio of the incident power of the antenna (P_{in}) to the power reflected back from the antenna of the source (P_{ref}) the mathematical expression is

$$R = 10\log_{10}(P_{in}/P_{ref})$$

1.2.5 VSWR

VSWR (Voltage Standing Wave Ratio), is a measure of how efficiently radio-frequency power is transmitted from a power source, through a transmission line, into a load (for example, from a power amplifier through a transmission line, to an antenna). In an ideal system, 100% of the energy is transmitted.

1.2.8 AXIAL RATIO

The Axial Ratio (AR) of an antenna is defined as the ratio between the major and minor axis of a circularly polarized antenna pattern. If an antenna has perfect circular polarization then this ratio would be 1 (0 dB). However, if the antenna has an elliptical polarization then this ratio would be greater than 1 (>0 dB).

1.2.9 RADIATION PATTERN

A radiation pattern defines the variation of the power radiated by an antenna as a function of the direction away from the antenna. This power variation as a function of the arrival angle is observed in the antenna's far field.

CHAPTER 2

2. LITERATURE SURVEY

2.1 DESIGN OF 16 ELEMENT RECTANGULAR PATCH ANTENNA ARRAY FOR 5G APPLICATIONS

Vishnumolakala Jyothika 1 et.al(2014)

This paper addresses the arrangement of a 16 component rectangular fixed cluster radio wire for 5G applications that gives a reasonable exchange speed of around 28 GHz. This is the most segment of this game-plan could be a rectangular fix accepting wire laid out on the Rogers RT/Duroid 5880 substrate ($\epsilon_r = 2.2$, $\tan\delta=0.00009$), which is reproduced and enhanced using an economically industrially accessible recreation program. Length of rectangular fix antenna is 3.58 and breadth is 4.52. Within a long time the improvement in communication frameworks demand the advancement of low cost, negligible weight and low-profile radio wires that are able to keep up tall execution over a wide range of frequencies.

A New and Compact Wide-Band Microstrip Filter-Antenna Design for 2.4 GHz ISM Band and 4G Applications

Yasir I. A. Al-Yasir 1 et.al(2016)

Another and smaller four-shaft wide-band planar channel radio wire configuration is proposed in this article. The impact of the dielectric material sort on the attributes of the plan is additionally explored and introduced. The channel radio wire structure is framed by a fourth-request planar band-pass channel (BPF) with a monopole microstrip receiving wire. The planned channel receiving wire works at a middle recurrence of 2.4 GHz and has a moderately wide-band impedance data transfer capacity of about 1.22 GHz and a partial data transfer capacity (FBW) of about half. The impacts of three distinct sorts of substrate material, which are Rogers RT5880, Rogers RO3003, and FR-4, are examined and introduced utilizing a similar arrangement.

Koch limit on the square fix microstrip receiving wire for ultra wideband applications

Manisha Gupta et.al(2018)

In this paper a novel smaller microstrip feed square fix receiving wire with right calculated isosceles Koch fractal math on its edges is intended for ultra wideband applications. The emanating patch is changed in a few stages to accomplish a multiband circularly energized radio wire. The fractal radio wire is reenacted utilizing CST Microwave Studio Simulator. Radio wire's exhibition is then contrasted with symmetrical Koch, Minkowski and Sierpinski fractal calculations.

Plan Of Multiband Microstrip Patch Antenna For Wlan,Wimax And X-Band Applications

Pronami Bora et.al(2019)

This letter depicts a little, single-feed, circularly enraptured fixed radio wire for broadband. The radio wire comprises a microstrip fix and pins on the Reactive Impedance Surface (RIS) enlivened by metamaterials. The RIS structure, comprising 4 or 4 standard metallic square fixes and four shorting pins which assists with improving the receiving wire data transfer capacity. The last enhanced design displays an impedance data transfer capacity of 53.75%(4.650GHz-7.617GHz) along with a 3-dB pivotal proportion

data transfer capacity of 30.4%(4.6242GHz-6.3036GHz). In addition, the proposed radio wire yields a decent main side increase of 5.8 dBi at 5.52Ghz

2.2 DESIGN METHODS

After the discussion of the simplified formulation in previous sections, the procedure for designing a rectangular microstrip patch antenna is explained. In this procedure there are three essential parameters for the design: the frequency of operation f , the dielectric constant of the substrate ϵ_r and the height of the dielectric substrate h

For a given ϵ_r and h , we design a microstrip antenna for the resonant frequency f_0 (finding the width and length of the patch).

2.3 THE MICROSTRIP PATCH ANTENNA CALCULATION PROCESS

Stage 1: Calculation of the Width (W)

Stage 2: Calculation of the Effective Dielectric Constant. This depends on the thickness, dielectric constant of the dielectric and the determined width of the fixed receiving wire.

Stage 3: Calculation of the Effective length

Stage 4: Calculation of the length expansion ΔL

Stage 5: Calculation of real length of the fix

Where the accompanying boundaries are utilized

f_0 is the Resonance Frequency W is the Width of the Patch

L is the Length of the Patch

h is the thickness

ϵ_r is the general Permittivity of the dielectric substrate c is the Speed of light: 3×10^8

2.4 ADVANTAGES AND DISADVANTAGES OF MICROSTRIP PATCH ANTENNAS

The benefits of microstrip fix receiving wires are Planar, which can likewise be made conformal to a molded surface, Low profile, Low radar cross-area, Rough, Can be created by printed circuit innovation, Can be incorporated with circuit components, Can be intended for double polarization activities, Can be intended for double or multi-recurrence activities. These benefits make microstrip fix radio wires considerably more appropriate for airplanes, space apparatus, and rockets than regular receiving wires as they do not meddle with the streamlined features of these moving vehicles. Their planar profiles are to appear differently

in relation to those of the varieties of microstrip fix radio wires made conformal to a wing shape surface. In view of the benefits recorded over, the microstrip fix radio wire has likewise gotten the top pick of receiving wire architects for business portable and remote correspondence frameworks.

DISADVANTAGES OF MICROSTRIP PATCH ANTENNAS

There are several disadvantages associated with microstrip patch antennas. In its basic form, the microstrip antenna has a narrow impedance bandwidth, typically less than 5%. However, various bandwidth-widening techniques have been developed. Up to 50% bandwidth has been achieved. It is by and large obvious that more extensive data transfer capacity is accomplished with the penance of expanded radio wire actual volume. Due to the small separation between the radiating patch and its ground plane, the microstrip antenna can handle relatively low RF power. The average power considered safe is a few tens of watts. While a single patch element generally incurs very little loss because it is only about one-half wave long, microstrip arrays generally have larger ohmic loss than arrays of other types of antennas of equivalent aperture size. This ohmic misfortune generally happens in the dielectric substrate and the metal conductor of the microstrip line feed network and power dividing circuit.

CHAPTER 3

3 AIM AND SCOPE

3.1 EXISTING SYSTEM

In the existing work designs of both planar ultra-wide band (UWB) antenna and UWB antenna with two rejected bands are given. The antenna consists of a rectangular patch etched on the FR4- substrate with a feed line. The rectangular patch has one round cut at each corner with one slot in the ground plane. The tuning bands achieved by inserting slots in the patch and the feed. The impact of these substrates on the impedance bandwidth, efficiency and gain of the antennas is Analyzed. Sonnet suite software has been used here to design. The main drawbacks are Low impedance bandwidth, Low gain, Extra radiation occurs from its feeds and junctions, It supports only linear polarization.

3.2 PROPOSED SYSTEM

The proposed work deals with the design of a slotted patch antenna that will be designed and analyzed for wireless applications. Patch will be tuned in order to achieve circular polarization. Design will be analyzed with and without slots and with various types of slots in order to enhance the performance. Rogers substrate material will be used in the design. Both wave port feed and coaxial line feed will be analyzed to find which feed gives better performance. Various parameters like return loss, bandwidth,

gain, directivity and radiation patterns will be analyzed. The design will be developed ,Analysis will be carried out for simulated and Measured results. HFSS 15.0 software has been used here to design the Antenna.

3.3 ABOUT SLOT, CIRCULAR POLARIZATION

Circularly spellbound (CP) microstrip radio wires have been famously utilized in different contemporary remote correspondences frameworks, for example, for satellite correspondence, WLAN (Wireless Local Area Network) and WiMAX (Worldwide

Interoperability for Microwave Access),GPS (Global Positioning System), RFID (Radiofrequency identification) tag and RFID readers because of the versatile orientation of the transmitter and receiver. Slot antennas are usually used at [UHF](#) and [microwave](#) frequencies. They are used in standard laboratory [microwave](#) sources used for research, UHF television transmitting antennas, antennas on missiles and aircraft, [sector antennas](#) for [cellular base stations](#), and particularly [marine radar](#) antennas. A slot antenna's main advantages are its size, design simplicity, and convenient adaptation to mass production using either waveguide or PC board technology.

3.4 PATCH

A patch antenna is a type of radio antenna with a low profile, which can be mounted on a flat surface. It consists of a planar rectangular, circular, triangular, or any geometrical sheet or "patch" of metal, mounted over a larger sheet of metal called a ground plane. the two metal sheets together form a resonant piece of microstrip transmission line with a length of approximately one-half wavelength of the radio waves. The radiation mechanism arises from discontinuities at each truncated edge of the microstrip transmission line. The radiation at the edges causes the antenna to act slightly larger electrically than its physical dimensions, so in order for the antenna to be resonant, a length of microstrip transmission line slightly shorter than one-half the wavelength at the frequency is used. The patch antenna is mainly practical at microwave frequencies, at which wavelengths are short enough that the patches are conveniently small. It is widely used in portable wireless devices because of the ease of fabricating it on printed circuit boards. Multiple patch antennas on the same substrate called microstrip antennas, can be used to make high gain array antennas, and phased arrays in which the beam can be electronically steered.

A variant of the patch antenna commonly used in mobile phones is the shorted patch antenna, or planar inverted-F antenna (PIFA). In this antenna, one corner of the patch (or sometimes one edge) is grounded with a ground pin. This variant has better matching than the standard patch. Another variant of patch antenna with the partially etched ground plane, also known as printed monopole antenna, is a very versatile antenna for dual-band operations.

3.5 GROUND

A ground plane is an electrically conductive surface, usually connected to electrical ground. The term has two different meanings in separate areas of electrical engineering. In antenna theory, a ground plane is a conducting surface large in comparison to the wavelength, such as the Earth, which is connected to the transmitter's ground wire and serves as a reflecting surface for radio waves. In printed circuit boards, a ground plane is a large area of copper foil on the board which is connected to the power supply ground terminal and serves as a return path for current from different components on the board.

3.6 SUBSTRATE

Substrate is a base or container on which a microstrip patch (metallic sheet) antenna is fabricated and it plays an important role in microstrip antenna functioning. The substrate in microstrip antennas is principally needed for the mechanical support of the antenna. To provide this support, the substrate should consist of a dielectric material, which may affect the electrical performance of the antenna, circuits and transmission line. A substrate must, therefore, simultaneously satisfy the electrical and mechanical requirements, which is sometimes difficult to meet.

Right substrate selection is a must on the basis of cost, efficiency and size. Patch antenna is fabricated by etching the antenna element pattern in metal trace bonded to an insulating dielectric substrate with a continuous metal layer bonded to the opposite side of the substrate which forms a ground plane.

Substrate (dielectrics) are used for improved electrical and mechanical stability. They are used to reduce the size of the antenna (higher permittivity, lower size) and can help to produce displacement current which produces time varying Magnetic Field (by Ampere's Law). This can in turn produce time varying Electric Field (by Faraday's law) and a propagating EM field is created. Hence, a substrate can enhance an antenna's radiation capability.

In order to design a microstrip patch antenna at first the designer is to select the substrate material and its thickness. So, if the designer has a clear conception about the effect of changing substrate material and its thickness on the performance of the antenna, it will be easier to design an antenna. Appropriate selection of dielectric material and its thickness is an important task for designing a microstrip patch antenna.

3.7 PORT

An antenna port is generally used as a generic term for signal transmission under identical channel conditions. For each LTE operating mode in the downlink direction for which an independent channel is assumed (e.g. SISO vs. MIMO), a separate logical antenna port is define.

3.8 FEED LINE

A radio antenna, the feed line (feedline), or feeder, is the cable or other transmission line that connects the antenna with the radio transmitter or receiver. In a transmitting antenna, it feeds the radio frequency (RF) current from the transmitter to the antenna, where it is radiated as radio waves. In a receiving antenna it transfers the tiny RF voltage induced in the antenna by the radio wave to the receiver. In order to carry RF current efficiently, feed lines are made of specialized types of cable called transmission line. Particularly with a transmitting antenna, the feed line is a critical component that must be adjusted to work correctly with the antenna and transmitter. Each type of transmission line has a specific characteristic impedance. This must be matched to the impedance of the antenna and the transmitter, to transfer power efficiently to the antenna. If these impedances are not matched it can cause a condition called standing waves on the feed line, in which the RF energy is reflected back toward the transmitter, wasting energy and possibly overheating the transmitter. This adjustment is done with a device called an antenna tuner in the transmitter, and sometimes a matching network at the antenna.

HFSS FOR ANTENNA SIMULATION

Antennas are virtually everywhere. From business applications, for example, cell phones, RFID labels, and remote printers, to safeguard applications, for example, staged exhibit radio wires for airplane radar frameworks or satellite-based, to give coordinated ground based communication systems. Electromagnetic reenactment is an important device in receiving wire plan and stage coordination giving the fashioner the capacity to basically plan and assess the possibility of situations just as checking the last fabricated plan. ANSYS® HFSS™ dominates at a wide assortment of high recurrence, full-wave, electromagnetic applications including radio wire plan and arrangement since it utilizes various progressed solver strategies to reenact the receiving wire as well as the impacts of its connection with the whole framework, including the taking care of framework just as the stage. settling on it is a definitive instrument of decision for receiving wire recreation. Bus driving 3D electromagnetic (EM) recreation instrument for high recurrence and fast electronic segments. Figure 1 features a few receiving wire related applications with accentuation on radio wires close by different constructions. With various reenactment advances and incredible mechanized versatile lattice refinement giving best quality level exactness, HFSS can help receiving wire planners who are continually tested with carrying out plans across increasingly more recurrence groups inside a more modest and more modest impression. With these extra specialized difficulties alongside the always contracting time to showcase, recreation with HFSS is an unquestionable requirement in the receiving wire plan and incorporation measure. Scaling down of the radio wires, restricted channel transfer speed, decreased plan time, and receiving wire association with different parts present solid difficulties to the plan engineer. HFSS gives programmed, precise, and proficient answers for beat execution portrayal, for example, return misfortune, input impedance, gain, directivity and an assortment of polarization attributes can be investigated in HFSS. Key post-preparing highlights, for example, the capacity to overlay the 3D far-field design on the receiving wire math can give the architect important knowledge and direct relationship between the radio wire and the subsequent radiation design. HFSS likewise offers electric and attractive field perception both in the close field and far-field giving plan understanding that isn't effectively accessible through estimation. This knowledge permits the architect to decide the segments of the math pertinent to the antenna's performance. Combined with Optimetrics™, HFSS likewise permits specialists to parametrically clear plan varieties to examine the radio wire's plan space utilizing such improvement methods as Quasi Newton, Pattern Search, Sequential Nonlinear Programming (SNLP), Blended Integer SNLP, and hereditary

calculations. This modern degree of investigation that can give plan sensitivities and data on by and large measurable execution and assembling yields permit the designer to go to creation and market with trust in outcomes and execution. Programmed Adaptive Meshing A vital element of HFSS is programmed versatile lattice refinement which creates a precise arrangement dependent on the material science or electromagnetics of the plan. This mechanized fitting procedure leaves the attention on the receiving wire plan instead of investing energy deciding and making the best lattice. This computerization and ensured precision separates HFSS from any remaining electromagnetic test systems, which commonly require manual client controls to guarantee that the produced network is reasonable and exact for recreation. Without the correct mesh, the results from such simulators can be erroneous. But with automatic adaptive meshing, HFSS lets the physics define the mesh and not the other way around and guarantees accurate results. The meshing algorithm adaptively refined the mesh throughout the geometry; it iteratively adds mesh elements in areas where a finer mesh is needed due to the localized electromagnetic field behavior. Figure 2 shows the versatile lattice measure for a fixed radio wire working at 11.5 GHz utilizing the limited component strategy (FEM) in HFSS.

The merits of automatic adaptive meshing are

The cross section size is right and reasonable for proficient reenactments prompting profoundly exact arrangements. Such a procedure dependably 'tunes' the cross section to the electrical conduct of the receiving wire. You don't have to be a cross section master and you can zero in on the plan instead of the reproduction arrangement. You can investigate plan alternatives rapidly and economically and diminish the quantity of models. Fewer or no models guarantee enormous investment funds on schedule and cash on equipment advancement and testing. Top to bottom investigation of the plan and its electromagnetic conduct that is absurd from the customary form and test theory. You just need to make the math, indicate material properties, limit conditions, excitations, and arrangement recurrence and HFSS deals with the rest. Radio wire Simulation Technologies in HFSS. HFSS offers the accompanying reproduction strategies and devices relying on the sort of issue you need to tackle Finite Element Method (Enabled with HFSS). Integral Equations (Enabled with HFSS-IE). Physical Optics (Enabled with HFSS-IE). FEM Transient (Enabled with HFSS-TR). Antenna Design Toolkit gave HFSS including more than 50 standard radio wire plans Finite

Element Method The limited component strategy is exceptionally appropriate for 3D discretionarily molded geom

Finite Element Method

The finite part methodology is extremely suited to 3D arbitrarily-shaped geometries. In this strategy, the mathematical model is consequently isolated into various tetrahedral components conformal to all surfaces of the calculation. Tetrahedral elements are highly suited for this type of unstructured and non-uniform mesh since they can be stretched and pulled to fit any arbitrary geometry. The finite element formulation uses advanced mathematical techniques to satisfy Maxwell's Equations in the entire model. This method handles complex materials and geometries efficiently. FEM settles the model by making a volume based lattice and produces field arrangements. As demonstrated in Figure 3, the fields are expressly settled all through the whole volume – not simply the radio wire and the item to which it is coupled (for this situation the human head) however additionally the setting within which it's placed. The example shown within the Figure three illustrates a smartphone close to a phantom model of the caput that simulates realistic specific absorption rate (SAR) measurements. The answer takes advantage of HFSS' FEM thinker and HFSS Optimetrics to specify the position of the smartphone. This assists associations with meeting administrative consistency before their items hit the market. Accuracy within the SAR mensuration saves duplication of efforts and activity.


Integral Equations

HFSS-IE shares identical modeller interface and analysis setup as HFSS and is enforced as a style kind within the HFSS desktop. Existing HFSS users find HFSS-IE genuinely like HFSS and along these lines require negligible preparation for successful use. IE utilizes the 3D Method of Moments (MoM) procedure for effectively taking care of open radiation and dissipating issues where flows are tackled on a superficial level lattice as demonstrated in Figure 4. This is the best solver for structures that are basically metal yet may in like manner join dielectrics. The receiving wires addressed are in an open climate accordingly no radiation limit or air volume is required just like the case with HFSS and limited components. You can utilize the IE solver for productive investigation of electrically huge metallic designs where applications could incorporate, receiving wire situation on vehicles, RCS, and reflector radio

wire examination. HFSS-IE offers the significant benefit of utilizing the versatile cross estimate (ACA) strategy for enormous issue sizes. The ACA procedure gives diminished machine assets to a mater goal, though being undeniably fit to the mechanized accommodative cross section algorithmic principle used by HFSS-IE. Hybrid FEM-IE Solution HFSS offers the capacity to use the strength of both limited component technique (HFSS) and basic conditions strategy (HFSS-IE) into a solitary issue. A particularly crossover arrangement is exceptionally beneficial. HFSS-IE can be utilized to settle for the field spread through free space and along transmitters outside the FEM volume utilized normally to show the nitty gritty calculation and dielectrics of the receiving wire parts killing the necessity for a FEM volume network all through. Moreover, the IE solution region can be contiguous with the FEM region such that currents flow from one solution domain to another. Figure half dozen illustrates the appliance of the combined FEM and that is hybrid answer on 2 antenna structures. The first is a full wave arrangement of a reflector receiving wire 60 frequencies in breadth with a mind boggling 3D feed horn. The feed horn is solved using HFSS' FEM solution and the main reflector and sun-reflectors are solved using IE. This large problem was solved in 37GB RAM in only 3. 2 hours. The second example in Figure half-dozen could be a satellite with an associated array of helix antennas mounted on its prime surface. For this situation the IE strategy is utilized to shorten the FEM locale in a successful engrossing limit condition. A conformal air box is put round the satellite on that FE-BI is applied prompting multiple times RAM decrease over Associate in Nursing FEM exclusively answer.

CHAPTER 4



SIMULATION AND RESULT ANALYSIS





ANTENNA WITHOUT SLOT

RESULT


VSWR




3D POLAR PLOT




ANTENNA WITH SLOT




RESULT




VSWR




3D PATTERN DESIGN



Radiation Pattern





ADVANTAGES

The advantages of microstrip patch antennas are Ease of manufacturing, High Gain, Microstrip fix radio wires are effective radiators, Simple in combination with microwave coordination circuits.

COMPARISON

Comparison of various antenna parameters for with slot and without slot antenna are, Directivity for with slot antenna is 180 and for without slot is 30. Gain is 8.84 for with slot and 3.4 for without slot. VSWR is 0.1055 for with slot and 21.41 for without slot. The Vswr should be always less than 2, if it is greater than that, then we consider the antenna is not a good one. The radiated power is 0.94w for with slot and 0.17w for without slot. The accepted power is 0.96w for with slot and 0.25w for without slot. Incident power is 1w for both with and without slot. Radiation efficiency is 96% for with slot and 69% for without slot. Axial ratio is 1.7 for with slot and 12 for without slot. If the axial ratio is less than 3, then we can consider it as circular polarization and if it is greater than 3 then we can consider it as linear polarization. The frequency range of the antenna with slot is 4.8 GHz and for without slot is 2.24GHz.

TABLE

Parameter	With Slot	Without Slot
Directivity	180	30
Gain	8.7	3.4
Frequency	4.8	2.24
VSWR	0.1055	21.41
Radiated Power	0.94w	0.17w
Accepted power	0.96w	0.25w
Incident Power	1w	1w
Radiation Efficiency	96%	69%
Axial Ratio	1.7	12
Polarization	Circular	Linear

CHAPTER 5

CONCLUSION

Compact circularly polarized diagonally radially symmetrical slotted microstrip fix radio wires are examined and offered upheld very surprising framed slots. Any abstractly formed space can be used to achieve circularly enchanted radiation with an accepting wire of more modest size. The cross-circle molded slantingly symmetric opened microstrip fix receiving wire for circularly energized radiation is the awesome correlation with various 2 openings. It's been shown that by powerful the overall borders of the openings, the in activity band of the receiving wire is regularly tuned with brilliant circularly spellbound radiation for an ideal working frequency. So the microstrip fix getting wire for low return incident, high expansion and high 3-dB AR information move limit has been produced and likely cultivated for ISM band applications. The previously mentioned abilities of the antenna have been achieved by cutting slots of various shapes (cross-circle, L and flower slot). Measured results (S11) believe the simulated values. From the experimental results it's clear that the cross-circle configuration among the invented structures offers high 10-dB come loss information measure of fifty (2.38 to 2.50 GHz) and 3-dB axial quantitative relation information measure of twenty-two (2.435 to 2.465 GHz).

REFERENCES

1. Hussaini, A. Green Flexible RF for 5G. In Fundamentals of 5G Mobile Networks, 1st ed.; Rodriguez, J., Ed.; John Wiley and Sons: Hoboken, NJ, USA, 2015.
2. Rodriguez, J.; Radwan, A.; Barbosa, C.; Fitzek, F.H.P.; Abd-Alhameed, R.A.; Noras, J.M.; Jones, S.M.R.; Politis, I.; Galiotos, P.; Schulte, G.; et al. SECRET—Secure Network Coding for Reduced Energy cutting edge Mobile Small Cells: An European Training Network in

Wireless Communications and Networking for 5G. In Proceedings of the 2017 Internet Technologies and Applications (ITA), Wrexham, UK, 12–15 September 2017; pp. 329–33

3. 3. Parchin, N.O. Microwave/RF Components for 5G Front-End Systems; AVID SCIENCE: Telangana, India, 2020.

4. Al-Yasir, Y.; Abd-Alhameed, R.A.; Noras, J.M.; Abdulkhaleq, A.M.; Ojaroudi, N. Plan of Very Compact Comblined Band-Pass Filter for 5G Applications. In Proceedings of the Loughborough Antennas and Propagation Conference (LAPC), Loughborough, UK, 12–13 November 2018; pp. 1–4.

5. Abdulraheem, Y.I.; Abdullah, A.; Mohammed, H.; Abd-Alhameed, R.; Noras, J. Plan of Frequency reconfigurable Multiband Compact Antenna utilizing two PIN diodes for WLAN/WiMAX Applications. IET Microw. Radio wires Propag. 2017, 11, 1098–1105. [CrossRef]

6. Al-Yasir, Y.I.A.; Tu, Y.; Bakr, M.S.; Parchin, N.O.; Asharaa, A.S.; Mshwat, W.A.; Abd-Alhameed, R.A.; Noras, J.M. Plan of multi-standard single/tri/quint-wideband unbalanced ventured impedance resonator channels with flexible TZs. IET Microw. Radio wires Propag. 2019, 13, 1637–1645. [CrossRef]

7. Liu, H.; Ren, B.P.; Li, S.; Guan, X.H.; Wen, P.; Peng, X.X.Y. High-Temperature Superconducting Bandpass Filter Using Asymmetric Stepped-Impedance Resonators with Wide-Stopband Performance. IEEE Trans. Appl. Supercond. 2015, 25, 1–6.

8. Al-Yasir, Y.I.A.; Tu, Y.; Parchin, N.O.; Abdulkhaleq, A.; Kosha, J.; Ullah, A.; Abd-Alhameed, R.; Noras, J. New Multi-standard Dual-wideband and Quad wideband Asymmetric Step Impedance Resonators Filters With Wide Stop Band Restriction. J.RF Microw. Comput. Helped Eng. 2019, 29, e21802.

ag4

by Qq Qq

Submission date: 15-Apr-2021 10:48AM (UTC-0700)

Submission ID: 1560158578

File name: again_3.pdf (1.9M)

Word count: 6145


Character count: 37301

A slotted microstrip patch antenna for wideband wireless applications with circular polarization

Submitted in partial fulfillment ¹³ of the requirements for the award of Bachelor of Engineering / Technology Degree in **ELECTRONICS AND COMMUNICATION ENGINEERING**

by

GADIKOTA REDDY CHAITANYA REDDY(Register No. 37130129) **GAJJALA ARUN KISHORE REDDY**(Register No. 37130130)



¹⁵ **DEPARTMENT OF ELECTRONICS AND COMMUNICATION ENGINEERING SCHOOL OF ELECTRONICS AND COMMUNICATION ENGINEERING**

SATHYABAMA

**INSTITUTE OF SCIENCE AND TECHNOLOGY
(DEEMED TO BE UNIVERSITY)**

Accredited with Grade "A" by NAAC

JEPPIAAR NAGAR, RAJIV GANDHI SALAI, CHENNAI - 600 119

MARCH 2021



SATHYABAMA

INSTITUTE OF SCIENCE AND TECHNOLOGY
(DEEMED TO BE UNIVERSITY)

Accredited "A" Grade by NAAC | 12B Status by UGC | Approved by AICTE
www.sathyabama.ac.in

DEPARTMENT OF ELECTRONICS AND COMMUNICATION ENGINEERING

BONAFIDE CERTIFICATE

This is to certify that this Project Report is the bonafide work of **GADIKOTA REDDY CHAITANYA REDDY** (Reg. No. 37130129) and **GAJJALA ARUN KISHORE REDDY** (Reg. No. 37130130) who carried out the project entitled **A SLOTTED MICROSTRIP PATCH ANTENNA FOR WIDEBAND WIRELESS APPLICATIONS WITH CIRCULAR POLARIZATION** under our supervision from December 2020 to March 2021.

Dr. I.REXILINE SHEEBA M.E.,ph.D
Internal Guide

Dr. T.RAVI, M.E,ph.D
Head of the Department

Submitted for Viva voce Examination held on _____

Name:

Signature:

Internal Examiner

External Examiner

DECLARATION

We **GADIKOTA REDDY CHAITANYA REDDY**(Reg. No. 37130129) and **GAJJALA ARUN KISHORE REDDY** (Reg. No. 37130130) hereby declare that the Project Report entitled **A SLOTTED MICROSTRIP PATCH ANTENNA FOR WIDEBAND AND WIRELESS APPLICATIONS WITH CIRCULAR POLARIZATION**

done by us under the guidance of **DR. I.REXILINE SHEEBA M.E, Ph.D** at sathyabama institute of science and technology is submitted ¹¹ in partial fulfillment of the requirements for the award of Bachelor of Engineering / technology degree in **ELECTRONICS AND COMMUNICATION ENGINEERING**.

GADIKOTA REDDY CHAITANYA REDDY

GAJJALA ARUN KISHORE REDDY

DATE:

PLACE:

SIGNATURE OF THE CANDIDATES

ACKNOWLEDGEMENT

We are pleased to acknowledge our sincere thanks to the Board of Management of SATHYABAMA for their kind encouragement in doing this project and for completing it successfully. We are grateful to them.

We convey our thanks to Dr. N. M. Nanditha., Dean, School of ELECTRONICS AND COMMUNICATION ENGINEERING and Dr. T.RAVI, M.E,Ph.D, Head of the Department, Dept. of ELECTRONICS AND COMMUNICATION ENGINEERING for providing us necessary support and details at the right time during the progressive reviews.

We would like to express our sincere and deep sense of gratitude to our Project Guide Dr. I.REXIINE SHEEBA M.E,Ph.D for her significant direction, ideas and steady consolation prepared for the fruitful consummation of our task work.

We wish to express our thanks to all Teaching and Non-teaching staff members of the Department of ELECTRONICS AND COMMUNICATION ENGINEERING who were helpful in many ways for the completion of the project.

TABLE OF CONTENTS

ABSTRACT

V

TABLE

VI

LIST OF FIGURES

VII

CHAPTER.NO	TITLE	PAGE. NO
1	INTRODUCTION	8
	1.1 ANTENNA	9
	1.2 ANTENNA PARAMETERS	11
	1.2.1 POWER GAIN	12
	1.2.2 EFFICIENCY	12
	1.2.3 DIRECTIVITY	13
	1.2.4 PATH LOSS	14
	1.2.5 RETURN LOSS	14
2	LITERATURE SURVEY	15
	2.1 DESIGN OF 16 ELEMENT RECTANGULAR PATCH ANTENNA ARRAY FOR 5G APPLICATIONS	15
	2.2 DESIGN METHODS	19
	2.3 THE MICROSTRIP PATCH ANTENNA CALCULATION PROCESS	19
	2.4 ADVANTAGES AND DISADVANTAGES OF MICROSTRIP PATCH ANTENNA	21
3	AIM AND SCOPE	24
	3.1 EXISTING SYSTEM	24
	3.2 DRAWBACKS	25
	3.3 PROPOSED WORK	25
	3.4 ABOUT SLOT, CIRCULAR POLARISATION	26
	3.5 SOFTWARE REQUIREMENT	
	3.6 SIMULATION TOOL	
4	RESULT	39
	4.1 ANTENNA WITH SLOT	39
	4.1.1 VSWR	
	4.1.2 RADIATION PATTERN	
	4.1.3 3D PATTERN	42
	4.2 ANTENNA WITHOUT SLOT	
	4.2.1 VSWR	
	4.2.2 RADIATION PATTERN	
	4.2.3 3D POLAR PLOT	
5	CONCLUSION	45
	5.1 REFERENCES	

LIST OF FIGURES

FIGURE NO	TITLE	PAGE NO
1.1	Antenna	11
2.6	Ansys HFSS 15.0.64 bit	28
4.1	Antenna with slot	37
4.1.1	VSWR	38
4.1.2	Radiation Pattern	39
4.1.3	:3D Pattern	39
4.2	Antenna without slot	41
4.2.1	VSWR	42
4.2.2	Radiation Pattern	43
4.2.2	2D polar plot	43

LIST OF SYMBOLS

Σ	Efficiency
Φ	azimuth
θ	altitude
W	length Extension
GHz	Gigahertz
Σr	Relative Permittivity
h	Thickness
L_{eff}	Effective Length
c	Speed of Light
f_0	Resonant Frequency
w	Width
dB	Decibel

**A SLOTTED MICROSTRIP PATCH ANTENNA FOR WIDEBAND
WIRELESS APPLICATIONS WITH CIRCULAR POLARIZATION**

ABSTRACT:

Circularly polarized diagonally regular slotted microstrip-patch antennas area unit planned with compact size. The compact circularly polarized (CP) diagonally regular slotted microstrip- patch (DSSMP) antenna style rules are summarized. Circularly polarized radiation is achieved victimization at random formed slots in diagonal directions on the sq. microstrip-patch antenna. totally different shapes for the slots area unit studied and compared, supported the fastened overall volume of the antenna for circularly polarized diagonally regular slotted microstrip-patch antennas. The cross-formed opening corner to corner symmetric opened microstrip-fix radio wire is smaller when contrasted and the round , square-, and roundabout ring-molded skew symmetric opened microstrip-fix receiving wires. A deliberate 3 dB pivotal proportion (AR) data transfer capacity of around 0.7% (6.0 MHz) with 2.0% (18.0 MHz) impedance data transmission was accomplished. The deliberate boresight acquired was more than 3.3 dBic over the operating band, while the overall antenna size was $0.272\lambda_0 \times 0.272\lambda_0 \times 0.0138\lambda_0$ at 0.905 GHz.

CHAPTER 1:**INTRODUCTION:**

The microstrip antenna has a number of useful properties such as small size, low-cost fabrication, low profile, light weight, ease of installation and integration with feed networks.

Microstrip receiving wire in its easiest structure comprises a transmitting patch which consists of a directing material like Copper or Gold¹⁶ on one side of a dielectric substrate and a ground plane on the opposite side. There are various states of receiving wire contingent upon its application. When all is said in done, the microstrip radio wire has numerous remarkable and alluring properties. These properties incorporate low profile, light weight, being conservative and comparable to mounting structure, simple creation and coordination with strong state gadgets. There are various and notable strategies to expand the transmission capacity of radio wires, including increment of the substrate thickness, the utilization of a low dielectric substrate, and the utilization of numerous resonators. Hence, the interest in multiband radio wires is expanding, particularly to decrease the quantity of receiving wires inserted in consolidating various applications on a solitary receiving wire.

ANTENNA:



In radio engineering, an antenna or aerial is that the ⁵ interface between radio waves propagating through space and electrical currents occupying metal conductors, used with a transmitter or receiver.[1] In transmission, a sender provides an electrical current to the radio wire's terminals, and along these lines the receiving wire transmits the energy from the current as electromagnetic waves (radio waves). In gathering, a receiving wire captures some of the force of an electromagnetic radiation to deliver an electrical flow at its terminals, that's applied to a collector to be intense. Receiving wires are elementary segments of all radio gear.

A receiving wire could be a sort of channel (components), electrically related to the recipient or transmitter. Receiving wires are meant to send and acquire radio waves all told even ways in which equally (omnidirectional radio wires), or specially a particular means (directional, or high-gain, or "shaft" radio wires). A receiving wire could incorporate segments not related to the transmitter, allegorical reflectors, horns, or parasitic

components that serve to coordinate the radio waves into a bar or alternative needed radiation style. Receiving wires are required by any radio beneficiary or transmitter and its electrical association with the magnetism field.[8] Radio waves are magnetism waves that facilitate signals through the air (or through space) at the speed of lightweight with virtually no transmission loss. associate degree automobile's whip antenna, a standard example of associate degree omnidirectional antenna. Antennas will be classified as omnidirectional, diverging energy or so equally all told directions, or directional, wherever energy radiates a lot of on one direction than others. (Receiving wires are corresponding, thus an identical impact happens for gathering of radio waves.) a completely uniform omnidirectional receiving wire is not actually conceivable. Some radio wire sorts have an even radiation style within the flat plane, however send very little energy upward or raining. A "directional" radio wire unremarkably is predicted to amplify its coupling to the magnetism field toward the opposite station.

ANTENNA PARAMETERS

An associate degree antenna is an electrical conductor or system of conductors
 Transmitter- Radiates magnetic force energy into house Receiver - Collects magnetic force energy from house

POWER GAIN

Power gain (or simply **gain**) is a Gain measure of the ability of the antenna to direct the input power into radiation in a particular direction and is measured at the peak radiation intensity. Consider the force thickness emanated by an isotropic radio wire with input power P_U a good way off R which is given by $S = P_0/4\pi R^2$. An isotropic antenna radiates equally in all directions, and its radiated power density S is found by dividing the radiated power by the area of the sphere $4\pi R^2$. An isotropic radiator is considered to be 100% efficient and also measure that combines an antenna's efficiency η_{antenna} and directivity D :

$$G = \eta_{\text{antenna}} \cdot D$$

EFFICIENCY

The efficiency η_{antenna} of an antenna is the total radiated power P_0 divided by the input power at the feedpoint

$$\eta_{\text{antenna}} = P_0/P_{\text{in}}$$

A transmitting antenna is supplied power by a feedline, a transmission line connecting the antenna to a radio transmitter.

The **input power** P_{in} to the antenna is typically defined to be the power supplied to the antenna's terminals (the *feedpoint*), so antenna power losses do not include power lost due to joule heating in the feedline and

reflections back down the feedline because of receiving wire/line impedance crisscrosses. The electromagnetic reciprocity theorem guarantees that the electrical properties of an antenna, such as efficiency, directivity, and gain, are the same when the antenna is used for receiving as when it is transmitting.

DIRECTIVITY

A radio wire's directivity is controlled by its radiation design, how the transmitted force is appropriated with heading in three measurements. All radio wires are directional to a more prominent or lesser degree, implying that they emanate more force in certain ways than others. The course is determined here in circular directions (θ, ϕ) where θ is the elevation or point over a predefined reference plane (like the ground), while ϕ is the azimuth as the point between the projection of the provided guidance onto the reference plane and a predetermined reference bearing (like north or east) in that plane with indicated sign (either clockwise or counterclockwise).

The dissemination of yield power as a component of the potential headings (θ, ϕ) is given by its radiation force $U(\theta, \phi)$ (in SI units: watts per steradian, $\text{W} \cdot \text{sr}^{-1}$). The yield power is acquired from the radiation force by incorporating the last over all strong points $d\Omega = \sin \theta \, d\theta \, d\phi$

PATH LOSS

Way misfortune typically incorporates proliferation misfortunes brought about by the characteristic extension of the radio wave front in free space (which normally takes the state of a consistently expanding circle), assimilation misfortunes (some of the time called infiltration misfortunes), when the sign goes through media not straightforward to electromagnetic waves, diffraction misfortunes when portion of the radio wave front is discouraged by a dark hindrance, and losses caused by other phenomena.

$$PL = P_t / P_r$$

RETURN LOSS

Return misfortune is a significant boundary when testing a receiving wire. It is identified with impedance coordinating and the greatest exchange of force hypothesis. It is also a measure of the effectiveness of an antenna to deliver power from source to antenna. The return loss (**RL**) is defined by the ratio of the incident power of the antenna (P_{in}) to the power reflected back from the antenna of the source (P_{ref}) the mathematical expression is

$$R = 10 \log_{10}(P_i / P_r)$$

CHAPTER 2:

LITERATURE SURVEY:

DESIGN OF 16 ELEMENT RECTANGULAR PATCH ANTENNA ARRAY FOR 5G APPLICATIONS

Vishnumolakala Jyothika 1, Madu Sai Pooma Chandra Shekar
2, Sagiri Vamsi Krishna³, Md. Zia Ur Rahman

This paper addresses the arrangement of a 16 component rectangular fixed cluster radio wire for 5G applications that gives a reasonable exchange speed of around 28 GHz. This is the most segment of this game-plan could be a rectangular fix accepting wire laid out on the Rogers RT/Duroid 5880 substrate ($\epsilon_r = 2.2$, $\tan\delta = 0.00009$), which is reproduced and enhanced using an economically industrially accessible recreation program. Length of rectangular fix antenna is 3.58 and breadth is 4.52. Within the later a long time the improvement in communication frameworks demand the advancement about low cost, negligible weight and low-profile radio wires this are able of keeping up tall execution over a wide range of frequencies

A New and Compact Wide-Band Microstrip Filter-Antenna Design for 2.4 GHz ISM Band and 4G Applications

Yasir I. A. Al-Yasir ¹ , Mohammed K. Alkhafaji ² , Hana'a A. Alhamadani ²

Another and smaller four-shaft wide-band planar channel radio wire configuration is proposed in this article. The impact of the dielectric material sort on the attributes of the plan is additionally explored and introduced. The channel radio wire structure is framed by a fourth-request planar band-pass channel (BPF) with a monopole microstrip receiving wire. The planned channel receiving wire works at a middle recurrence of 2.4 GHz and has a moderately wide-band impedance data transfer capacity of about 1.22 GHz and a partial data transfer capacity (FB W) of about half. The impacts of three distinct sorts of substrate material, which are Rogers RT5880, Rogers RO3003, and FR-4, are examined and introduced utilizing a similar arrangement.

Koch limit on the square fix microstrip receiving wire for ultra wideband applications

Manisha Gupta, Vinita Mathur.

In this paper a novel smaller microstrip feed square fix receiving wire with right calculated isosceles Koch fractal math on its edges is intended for ultra wideband applications. The emanating patch is changed in a few stages to accomplish a multiband circularly energized radio wire. The fractal radio wire is reenacted utilizing CST Microwave Studio Simulator. Radio wire's exhibition is then contrasted with symmetrical Koch, Minkowski and Sierpinski fractal calculations.

Plan Of Multiband Microstrip Patch Antenna For Wlan,Wimax And X-Band Applications

Pronami Bora, Challapalli gunasekhar, Pathan Sameer khan, Kokatam.vinay reddy, Marthala.Venkat sai, P. Pardhasaradhi

This letter depicts a little, single-feed, circularly enraptured fixed radio wire for broadband. The radio wire comprises a microstrip fix and pins on the Reactive Impedance Surface (RIS) enlivened by metamaterials. The RIS structure, comprising 4 or 4 standard metallic square fixes and four shorting pins which assists with improving the receiving wire data transfer capacity. The last enhanced design displays an impedance data transfer capacity of $53.757c(4.650GHz-7.617GHz)$ along with a 3-dB pivotal proportion

data transfer capacity of $30.47c(4.6242GHz-6.3036GHz)$. In addition, the proposed radio wire yields a decent main side increase of 5.8 dBi at 5.52Ghz

DESIGN METHODS

After the discussion of the simplified formulation in previous sections, the procedure for designing a rectangular microstrip patch antenna is explained. In this procedure there are three essential parameters for the design: the frequency of operation f , the dielectric constant of the substrate ϵ_r and the height of the dielectric substrate h

For a given ϵ_r and h , we design a microstrip antenna for the resonant frequency f_r (finding the width and length of the patch).

THE MICROSTRIP PATCH ANTENNA

Computation PROCESS

Plan EQUATION:

The Microstrip Patch Antenna Calculation Process

Stage 1: Calculation of the Width (W) -

Stage 2: Calculation of the Effective Dielectric Constant. This depends on the tallness, dielectric steady of the dielectric and the determined width of the fixed receiving wire.

Stage 3: Calculation of the Effective length

Stage 4: Calculation of the length expansion ΔL

Stage 5: Calculation of real length of the fix

Where the accompanying boundaries are utilized

f_0 is the Resonance Frequency W is the Width of the Patch

L is the Length of the Patch

h is the thickness

ϵ_r is the general Permittivity of the dielectric substrate c is the Speed of light: 3×10^8

ADVANTAGES AND DISADVANTAGES OF MICROSTRIP PATCH ANTENNAS

The benefits of microstrip fix receiving wires are:

1. Planar, which can likewise be made conformal to a molded surface
2. Low profile
3. Low radar cross-area
4. Rough
5. Can be created by printed circuit innovation
6. Can be incorporated with circuit components
7. Can be intended for double polarization activities

8.Can be intended for double or multi-recurrence activities

9.These benefits make microstrip fix radio wires considerably more appropriate for airplanes, space apparatus, and rockets than regular receiving wires as they do not meddle with the streamlined features of these moving vehicles. Their planar profiles are to appear differently in relation to those of the varieties of microstrip fix radio wires made conformal to a wing shape surface. In view of the benefits recorded over, the microstrip fix radio wire has likewise gotten the top pick of receiving wire architects for business portable and remote correspondence frameworks.



DISADVANTAGES OF MICROSTRIP PATCH ANTENNAS

There are several disadvantages associated with microstrip patch antennas.

1.In its basic form, the microstrip antenna has a narrow impedance bandwidth, typically less than 5%. However, various bandwidth-widening techniques have been developed. Up to 50% bandwidth has been achieved.

2.It is by and large obvious that more extensive data transfer capacity is accomplished with the penance of expanded radio wire actual volume.

3.Due to the small separation between the radiating patch and its ground plane, the microstrip antenna can handle relatively low RF power. The average power considered safe is a few tens of watts.

4.  misfortune generally happens .

CHAPTER 3:

AIM AND SCOPE:

EXISTING SYSTEM

- In the existing work designs of both planar ultra-wide band (UWB) antenna and UWB antenna with two rejected bands are given.
- The antenna consists of a rectangular patch etched on the FR4- substrate with a feed line.

- The rectangular patch has one round cut at each corner with one slot in the ground plane.
- The tuning bands achieved by inserting slots in the patch and the feed.
- The impact of these substrates on the impedance bandwidth, efficiency and gain of the antennas is Analyzed.
- Sonnet suite software has been used here to design.

DRAWBACKS

- Low impedance bandwidth.
- Low gain.
- Extra radiation occurs from its feeds and junctions.
- It supports only linear polarization.

PROPOSED SYSTEM

- The proposed work deals with the design of a slotted patch antenna that will be designed and analysed for wireless applications.

- Patch will be tuned in order to achieve circular polarization.
- Design will be analysed with and without slots and with various types of slots in order to enhance the performance.
- Rogers substrate material will be used in the design.
- Both wave port feed and coaxial line feed will be analysed to find which feed gives better performance.
- Various parameters like return loss, bandwidth, gain, directivity and radiation patterns will be analysed.
- The design will be developed ,Analysis will be carried out for simulated and Measured results.
- HFSS 15.0 software has been used here to design the Antenna.

ABOUT SLOT,CIRCULAR POLARIZATION

- Circularly spellbound (CP) microstrip radio wires have been famously utilized in different contemporary remote correspondences frameworks, for example, ⁹for satellite correspondence, WLAN (Wireless Local Area Network) and WiMAX (Worldwide Interoperability for Microwave Access),GPS (Global Positioning System),RFID (Radio-

frequency identification) tag and RFID readers because of the versatile orientation of the transmitter and receiver.

- Slot antennas are usually used at [UHF](#) and [microwave](#) frequencies. They are used in standard laboratory [microwave](#) sources used for research, UHF television transmitting antennas, antennas on missiles and aircraft, [sector antennas](#) for [cellular base stations](#), and particularly [marine radar](#) antennas. A slot antenna's main advantages are its size, design simplicity, and convenient adaptation to mass production using either waveguide or PC board technology.

SOFTWARE REQUIREMENTS

Ansys hfss 15.0 (64 bit)

SIMULATION TOOL

¹ Ansys HFSS is a 3D electromagnetic (EM) reproduction programming for planning and reenacting high-recurrence electronic items like radio wires, receiving wire clusters, RF or microwave parts, high velocity interconnects, channels, connectors, IC bundles and printed circuit sheets. Architects overall use Ansys HFSS to plan high-recurrence, rapid hardware found in interchanges frameworks, radar frameworks, progressed driver help frameworks (ADAS), satellites, web-of-things (IoT) items and other high velocity RF and computerized gadgets.

HFSS (High Frequency Structure Simulator) utilizes adaptable solvers and a natural GUI to give you unmatched execution in addition to profound knowledge into all your 3D EM issues. Through mix with Ansys warm, underlying and liquid elements devices, HFSS gives an amazing and complete multiphysics investigation of electronic items, guaranteeing their warm and primary unwavering quality. HFSS is inseparable from best quality level exactness and dependability for handling 3D EM challenges by excellence of its programmed versatile cross section strategy and refined solvers, which can be sped up through elite figuring (HPC) innovation.

The Ansys HFSS reproduction suite comprises a complete arrangement of solvers to address assorted electromagnetic issues going in detail and scale from aloof IC parts to amazingly huge scope EM investigations, for example, auto radar scenes for ADAS frameworks. Its dependable programmed versatile network refinement allows you to zero in on the plan as opposed to investing energy deciding and making the best lattice. This mechanization and ensured exactness separates HFSS from any remaining EM test systems, which require manual client control and various answers to guarantee that the created network is appropriate and precise. With Ansys HFSS, the material science characterizes the cross section as opposed to the lattice characterizing the physical science.

8
plan
lifts your item's
. Beat the opposition and catch your
market with Ansys HFSS.

ANSYS HFSS 15.0 64 BIT

HFSS FOR ANTENNA SIMULATION:

Antennas are virtually everywhere .From business applications, for

example, cell phones, RFID labels, and remote printers, to safeguard applications, for example, staged exhibit radio wires for airplane radar frameworks or satellite-based, to give coordinated ground based communication systems. Electromagnetic reenactment is an important device in receiving wire plan and stage coordination giving the fashioner the capacity to basically plan and assess the possibility of situations just as checking the last fabricated plan. ANSYS HFSS dominates at a wide assortment of high recurrence, full-wave, electromagnetic applications including radio wire plan and arrangement since it utilizes various progressed solver strategies to reenact the receiving wire as well as the impacts of its connection with the whole framework, including the taking care of framework just as the stage.

settling on it is a definitive instrument of decision for receiving wire recreation. Bus driving 3D electromagnetic (EM) recreation instrument for high recurrence and fast electronic segments. Figure 1 features a few receiving wire related applications with accentuation on

radio wires close by different constructions. With various reenactment advances and incredible mechanized versatile lattice refinement giving best quality level exactness, HFSS can help receiving wire planners who are continually tested with carrying out plans across increasingly more recurrence groups inside a more modest and more modest impression. With these extra specialized difficulties alongside the always contracting time to showcase, recreation with HFSS is an unquestionable requirement in the receiving wire plan and incorporation measure. Scaling down of the radio wires, restricted channel transfer speed, decreased plan time, and receiving wire association with different parts present solid difficulties to the plan engineer. HFSS gives programmed, precise, and proficient answers for beat execution portrayal, for example, return misfortune, input impedance, gain, directivity and an assortment of polarization attributes can be investigated in HFSS. Key post-preparing highlights, for example, the capacity to overlay the 3D far-field design on the receiving wire mesh can give the architect important knowledge and direct relationship between the radio wire and the subsequent radiation design. HFSS likewise offers electric and attractive field perception both in the close field and far-field giving plan understanding that isn't effectively accessible through estimation. This knowledge permits the architect to decide the segments of the mesh pertinent to the antenna's performance. Combined with Optimetrics™, HFSS likewise permits specialists to parametrically clear plan varieties to examine the radio wire's plan space utilizing such improvement methods as Quasi Newton, Pattern Search, Sequential Nonlinear Programming (SNLP), Blended Integer SNLP, and hereditary calculations. This modern degree of investigation that can give plan sensitivities and data on by and large measurable execution and assembling yields permit the designer to go to creation and market with trust in outcomes and execution. Programmed Adaptive Meshing A vital element of HFSS is programmed versatile lattice refinement which creates a precise arrangement dependent on the material science or electromagnetics of the plan. This mechanized fitting procedure leaves the attention on the receiving wire plan

instead of investing energy deciding and making the best lattice. This computerization and ensured precision separates HFSS from any remaining electromagnetic test systems, which commonly require manual client controls to guarantee that the produced network is reasonable and exact for recreation.. Without the correct mesh, the results from such simulators can be erroneous. But with automatic adaptive meshing, HFSS lets the physics define the mesh and not the other way around and guarantees accurate results. The meshing algorithm adaptively refined the mesh throughout the geometry; it iteratively adds mesh elements in areas where a finer mesh is needed due to the localized electromagnetic field behavior. Figure 2 shows the versatile lattice measure for a fixed radio wire working at 11.5 GHz utilizing the limited component strategy (**FEM**) in HFSS.

The merits of automatic adaptive meshing are:

- The cross section size is right and reasonable for proficient reenactments prompting profoundly exact arrangements.
- Such a procedure dependably 'tunes' the cross section to the electrical conduct of the receiving wire
- You don't have to be a cross section master and you can zero in on the plan instead of the reproduction arrangement.
- You can investigate plan alternatives rapidly and economically and diminish the quantity of models.
- Fewer or no models guarantee enormous investment funds on schedule and cash on equipment advancement and testing.

- top to bottom investigation of the plan and its electromagnetic conduct that is absurd from the customary form and test theory. You just need to make the math, indicate material properties, limit conditions, excitations, and arrangement recurrence and HFSS deals with the rest

Radio wire Simulation Technologies in HFSS

HFSS offers the accompanying reproduction strategies and devices relying on the sort of issue you need to tackle:

- Finite Element Method (Enabled with HFSS)
- Integral Equations (Enabled with HFSS-IE)
- Physical Optics (Enabled with HFSS-IE)
- FEM Transient (Enabled with HFSS-TR)
- Antenna Design Toolkit gave HFSS including more than 50 standard radio wire plans Finite Element Method The limited component strategy is exceptionally appropriate for 3D discretionarily molded geom

Finite Element Method:

The finite part methodology is extremely suited to 3D arbitrarily-shaped geometries. In this strategy, the mathematical model is consequently isolated into various tetrahedral components conformal to all surfaces of the calculation. Tetrahedral elements are highly suited for this type of unstructured and non-uniform mesh since they can be stretched and pulled to fit any arbitrary geometry. The finite element formulation uses advanced mathematical techniques to satisfy Maxwell's Equations in the entire model. This method handles complex materials and geometries efficiently. FEM settles the model by making a volume based lattice and produces field arrangements. As demonstrated in Figure 3, the fields are expressly settled all through the whole volume — not simply the radio wire and the item to which it is coupled (for this situation the human head) however additionally the setting within which it's placed. The example shown within the Figure three illustrates a smartphone close to a phantom model of the caput that simulates realistic specific absorption rate (SAR) measurements. The answer takes advantage of HFSS' FEM thinker and HFSS Optimetrics to

specify the position of the smartphone. This assists associations with meeting administrative consistency before their items hit the market. Accuracy within the SAR mensuration saves duplication of efforts and activity.

Integral Equations :

HFSS-IE shares identical modeller interface and analysis setup as HFSS and is enforced as a style kind within the HFSS desktop. Existing HFSS users find HFSS-IE genuinely like HFSS and along these lines require negligible preparation for successful use. IE utilizes the 3D Method of Moments (MoM) procedure for effectively taking care of open radiation and dissipating issues where flows are tackled on a superficial level lattice as demonstrated in Figure 4. This is the best solver for structures that are basically metal yet may in like manner join dielectrics. The receiving wires addressed are in an open climate accordingly no radiation limit or air volume is required just like the case with HFSS and limited components. You can utilize the IE solver for productive investigation of electrically huge metallic designs where applications could incorporate, receiving wire situation on vehicles, RCS, and reflector radio wire examination. HFSS-IE offers the significant benefit of utilizing the versatile cross estimate (ACA) strategy for enormous issue sizes. The ACA procedure gives


diminished machine assets to a mater goal, though being undeniably fit to the mechanized accommodative cross section algorithmic principle used by HFSS-IE. Hybrid FEM-IE Solution HFSS offers the capacity to use the strength of both limited component technique (HFSS) and basic conditions strategy (HFSS-IE) into a solitary issue. A particularly crossover arrangement is exceptionally beneficial. HFSS-IE can be utilized to settle for the field spread through free space and along transmitters outside the FEM volume utilized normally to show the nitty gritty calculation and dielectrics of the receiving wire parts killing the necessity for a FEM volume network all through. Moreover, the IE solution region can be contiguous with the FEM region such that currents flow from one solution domain to another. Figure half dozen illustrates the appliance of the combined FEM and that is hybrid answer on 2 antenna structures. The first is a full wave arrangement of a reflector receiving wire 60 frequencies in breadth with a mind boggling 3D feed horn. The feed horn is solved using HFSS' FEM solution and the main reflector and sun-reflectors are solved using IE. This large problem was solved in 37GB RAM in only 3. 2 hours. The second example in Figure half-dozen could be a satellite with an associated array of helix antennas mounted on its prime surface. For this situation the IE strategy is utilized to shorten the FEM locale in a successful engrossing limit condition. A conformal air box is put

round the satellite on that FE-BI is applied prompting multiple times
RAM decrease over Associate in Nursing FEM exclusively answer


CHAPTER 4:

RESULT ANALYSIS:


MICROSTRIP PATCH ANTENNA WITH SLOT




RESULT




VSWR:




3D PATTERN DESIGN:






Radiation Pattern






ANTENNA DESIGN WITHOUT SLOT






3D polar Plot



Radiation Pattern 4



ADVANTAGES:

- 1 .Ease of manufacturing.
- 2.High Gain.
- 3 Microstrip fix radio wires are effective radiators.
- 4 Simple in combination with microwave coordination circuits.

COMPARISON:

Parameter	With Slot	Without Slot
Peak Directivity	18D	3D
Peak gain	8.7	3 . 4
VSWR	D.1055	21.41
Radiated Power	D.94w	0.17w
Accepted power	D.96w	0.25w
Incident Power	1w	1w
Radiation Efficiency	96%	69%
Axial Ratio	1.7	12
Polarization	Circular	Linear

CHAPTER 5:

CONCLUSION

Compact circularly polarized diagonally radially symmetrical slotted microstrip fix radio wires are examined and offered upheld very surprising framed slots. Any abstractly formed space can be used to achieve circularly enchanted radiation with an accepting wire of more modest size. The cross-circle molded slantingly symmetric opened microstrip fix receiving wire for circularly energized radiation is the awesome correlation with various 2 openings. It's been shown that by powerful the overall borders of the openings, the in activity band of the receiving wire is regularly tuned with brilliant circularly spellbound radiation for an ideal working frequency. So the microstrip fix getting wire for low return incident, high expansion and high 3-dB AR information move limit has been produced and likely cultivated for ISM band applications. The previously mentioned abilities of the antenna have been achieved by cutting slots of various shapes (cross-circle, L and flower slot). Measured results (S_{11}) believe the simulated values. From the experimental results it's clear that the cross-circle configuration among the invented structures offers high 10-dB come loss information measure of fifty (2.38 to 2.50 GHz) and 3-dB axial quantitative relation information measure of twenty-two (2.435 to 2.465 GHz).

REFERENCES

1. Hussaini, A. Green Flexible RF for 5G. In Fundamentals of 5G Mobile Networks, 1st ed.; Rodriguez, J., Ed.; John Wiley and Sons: Hoboken, NJ, USA, 2015.
2. Rodriguez, J.; Radwan, A.; Barbosa, C.; Fitzek, F.H.P.; Abd-Alhameed, R.A.; Noras, J.M.; Jones, S.M.R.; Politis, I.; Galiotos, P.; Schulte, G.; et al. SECRET—Secure Network Coding for Reduced Energy cutting edge Mobile Small Cells: An European Training Network in Wireless Communications and Networking for 5G. In Proceedings of the 2017 Internet Technologies and Applications (ITA), Wrexham, UK, 12—15 September 2017; pp. 329—33
- 3.3. Parchin, N.O. Microwave/RF Components for 5G Front-End Systems; AVID SCIENCE: Telangana, India, 2020.
4. Al—Yasir, Y.; Abd—Alhameed, R.A.; Noras, J.M.; Abdulkhaleq, A.M.; Ojaroudi, N. Plan of Very Compact Comblined Band-Pass Filter for 5G Applications. In Proceedings of the Loughborough Antennas and Propagation Conference (LAPC), Loughborough, UK, 12—13 November 2018; pp. 1—4.
5. Abdulraheem, Y.I.; Abdullah, A.; Mohammed, H.; Abd—Alhameed, R.; Noras, J. Plan of Frequency reconfigurable Multiband Compact

Antenna utilizing two PIN diodes for WLAN/WiMAX Applications. IET Microw. Radio wires Propag. 2017, 11, 1098—1105. [CrossRef]

6. Al-Yasir, Y.I.A.; Tu, Y.; Bakr, M.S.; Parchin, N.O.; Asharaa, A.S.; Mshwat, W.A.; Abd-Alhameed, R.A.; Noras, J.M. Plan of multi-standard single/tri/quint-wideband unbalanced ventured impedance resonator channels with flexible TZs. IET Microw. Radio wires Propag. 2019, 13, 1637—1645. [CrossRef]

7. Liu, H.; Ren, B.P.; Li, S.; Guan, X.H.; Wen, P.; Peng, X.X.Y. High-Temperature Superconducting Bandpass Filter Using Asymmetric Stepped-Impedance Resonators with Wide-Stopband Performance. IEEE Trans. Appl. Supercond. 2015, 25, 1—6.

8. Al-Yasir, Y.I.A.; Tu, Y.; Parchin, N.O.; Abdulkhaleq, A.; Kosha, J.; Ullah, A.; Abd-Alhameed, R.; Noras, J. New Multi-standard Dual-wideband and Quad wideband Asymmetric Step Impedance Resonators Filters With Wide Stop Band Restriction. J.RF Microw. Comput. Helped Eng. 2019, 29, e21802.

ORIGINALITY REPORT

10%

SIMILARITY INDEX

4%

INTERNET SOURCES

5%

PUBLICATIONS

9%

STUDENT PAPERS

PRIMARY SOURCES

1

Submitted to Amity University

Student Paper

2%

2

Submitted to University of Wollongong

Student Paper

1%

3

Suraj Kumar, Manisha Gupta, Arun Kumar.
"Chapter 19 Breast Cancer Detection Based
on Antenna Data Collection and Analysis",
Springer Science and Business Media LLC,
2021

Publication

1%

4

www.worldscientific.com

Internet Source

1%

5

Submitted to University of Johannesburg

Student Paper

1%

6

Submitted to College of Engineering &
Technology Bhubaneswar

Student Paper

<1%

7

article.sapub.org

Internet Source

<1%

8	Submitted to Liberty Union High School District Student Paper	<1%
9	www.mdpi.com Internet Source	<1%
10	Submitted to BITS, Pilani-Dubai Student Paper	<1%
11	Submitted to Delhi Technological University Student Paper	<1%
12	Nasimuddin, , Zhi Ning Chen, and Xianming Qing. "Slotted Microstrip Antennas for Circular Polarization with Compact Size", IEEE Antennas and Propagation Magazine, 2013. Publication	<1%
13	Submitted to Sharda University Student Paper	<1%
14	Submitted to University of Bedfordshire Student Paper	<1%
15	Submitted to Khulna University of Engineering & Technology Student Paper	<1%
16	Submitted to Kuala Lumpur Infrastructure University College Student Paper	<1%

17

"A Compact Design of Ultra Wide Band Antenna with 5.5GHz to 5.9GHz Dual Band Characteristics", International Journal of Innovative Technology and Exploring Engineering, 2019

Publication

<1%

Exclude quotes On

Exclude matches Off

Exclude bibliography On