

DESIGN OF FISHERMAN SAFETY COMMUNICATION DEVICE USING LORA TECHNOLOGY

Submitted in partial fulfillment of requirements for the award of Bachelor of Engineering in
Electronics and Communication Engineering

by

J.VIJAY SUCHIT(37130166)



DEPARTMENT OF ELECTRONICS AND COMMUNICATION ENGINEERING

SCHOOL OF ELECTRICAL AND ELECTRONICS

SATHYABAMA

INSTITUTE OF SCIENCE AND TECHNOLOGY

(DEEMED TO BE UNIVERSITY)

Accredited with Grade "A" by NAAC

JEPPIAAR NAGAR, RAJIV GANDHI SALAI, CHENNAI – 600119

MARCH – 2021



SATHYABAMA

INSTITUTE OF SCIENCE AND TECHNOLOGY
(DEEMED TO BE UNIVERSITY)

Accredited with “A” grade by NAAC I 12B Status
by UGC I Approved by AICTE

Jeppiaar Nagar, Rajiv Gandhi Salai, Chennai – 600 119

www.sathyabama.ac.in



DEPARTMENT OF Electronics and Communication Engineering

BONAFIDE CERTIFICATE

This is to certify that this Project Report is the bonafide work of J.Vijay Suchit (37130166) who carried out the project entitled “**Design of fisherman Saftey communication device using lora technology**” under my supervision from December 2020 to March 2021.

Internal Guide

Mr.IMMANUEL RAJKUMAR ME., (Ph.D)

Head of Department

Dr.T.RAVI ME.,Ph.D.

Submitted for Viva voce Examination held on _____

Internal Examiner

External Examiner

DECLARATION

I ,J.VIJAY SUCHIT (37130166) hereby declare that the Project Report entitled “**Design of fisherman Saftey communication device using lora technology**” done by me under the guidance of Mr.IMMANUEL RAJKUMAR ME., (Ph.D). is submitted in partial fulfillment of the requirements for the award of Bachelor of Engineering degree in Electronics and Communication Engineering.

DATE:

PLACE:

SIGNATURE OF THE CANDIDATE

ACKNOWLEDGEMENT

I am pleased to acknowledge my sincere thanks to Board of Management of **SATHYABAMA** for their kind encouragement in doing this project and for completing it successfully. I am grateful to them.

I convey my thanks to **Dr.N.M.NANDHITHA M.E., Ph.D.** Dean, School of Electronics and Communication Engineering and **Dr.T.RAVI M.E., Ph.D.** Head of the Department, Department of Electronics and Communication Engineering for providing me necessary support and details at the right time during the progressive reviews.

I would like to express our sincere and deep sense of gratitude to our Project Guide **Mr.IMMANUEL RAJKUMAR ME (Ph.D).** for his valuable guidance, suggestions and constant encouragement paved way for the successful completion of my project work.

I wish to express my thanks to all Teaching and Non-teaching staff members of the Department of **Electronics and Communication Engineering** who were helpful in many ways for the completion of the project.

I would like to thank our beloved **PARENTS** for their constant love and support, without whom this wouldn't be possible and finally I would like to thank the **ALMIGHTY** for his wonderful blessing.

ABSTRACT

The tracking of a fisherman is being difficult when there is a bad weather conditions. To reduce the risk of missing the fisherman, sending the location of the fisherman plays a crucial role. In this project we are developing a model which tracks the fisherman location, pressure & temperature and sends the data to the base station through LoRa module. LoRa module can transmit the data through a long distance and the pressure, temperature parameters are taken to know the status of the weather at fisherman's end.

TABLE OF CONTENTS

CHAPTER NO	TITLE	PAGE NO
	ABSTRACT	
	LIST OF FIGURES	
	LIST OF TABLES	
1	INTRODUCTION	1
2	LITERATURE SURVEY	2-4
3	PROPOSED SYSTEM	5
4	4.1 LORA MODULE	6-7
	4.2 PARAMETERS OF LORA MODULE	9-10
	4.3 OPERATIONS OF LORA MODULE	10-12
	4.4 POWER SUPPLY STRATEGY	12
	4.5 LOW BATTERY DETECTOR	12
	4.6 FREQUENCY SYNTHESIS	13-14
	4.7 RECEIVER DESCRIPTION	14-17
	4.8 BMP 180 SENSOR	17-26
	4.9 GPS MODULE	27-37
	4.10 OLED DISPLAY	37-40
	4.11 TRANSMITTER CIRCUIT	41-44
	4.12 RECEIVER CIRCUIT	45-46
5	OUTPUT OF THE RECEIVER	47
6	CONCLUSION	48
	REFERENCES	49-50

LIST OF FIGURES

FIGURE NO	TITLE	PAGE NO
1.1.1	BLOCK DIAGRAM	6
1.1.2	LORA MODULE	7
1.1.3	FEATURES OF LORA MODULE	8
1.2.1	BMP 180 SENSOR	17
1.2.2	BMP180 SENSOR PIN OUT	18
1.3	TYPICAL APPLICATION CIRCUIT	20
1.4	MEASUREMENT FLOW OF BMP180	22
1.5	ALGORITHMS	24
1.6	PIN CONFIGURATION OF BMP180	25
2.1	GPS MODULE	27
2.1.1	CONNECTION OF NEO-6M TO ARDUINO	30
2.1.2	GPS OUTPUT	32
3.1	LOCATION OUTPUT	36
4.1	OLED DISPLAY	37
5.1	TRANSMITTER CIRCUIT	40
5.2	RECEIVER CIRCUIT	44
6.1	OUTPUT ON OLED DISPLAY	47
6.2	OUTPUT ON ARDUINO IDE	47

LIST OF TABLES

TABLE NO	TITLE	PAGE NO
1.1.1	PARAMETERS OF LORA MODULE	7
1.1.2	OPERATION OF LORA MODULE	12
1.1.3	OVER CURRENT PROTECTION	14
1.2.1	CORRECTION FACTOR	15
1.2.2	PIN DESCRIPTION	16
1.3.1	CHARECTERESTICS	19
1.3.2	ABSOLUTE MAXIMUM RATINGS	19
1.3.3	HARDWARE PRESSURE SAMPLING MODES	22
1.4	PIN CONFIGURATION OF BMP 180	26
1.5	PIN WIRING	29
1.6	PIN CONFIGURATION	38

CHAPTER-1

INTRODUCTION

The existing communication technologies, *e.g.* Wi-Fi, ZigBee, and Bluetooth, have an insufficient coverage area. While well known portable advancements like LTE, isn't the best arrangement as it requires tremendous force and exorbitant. One of the arrangements is utilizing Long-Range (LoRa) innovation. The utilization of LoRa networks is applied to give association benefits that require an all-inclusive scope of distance, low-bitrate, and low-power too. Today, the execution of LoRa for critical applications in day by day human existence gets perhaps the most mainstream subjects. Therefore, in this paper, we will focus on LoRa application as a fundamental technology for fishermen's safety involving several features such as: pressure, temperature, latitude& longitude location . Although the cellular signal still reaches the shore or even the territorial zone, a special communication device should be used by fishermen. It will be ineffective if they only use a smart phone as a communication device without additional modules because the signal strength of the cellular network cannot be predicted accurately. Moreover, the LoRa module can reach about 5-10 km distance from the shore. The system consisting of 1) GPS NEO-6M 2) LoRa module 3) BMP 180 Pressure+Temperature sensor 4) 12C OLED display 5) Arduino UNO. The proposed system has three functions as follows:

This proposed system can be employed as a fishermen tracker device.

Temperature &

Pressure at the sea level can be known.

CHAPTER-2

LITERATURE SURVEY

Title: Design and implementation of open LoRa for IOT

Author: Q. Zhou, K. Zheng, L. Hou, J. Xing and R. Xu

Long Range (LoRa) network is arising as perhaps the most encouraging low-power wide-region (LPWA) organizations, since it empowers the energy-requirement gadgets dispersed over wide zones to set up reasonable availability. Be that as it may, how to execute a practical and adaptable LoRa network is as yet an open test. This paper targets uncovering a possible arrangement of plan and execution, permitting clients to advantageously fabricate a private LoRa network for different IoT applications. Initial, a few commonplace application situations of LoRa network are talked about. At that point, the LoRa framework engineering is given the usefulness of every part. We address the equipment plan and execution of LoRa Gateway, which is the extension between LoRa hubs and LoRa network worker. Particularly, this paper contributes by proposing an improved programming engineering of LoRa network worker whose source codes are open on GitHub. Under the engineering, LoRa network worker is partitioned into four decoupled modules and utilizes the informing framework dependent on streaming information for the collaboration between modules to ensure adaptability and adaptability. At last, the broad investigations are directed to assess the presentation of LoRa networks in commonplace conditions.

Title: Design and Implementation of small monitoring wireless network system based on LoRa

Author: J. Wang, S. Yi, D. Zhan and W. Zhang

we center around the acknowledgment of a little natural checking remote impromptu organization sensor framework dependent on LoRa(Long Range) which gives a continuous ease significant distance observing framework. The framework uses the Heltec WiFi LoRa 32 as both passage and hubs. It embraces ESP32 chip as MCU

which has a significant degree of low-power execution in the business. The framework incorporates both LoRa module(SX1278) and WiFi module, which make the framework consolidate the significant distance transmission and low force utilization of LoRa correspondence with the help of TCP/IP network correspondence. Our framework can give an easy to understand front end that is advantageous for clients ongoing observing of the framework. We utilize an extraordinary arrangement of self-coordinating organization conventions to meet the prerequisites of day by day checking and crisis cautioning.

Title: Lora-based measurement station for water quality monitoring: Case of botanical garden poo

Author: B. Ngom, M. Diallo, B. Gueye and N. Marilleau

The coming of Internet of Things (IoT) has made simpler to fabricate number of utilizations. Truth be told, the far off observing or detecting has been worked with by the IoT. Various sensor hubs with a systems administration capacity can be sent to have a specially appointed or constant observing framework. Be that as it may, physicists at UCAD's Faculty of Science actually utilize conventional intends to gather their water quality information from a pool in the personnel's Botanical Garden with on location estimations. This pool is utilized for hydroponics and to concentrate some amphibian species. In this paper, we present a water quality observing framework through LoRa transmission. It's a minimal effort framework made out of a far off station for constant information assortment and a web stage for representation and abuse. To assess the dependability and proficiency of the framework, we play out some exhibition tests and the outcomes are likewise introduced.

[4]Title: Optimal Configuration of LoRa Networks in Smart Cities

Author: Gopika Premsankar Bissan Ghaddar Mariusz Slabicki Mario Di Francesco

Long reach (LoRa) is a remote correspondence standard explicitly focused for asset obliged Internet of Things (IoT) gadgets. LoRa is a promising answer for keen city applications as it can give long-range network a low energy utilization. The quantity of LoRa-based organizations is becoming because of its activity in the unlicensed radio groups and the simplicity of organization arrangements. Be that as it may, the versatility

of such organizations endures as the quantity of conveyed gadgets increments. Specifically, the organization execution drops because of expanded dispute and impedance in the unlicensed LoRa radio groups. This outcomes in an expanded number of dropped messages and, hence, untrustworthy organization interchanges. In any case, network execution can be improved by suitably arranging the radio boundaries of every hub. To this end, in this article we plan whole number direct programming models to arrange LoRa hubs with the ideal boundaries that permit all gadgets to dependably send information with a low energy utilization. We assess the presentation of our answers through broad organization reproductions thinking about various sorts of reasonable arrangements. We find that our answer reliably accomplishes a higher conveyance proportion (up to 8% higher) than the cutting edge with negligible energy utilization. Additionally, the higher conveyance proportion is accomplished by a huge level of hubs in each organization, subsequently bringing about a reasonable distribution of radio assets. At long last, the ideal organization arrangements are acquired inside a brief timeframe, generally a lot quicker than the best in class. Subsequently, our answer can be promptly utilized by network administrators to decide ideal arrangements for their IoT organizations, bringing about improved organization unwavering quality.

CHAPTER-3

AIM OF THE PROJECT:

The main theme of this project is to solve the problem of communication and safety of a fisherman. The communication problem arises due to network and this can be solved by LoRa module. The fisherman safety problem can be solved by getting the data of temperature, pressure & location of the boat using GPS module and coordinates are transferred through LoRa module.

SCOPE OF THE PROJECT:

This product can be used in fisherman boats for knowing the temperature, pressure and their location. This system uses the LoRa technology for long distance data transmission and data will be displayed on the OLED screen at the fisherman's side. With this system we can save the lives of fishermen by tracking them, especially when there is a bad weather fisherman can be known the situation with the help of pressure and temperature.

CHAPTER-4

4.1 HARDWARE REQUIREMENTS:

LoRa module SX1278

GPS NEO-6M

BMP 180 Barometric

Pressure Sensor Arduino

UNO

12C OLED display

BLOCK DIAGRAM:




Fig:1.1 Block Diagram

4.2 LORA MODULE:

LoRa is additionally founded on tweet spread range tweak which the partnership claims keeps up low-power qualities and essentially expands correspondence range. Twitter spread range has been utilized in military and space correspondence for quite a long time, yet LoRa is the principal ease execution for business utilization.

information rates. The determination of the information rate is a compromise between correspondence reach and message term. Because of the spread range innovation, correspondences with various information rates don't meddle with one another and make a bunch of "virtual" channels extending the constraint of the doorway.




Fig:1.1.2 Lora Module

For most extreme adaptability the client may settle on the spread range regulation transfer speed (BW), spreading factor (SF) and mistake amendment rate (CR).

4.3 FEATURES:

This part gives a critical level layout of the helpfulness of the SX1278 low-power, significantly consolidated handset. The going with figure shows an enhanced square outline of the SX1278.

contra



ptions and entryways is fanned out on different repeat channels

SX1278 is a half-duplex, low-IF handset. Here the got RF signal is first updated by the LNA. The LNA inputs are single finished to confine the outside BoM and for straightforwardness of plan. All basic constraints of the RF front end and motorized state machine are absolutely configurable through a SPI interface which offers acceptance to SX1278's arrangement registers. This circuits a mode auto sequencer that directs the change and game plan of the SX1278 between brief procedures for activity in the speediest time possible.

The SX1278 are equipped with both standard FSK and LoRa (Long Range) modems. Subordinate upon the mode picked either ordinary OOK or FSK balance might be utilized or the LoRa spread arrive at modem. The LoRa modem uses a prohibitive spread reach change technique. This change, rather than legacy balance

strategies, permits an addition in interface monetary arrangement and extended immunity to in-band impediment.

Simultaneously the recurrence resistance necessity of the gem reference oscillator is free - allowing an introduction increase for a diminishing in system cost. In FSK/OOK mode the SX1278 maintains standard change methodologies including OOK, FSK, GFSK, MSK and GMSK. The SX1278 is particularly fit to limit band correspondence thanks to the low-IF engineering utilized and the underlying AFC functionality. The LoRa modem utilizes spread range balance and forward mistake adjustment strategies to build the reach and strength of radio correspondence joins contrasted with conventional FSK or OOK based balance. Instances of the presentation improvement conceivable, for a few potential settings, are summed up in the table beneath. Here the spreading component and mistake revision rate are plan factors that permit the creator to advance the compromise between involved transmission capacity, information rate, interface spending improvement and invulnerability to obstruction.

Another significant aspect of the LoRa modem is its expanded invulnerability to impedance. The LoRa modem is fit for co-channel GMSK dismissal of up to 20 dB. This resistance to impedance allows the straightforward conjunction of LoRa regulated frameworks either in groups of weighty phantom use or in half breed correspondence networks that utilize LoRa to broaden range when inheritance adjustment plans fall flat.

4.4 LoRa DIGITAL INTERFACE:

The LoRa modem incorporates three sorts of modernized interface, static arrangement registers, status registers and a FIFO data support. All are gotten to through the SX1278's SPI interface - full nuances of every sort of register are given under.

LoRa Configuration Registers

Course of action registers are gotten to through the SPI interface. Registers are understandable in all device mode including Sleep. Regardless, they should be made particularly in Sleep and Standby modes. In the event that it's not all that much difficulty, note that the modified significant level sequencer (TLS modes) are not open in LoRa mode. The substance of the LoRa arrangement registers is held in FSK/OOK mode.

4.5 PRINCIPLE OF OPERATION

Because of its double port arrangement, it is feasible to at the same time store both send and get information in the FIFO data support. The Similarly, for beneficiary action, the register illustrates the point in the information cushion where data will be composed to in occasion of a get activity.

As a matter of course, the gadget is designed at power up with the goal that portion of the accessible memory is devoted to receiver.

Be that as it may, because of the touching idea of the FIFO information cradle, the base locations for sender and receiver are completely configurable across the 256 byte memory territory. Every pointer can be set autonomously anyplace inside the FIFO. To misuse the greatest FIFO information cushion size in send or get mode, the entire FIFO information support can be used in each mode by setting the base keeps an eye on RegFifoTxBaseAddr and RegFifoRxBaseAddr at the lower part of the memory (0x00).

The FIFO data support is cleared when the device is put in SLEEP mode, in this way no permission to the FIFO data support is possible in rest mode. Regardless, the data in the FIFO data pad are held while trading across the other LoRaTMmodes of activity, so a got parcel can be retransmitted with least information taking care of on the regulator side. The FIFO information support isn't self-clearing (except if the gadget is placed in

rest mode) and the information may be "eradicated" when another arrangement of information is composed into the involved memory area.

The FIFO information support area to be perused from, or written to, through the SPI interface is characterized by the location pointer RegFifoAddrPtr. Prior to any peruse or compose activity it is consequently important to instate this pointer to the relating base worth. After perusing or keeping in touch with the FIFO information support (RegFifo) the location pointer will then augmentation consequently.

4.6 Interrupts in LoRa Mode

Two registers are used to control the IRQ in LoRa mode, the register RegIrqFlagsMask which is used to cover the frustrates and the register RegIrqFlags which shows which IRQ has been trigged. In the register RegIrqFlagsMask, setting a piece to '1' will cover the meddle with, which implies this prevent is disactivated. Obviously all the upset are available. In the register RegIrqFlags, a '1' exhibits a given IRQ has been trigged and a while later the IRQ ought to be clear by making a '1'.

4.7 OPERATION OF THE LoRa MODEM

The functioning strategies for LoRa modem are gotten to by enabling LoRa mode. Dependent upon functioning mode picked the extent of convenience and register access is given by the going with table:

Table 1.1.2 OPERATION OF THE LoRa MODEM

Operating Mode	Description
SLEEP	Low-power mode. In this mode only SPI and configuration registers are accessible. Lora FIFO is not accessible. Note that this is the only mode permissible to switch between FSK/OOK mode and LoRa mode.
STANDBY	both Crystal oscillator and Lora baseband blocks are turned on. RF part and PLLs are disabled
FSTX	This is a frequency synthesis mode for transmission. The PLL selected for transmission is locked and active at the transmit frequency. The RF part is off.
FSRX	This is a frequency synthesis mode for reception. The PLL selected for reception is locked and active at the receive frequency. The RF part is off.
TX	When activated the SX1276/77/78/79 powers all remaining blocks required for transmit, ramps the PA, transmits the packet and returns to Standby mode.
RXCONTINUOUS	When activated the SX1276/77/78/79 powers all remaining blocks required for reception, processing all received data until a new user request is made to change operating mode.
RXSINGLE	When activated the SX1276/77/78/79 powers all remaining blocks required for reception, remains in this state until a valid packet has been received and then returns to Standby mode.
CAD	When in CAD mode, the device will check a given channel to detect LoRa preamble signal

is feasible to get to any mode from some other mode by changing the worth in the RegOpMode register

POWER SUPPLY STRATEGY

The SX1278 utilizes an interior voltage guideline conspire which gives stable working voltage, and thus gadget attributes, ludicrous mechanical temperature and working voltage extent of action. This consolidates up to +17 dBm of RF yield power which is

kept up from 1.8 V to 3.7 V and +20 dBm from 2.4 V to 3.7 V. The SX1278 can be controlled from any low-upheaval voltage source through pins VBAT_ANA, VBAT_RF and VBAT_DIG. Decoupling capacitors should be related, as suggested in the reference plan of the applications part of this record, on VR_PA, VR_DIG and VR_ANA pins to ensure right action of the inborn voltage regulators.

4.8 LOW BATTERY DETECTOR

A less battery locator is in like manner allowing the age of an encroach upon signal as a result of the reserve voltage plunging under a programmable edge that is adaptable through the register RegLowBat.

FREQUENCY SYNTHESIS

The jewel oscillator is the essential arranging reference of the SX1278. It is used as the reference for the PLL's repeat blend and as the clock signal for all high level dealing with.

The valuable stone oscillator startup time, TS_OSC, depends upon the electrical characteristics of the pearl reference used, for more information on the electrical assurance of the jewel . The pearl partners with the Pierce oscillator on pins XTA and XTB. The SX1278 overhauls the startup time and thus triggers the PLL when the oscillator signal is consistent.

Alternatively, an outside clock can be utilized to supplant the gem oscillator. This normally shows up as a tight obstruction temperature reimbursed valuable stone oscillator (TCXO). While using an external clock source the piece of register RegTcxo should be set to 1 and the external clock should be given on XTA should be left open. The top zenith adequacy of the data sign ought to never outperform 1.8 V. Evaluation of the CLKOUT signal engages direct programming overseeing of the hidden valuable stone obstruction. Note To restrict the current use of the SX1278, if it's not all that much difficulty, ensure that the CLKOUT signal is injured when not required

4.9 RC OSCILLATOR

All arranging assignments in the less-power Sleep state of the Top Level upon the accuracy of internal RC oscillator. This oscillator is thus changed at contraption power-up not requiring of customer input.

RF load conditions by the over current assurance block. This has the additional advantage of securing battery sciences with restricted pinnacle current ability and limiting most pessimistic scenario PA utilization in battery life computation. The current limiter esteem is constrained by the OcpTrim bits in RegOcp, and is determined by the accompanying formulae:

Table:1.1.3 OVER CURRENT PROTECTION

<i>OcpTrim</i>	I_{MAX}	<i>I</i> _{max} Formula
0 to 15	45 to 120 mA	$45 + 5 * OcpTrim$ [mA]
16 to 27	130 to 240 mA	$-30 + 10 * OcpTrim$ [mA]
27+	240 mA	240 mA

RECEIVER DESCRIPTION

The SX1278 highlights a computerized recipient with the simple to advanced change measure being performed straightforwardly following the LNA-Mixers block. Notwithstanding the LoRa regulation plan the low-IF beneficiary can demodulate MSK adjustment. All separating, demodulation, acquire control, synchronization and parcel taking care of is performed carefully permitting a serious level of programmable adaptability. The recipient likewise has programmed

acquire adjustment, this improves the exactness of RSSI estimation and upgrades picture dismissal.

In the collector working mode two conditions of usefulness are characterized. Upon introductory change to collector working mode the recipient is in the 'beneficiary empowered' state. In this express the collector anticipates for either the client characterized substantial preface or RSSI location model to be satisfied.

4.10 TEMPERATURE MEASUREMENT

An independent temperature estimation block is utilized to gauge the temperature in any mode with the exception. It is empowered naturally, .The aftereffect of the estimation is taken. Because of interaction varieties, the supreme exactness of the outcome is ± 10 °C. Higher accuracy requires an adjustment strategy at a known temperature. The figure underneath shows the impact of simply such an adjustment interaction.

Tab:1.2.1 Correction Factor

Correction Factor 15			
Actual Temp [Celsius]	RegTemp [Dec]	Temp before calibration [°C]	Temp after calibration [°C]
85	181	74	89
75	190	65	80
65	201	54	69
55	211	44	59
45	222	33	48
35	232	23	38
25	245	10	25
15	0	0	15
5	10	-10	5
-5	21	-21	-6
-15	33	-33	-18
-25	44	-44	-29
-35	56	-56	-41
-40	63	-63	-48

4.11 RESET OF CHIP

A power on reset of the SX1278 is set off at power up. Also, a manual reset can be given by controlling pin 7. A manual reset of the SX1278 is possible regardless, for applications in which VDD can't be really isolated. Pin 7 should be pulled low for 100 microseconds, and a while later conveyed. The customer should then keep things under control for 5 ms before using the chip.

4.12 BMP180 (DIGITAL PRESSURE SENSOR)




Fig:1.2.1 BMP180 Sensor Module




Fig:1.2.2 BMP180 Sensor Pinout

TYPICAL APPLICATIONS

Improvement of GPS route (dead-retribution, incline discovery, and so on)

In-and out-entryway route

Relaxation and sports

Weather forecast

Vertical velocity indication (rise/sink speed)

4.13 ELECTRICAL CHARACTERISTICS

The BMP180 includes a piezo-resistive sensor, a simple to front line converter and a control unit with E2PROM and a successive I2C interface. The BMP180 passes on the uncompensated appraisal of crushing component and temperature. The E2PROM has dealt with 176 piece of individual course of action information. This is utilized to remunerate balance, temperature reliance and different restrictions of the sensor..

Table:1.3.1

ABSOLUTE MAXIMUM RATINGS


Parameter	Condition	Min	Max	Units
Storage temperature		-40	+85	°C
Supply voltage	all pins	-0.3	+4.25	V
ESD rating	HBM, R = 1.5kΩ, C = 100pF		±2	kV
Overpressure			10,000	hPa

Table:1.3.2

4.14 OPERATION

The BMP180 is planned to be related clearly to a microcontroller of a wireless through I2C transport. The squeezing element and temperature data should be reimbursed by the arrangement data of E2PROM of BMP180.

The BMP180 includes a piezo-resistive sensor, a simple to front line converter and a control unit with E2PROM and a successive I2C interface. The BMP180 passes on the uncompensated appraisal of crushing component and temperature. The E2PROM has dealt with 176 piece of individual course of action information. This is utilized to remunerate balance, temperature reliance and different restrictions of the sensor.



UP = pressure data (16 to 19 piece) UT = temperature data (16 cycle)

Fig :1.3 Regular circuit

4.15 CALCULATING OF TEMPERATURE , PRESSURE

For all assessments presented here an ANSI C code is available from Bosch Sensortec. The microcontroller sends a starting game plan to start a squeezing element or temperature assessment. Subsequent to changing over time, the outcome esteem (UP or UT, separately) can be perused by means of the I2C interface. For ascertaining temperature in °C and pressing factor in hPa, the adjustment information must be utilized. These constants can be scrutinized out from the BMP180 E2PROM through the I2C interface at programming instatement.

The looking at rate can be extended up to 128 models each second (standard mode) for dynamic assessment. For the present circumstance, it is sufficient to measure the temperature just once each second and to use this motivating force for all squeezing factor assessments during a comparable




Fig:1.4Measurement flow BMP180

4.16 HARDWARE PRESSURE SAMPLING ACCURACY MODES

By utilizing various modes the ideal trade off between power utilization, speed and goal can be chosen, see underneath table.

Table:1.3.3

Mode	Parameter <i>oversampling_setting</i>	Internal number of samples	Conversion time pressure max. [ms]	Avg. current @ 1 sample/s typ. [μA]	RMS noise typ. [hPa]	RMS noise typ. [m]
ultra low power	0	1	4.5	3	0.06	0.5
standard	1	2	7.5	5	0.05	0.4
high resolution	2	4	13.5	7	0.04	0.3
ultra high resolution	3	8	25.5	12	0.03	0.25

All that modes can be performed at higher speeds, for instance up to multiple times each second for standard mode, with the current use extending moderately to the model rate.


4.13.1 CALCULATING PRESSURE AND TEMPERATURE

The mode (ultra low power, standard, high, ultra significant standard) can be picked by the variable `oversampling_setting` (0, 1, 2, 3) in the C code.

Calculation of authentic temperature and squeezing factor in steps of 1Pa (= 0.01hPa = 0.01mbar) and temperature in steps of 0.1°C. The going with figure shows the

itemized calculation for pressing factor and temperature estimation.

Calculation of pressure and temperature for BMP180



example:

AC1 = 408
AC2 = -72
AC3 = -14383
AC4 = 32741
AC5 = 32757
AC6 = 23153
B1 = 6130
B2 = 4
MB = -32768
MC = -8711
MD = 2868

C code function: type:

bmp180_get_cal_param

short
short
short
unsigned short
unsigned short
unsigned short
short
short
short
short

UT = 27898

long

oss = 0
= oversampling_setting
(ultra low power mode)

short (0..3)

bmp180_get_ut

bmp180_get_up

UP = 23843

long

X1 = 4743
X2 = -2344
B5 = 2339
T = 150

long

long

long

bmp180_get_temperature

temp in 0.1°C

BMP180_calpressure

B6 = -1601
X1 = 1
X2 = 56
X3 = 57
B3 = 422
X1 = 2810
X2 = 59
X3 = 717
B4 = 33457
B7 = 1171050000
p = 70003

long

long

long

long

long

long

long

long

long

long

ohne Ganzzahl Email

74774,47523

74774

3466,260617

3466

X1 = 74529
X1 = 3454
X2 = -7859
p = 69964

long

press. in Pa

Fig : 1.5 Calculation for pressing factor and temperature estimation

4.17 PIN CONFIGURATION

Picture shows the gadget in top view. Gadget pins are appeared here straightforwardly just for direction purposes.




Fig: 1.6 pin diagram

MOUNTING AND ASSEMBLY RECOMMENDATIONS

To accomplish the predefined execution for you plan, the accompanying suggestions and the "Dealing with, binding and mounting guidelines BMP180" ought to be thought about when mounting a pressing factor sensor on a printed-circuit board (PCB):

4.18 ADVANTAGES OF BMP180:

With the ultra low power and voltage plan, the BMP180 is ideal for cells, PDAs, GPS and other PDAs.

Low elevation noise, and I2C correspondence.

Fast response.

4.19 GPS(NEO-6)




Fig:2.1 GPS Module

NEO-6M overall arranging structure (GPS) module, a particularly renowned, monetarily astute, tip top GPS module with a pottery fix radio wire, an on-board memory chip, and a support battery that can be favorably organized with a sweeping extent of microcontrollers. These days, two NEO-6M GPS modules are incredibly mainstream — the GY-GPS6MV2 and the GY-GPSV3-NEO.

NEO-6M GPS motor on these modules is a serious decent one, and it likewise has high affectability for indoor applications. Moreover, there's one MS621FE-viable battery-powered battery for reinforcement and EEPROM for putting away setup settings. The module functions admirably with a DC contribution to the 3.3-to 5-V reach the GPS modules depend on the u-blox NEO-6M GPS motor. When utilizing the fix radio wire, it ought to be arranged corresponding to the geographic skyline. The recieving wire should have full perspective on the sky, guaranteeing an immediate view with however many obvious satellites as could be expected under the circumstances.

4.20 PIN WIRING

The NEO-6M GPS module has four pins: VCC, RX, TX, and GND. The module talks with the Arduino through consecutive correspondence using the TX and RX pins, so the wiring couldn't be

GPS RAW DATA

To get rough GPS data you just need to start a consecutive correspondence with the GPS module using Software Serial.

Parts needed for testing this model are

Arduino

NEO-6M GPS module

Jumper wires

SCHEMATICS

Wire the NEO-6M GPS module to your Arduino by following the schematic under.





Fig:2.1.1 Connection of NEO-6M and Arduino

Also, if your module uses a different default baud rate than 9600 bps, you should modify the code on the following line:

This sketch listen to the GPS serial port, and when data is received from the module, it is sent to the serial monitor.

Open the Serial Monitor at a baud rate of 9600.



The screenshot shows the 'COM4 (Arduino/Genuino Uno)' window in the Arduino IDE. The Serial Monitor is open, displaying a series of NMEA sentences received from a GPS module. The sentences are as follows:

```
$GPRMC,191550.00,A,4,00831.54551,W,0.041,,030118,,,A*66
$GPVTG,,T,,M,0.041,N,0.076,K,A*27
$GPGGA,19,00831.54551,W,1,08,0.95,122.6,M,50.1,M,,*43
$GPGSA,A,3,24,12,15,29,19,25,32,14,,,,,1.61,0.95,1.30*0B
$GPGSV,4,1,13,02,04,104,,06,04,075,12,10,17,257,,12,78,015,26*75
$GPGSV,4,2,13,14,17,317,16,15,17,161,31,17,02,029,,18,09,228,20*7F
$GPGSV,4,3,13,19,18,040,33,24,57,087,32,25,55,251,31,29,16,181,29*7F
$GPGSV,4,4,13,32,37,308,25*42
$GPGLL,4,00831.54551,W,191550.00,A,A*71
$GPRMC,191551.00,A,4,00831.54550,W,0.024,,030118,,,A*6A
$GPVTG,,T,,M,0.024,N,0.044,K,A*25
$GPGGA,19,00831.54550,W,1,08,0.95,122.6,M,50.1,M,,*4C
$GPGSA,A,3,24,12,15,29,19,25,32,14,,,,,1.61,0.95,1.30*0B
$GPGSV,4,1,13,02,04,104,,06,04,075,11,10,17,257,,12,78,015,26*76
$GPGSV,4,2,13,14,17,317,17,15,17,161,30,17,02,029,,18,09,228,20*7F
$GPGSV,4,3,13,19,18,040,33,24,57,087,32,25,55,251,31,29,16,181,29*7F
$GPGSV,4,4,13,32,37,308,25*42
$GPGLL,4,00831.54550,W,191551.00,A,A*7E
```

At the bottom of the window, the 'Autoscroll' checkbox is checked. The baud rate is set to '9600 baud' and the line ending is set to 'Both NL & CR'. There is a 'Clear output' button on the right.

Fig:2.1.2

You ought to get a lot of data in the GPS standard language, NMEA. Each line you get in the serial screen is a NMEA sentence.

NMEA represents National Marine Electronics Association, and in the realm of GPS, it is a standard information design upheld by GPS makers.

GETTING LOCATION DATA

You can work with the rough data from the GPS, or you can change over those NMEA messages into an understandable and important association, by saving the characters progressions into factors. To do that, we will use the TinyGPS++ library..

This library simplifies it to get data on the spot in an organization that is valuable and straightforward.

```
#include <TinyGPS++.h>
#include <SoftwareSerial.h>
static const int RXPin = 4, TXPin = 3;
static const uint32_t GPSBaud = 9600;
TinyGPSPlus gps;
```

The serial connection to the GPS device

```
SoftwareSerial ss(RXPin, TXPin);
```

```
void setup(){
  Serial.begin(9600);
  ss.begin(GPSBaud);
}
```

```
void loop(){
```

This sketch displays information every time a new sentence is correctly encoded.

```
while (ss.available() > 0){
  gps.encode(ss.read());
  if (gps.location.isUpdated()){
```

```

    Serial.print("Latitude= ");
    Serial.print(gps.location.lat(), 6);
    Serial.print(" Longitude= ");
    Serial.println(gps.location.lng(), 6);
  }
}
}

```

Tuned in is the place where you demand the data. To get TinyGPS++ to work, you need to more than once pipe the characters to it from the GPS module utilizing the `encode()` strategy.

```

while (ss.available() > 0){
  gps.encode(ss.read());
}

```

Then, you can query the `gps` object to see if any data fields have been updated:

```

if (gps.location.isUpdated()){
  Serial.print("Latitude="); Serial.print(gps.location.lat(), 6);
  Serial.print("Longitude="); Serial.println(gps.location.lng(),6);
}

```

Getting the extension and longitude is has clear has using `gps.location.lat()`, and `gps.location.lng()`, exclusively.

Move the code to your Arduino, and you should see the region appeared on the chronic screen. Subsequent to transferring the code, stand by a couple of moments while the module changes the situation to get a more precise information.




Fig:3.1

ADVANTAGES OF NEO-6M:

- It can follow up to 22 satellites on 50 stations and accomplishes the business' most basic level of affectability for example - 161 dB following, while at the same time devouring essentially 45mA stock current.

In contrast to various GPS modules, it can do up to 5 territory revives a second with 2.5m Horizontal position exactness..

4.21 OLED DISPLAY

The natural light-emanating diode (OLED) show, that is the 0.96-inch show with 128×64 pixels as demonstrated in the accompanying figure.



Fig:4.1 OLED DISPLAY

The OLED show doesn't need backdrop illumination, which brings about an exceptionally pleasant differentiation in dull conditions. Moreover, its pixels burn-through energy just when they are on, so the OLED show burns-through less force when contrasted and different showcases.

The model we're utilizing here has just four pins and speaks with the Arduino utilizing I2C correspondence convention. There are models that go with an extra pin. There are furthermore other OLED shows that pass on using SPI correspondence. Since the OLED show utilizes I2C correspondence convention, wiring is straightforward. You just need to associate with the




Fig: 4.2

5 CHAPTER

TRANSMITTER CIRCUIT:




Fig:5.1

4.21.1 TRANSMITTER CODE:

Transmitter code

<pre>#include <SPI.h> #include <LoRa.h> #include <Wire.h> #include <Adafruit_GFX.h> #include <Adafruit_SSD1306.h> #include <DHT.h> #define SCREEN_WIDTH 128 // OLED display width, in pixels #define SCREEN_HEIGHT 64 // OLED display height, in pixels // Declaration for an SSD1306 display connected to I2C (SDA, SCL pins) #define OLED_RESET LED_BUILTIN // Reset pin # (or -1 if sharing Arduino reset pin) Adafruit_SSD1306 display(SCREEN_WIDTH, SCREEN_HEIGHT, &Wire, OLED_RESET); #define DHTPIN 0 //pin where the dht11 is connected #define ss 15 #define rst 16 #define dio 2 int counter = 0; DHT dht(DHTPIN, DHT11); void setup() { Serial.begin(115200); dht.begin(); /SSD1306_SWITCHCAPVCC= generate display voltage from 3.3V internally if(!display.begin(SSD1306_SWITCHCAPVCC, 0x3C)) { // Address 0x3D for 128x64</pre>	<pre>Serial.println(F("SSD1306 allocation failed")); for(;;); // Don't proceed, loop forever } while (!Serial); Serial.println("LoRa Sender"); LoRa.setPins(ss, rst, dio0); if (!LoRa.begin(473E6)) { Serial.println("Starting LoRa failed!"); delay(100); while (1); } display.display(); delay(2); display.clearDisplay(); } void loop() { float h = dht.readHumidity(); float t = dht.readTemperature(); if (isnan(h) isnan(t)) { Serial.println("Failed to read from DHT sensor!"); return; } Serial.print("Temperature: "); Serial.print(t); Serial.print(" degrees Celcius, Humidity: "); Serial.println(h); Serial.println(h); Serial.println(); Serial.print("Sending packet: "); Serial.println(counter);</pre>	<pre>display.clearDisplay(); display.setTextSize(2); // Normal 1:1 pixel scale display.setTextColor(WHITE); // Draw white text display.setCursor(0,0); // Start at top-left corner display.print(F("Pkt No:")); display.print(counter); display.setCursor(0,20); display.print("Tem:"); display.print(t); display.print("C"); display.setCursor(0,40); display.print("Hum:"); display.print(h); display.print("%"); display.print(""); display.display(); // send packet LoRa.beginPacket(); LoRa.print(F("Pkt No:")); LoRa.println(counter); LoRa.print("Temp: "); LoRa.print(t); LoRa.println("C"); LoRa.print("Hum: "); LoRa.print(h); LoRa.print("%"); LoRa.print(""); LoRa.println(""); LoRa.endPacket(); counter++; delay(3000); }</pre>
--	---	--

4.22 RECEIVER CIRCUIT:

Fig:5.2

4.22.1 RECEIVER CODE:

Code for Receiver

```
#include <SPI.h>
#include <LoRa.h>

#define ss 15
#define rst 16
#define dio0 4

void setup() {
  Serial.begin(115200);
  while (!Serial);

  Serial.println("LoRa Receiver Callback");

  LoRa.setPins(ss, rst, dio0);

  if (!LoRa.begin(473E6)) {
    Serial.println("Starting LoRa failed!");
    while (1);
  }

  // register the receive callback
  LoRa.onReceive(onReceive);

  // put the radio into receive mode
  LoRa.receive();
}

void loop() {
  // do nothing
}

void onReceive(int packetSize) {
  // received a packet
  Serial.println("Received packet ");

  // read packet
  for (int i = 0; i < packetSize; i++) {
    Serial.print((char)LoRa.read());
  }
}
```

CHAPTER-5

5 OUTPUT OF THE TRANSMITTER:



Fig:6.1

5.1 OUTPUT OF THE RECEIVER:

COM7

```
{
received packet with Time of 12787 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100568, end
LoRa Receiver
received packet with Time of 713 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100576, end
received packet with Time of 2276 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100573, end
received packet with Time of 3652 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100575, end
received packet with Time of 5229 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100571, end
received packet with Time of 6606 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100572, end
received packet with Time of 7983 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100575, end
received packet with Time of 9360 with RSSI -114 with received data : %, 12.785254, 80.456314, 29.60, 100575, end
received packet with Time of 10737 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100571, end
received packet with Time of 12290 with RSSI -116 with received data : %, 12.785254, 80.456314, 29.60, 100577, end
received packet with Time of 13667 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100574, end
received packet with Time of 15228 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100567, end
}
```

CHAPTER-6

CONCLUSION

From the results the location of the fisherman, pressure and temperature are taken from GPS, Barometric pressure sensor and sent through LoRa module to the base station.

By using the GPS NEO-6M the tracking of the fisherman is obtained. So, the monitoring of the fisherman is made easy and smarter. This helps to get the status of the fisherman from time to time and period to period.

The sensors used in the project makes the fisherman to know about the pressure, temperature & location.

The tracking of the fisherman helps in decrease of the missing cases of the fisherman in bad weather conditions.

Finally, the main conclusion is, fisherman safety is mainly comes under his location, pressure and temperature criteria. By using the sensors these parameters can be sent through the base station and can track his status.

REFERENCES

1. Bharat Chaudhari, Marco Zennaro and Suresh Borkar, "LPWAN Technologies: Emerging Application Characteristics Requirements and Design Considerations", *Future Internet*, vol. 12, pp. 46, 2020.
- Q. Zhou, K. Zheng, L. Hou, J. Xing and R. Xu, "Design and Implementation of Open LoRa for IoT", *IEEE Access*, vol. 7, pp. 100649-100657, 2019
- A. Zourmand, A. L. Kun Hing, C. Wai Hung and M. AbdulRehman, "Internet of Things (IoT) using LoRa technology", *2019 IEEE International Conference on Automatic Control and Intelligent Systems (I2CACIS)*, pp. 324-330, 2019.
- .Kais Mekki, Eddy Bajic, Frédéric Chaxel and Fernand Meyer, A comparative study of LPWAN technologies for large-scale IoT deployment, vol. 5, pp. 1-7, 2019.
- J. Wang, S. Yi, D. Zhan and W. Zhang, "Design and Implementation of small monitoring wireless network system based on LoRa", *4th Advanced Information Technology Electronic and Automation Control Conference (IAEAC)*, pp. 296-299, 2019
- B. Ngom, M. Diallo, B. Gueye and N. Marilleau, "Lora-based measurement station for water quality monitoring: Case of botanical garden pool", *2019 IEEE Sensors Applications Symposium (SAS). IEEE*, pp. 1-4, 2019.
- .T. Addabbo, A. Fort, A. Mecocci, M. Mugnaini, S. Parrino, A. Pozzebon, et al., "A Lora-based IoT sensor node for waste management based on a customized ultrasonic transceiver", *2019 IEEE SensorsApplications Symposium (SAS). IEEE*, pp. 1-6, 2019.
- Dunlop, H. Nguyen, R. Barton and J. Henry, "Interference analysis for LoRa chirp spread spectrum signals", *Proc. IEEE Canadian Conf. of Electr. and Comput. Engin. (CCECE)*, May 2019
- A. Mahmood, E. Sisinni, L. Guntupalli, R. Rondon, S. A. Hassan and M. Gidlund, "Scalability analysis of a LoRa network under imperfect orthogonality", *IEEE Trans. Ind. Informat.*, vol. 15, no. 3, pp. 1425-1436, Mar. 2019.
- .M. Ji, J. Yoon, J. Choo, M. Jang and A. Smith, "LoRa-based Visual Monitoring Scheme for Agriculture IoT", *IEEE Sensors Applications Symposium*, 2019.
- T. Elshabrawy and J. Robert, "Interleaved chirp spreading lora-based modulation", *IEEE Internet of Things Journal*, pp. 1-1, 2019.

- E. Murdyantoro, I. Rosyadi and H. Septian, "Studi Performansi Jarak Jangkauan Lora-Drainage Sebagai Infrastruktur Konektivitas Nirkabel Pada WP-LAN", *Din. Rekayasa*, vol. 15, no. 1, pp. 47, 2019.
- .P. Devi, D. Istianti, S. Y. Prawiro, N. Bogi, A. Karna and I. A. Nursafa, "Analisis Performansi Teknologi Akses LPWAN LoRa Antares Untuk Komunikasi Data End Node", *Citee 2019*, pp. 24-25, 2019.
- .D. Croce, M. Gucciardo, S. Mangione, G. Santaromita and I. Tinnirello, "Impact of lora imperfect orthogonality: Analysis of link-level performance", *IEEE Commun. Lett.*, vol. 22, no. 4, pp. 796-799, April 2018.
- L. Feltrin, C. Buratti, E. Vinciarelli, R. D. Bonis and R. Verdone, "Lorawan: Evaluation of link- and system-level performance", *IEEE Internet Things J.*, vol. 5, no. 3, pp. 2249-2258, June 2018.
- 13.P. Gotthard and T. Jankech, "Low-cost car park localization using RSSI in supervised LoRa mesh networks", *2018 15th Workshop on Positioning Navigation and Communications (WPNC)*. IEEE, pp. 1-6, 2018.

DESIGN OF FISHERMAN SAFTEY COMMUNICATION DEVICE USING LORA TECHNOLOGY

by Plagiarism Check

Submission date: 19-Apr-2021 04:10AM (UTC+0930)

Submission ID: 1562570953

File name: ilovepdf_merged_NEW.docx (1.68M)

Word count: 4922

Character count: 26384

DESIGN OF FISHERMAN SAFETY COMMUNICATION DEVICE USING LORA TECHNOLOGY

ABSTRACT

When the weather is bad, it is difficult to find a fisherman. Serving your Hunter position plays a key role in reducing the chance of losing him. In this project, we create a model that monitors the hunter's position, fatigue and temperature and sends the information to the base station via the Lora module. The parameters of pressure and temperature are taken to know the condition of the weather at the end of the fisherman using the Lora module, which can transmit data over long distances.

CHAPTER-1

INTRODUCTION

Wi-Fi, ZigBee and Bluetooth do not have adequate coverage for current network systems. However, popular mobile advances like LTE are not a viable option because they are more energy hungry and expensive. Long Range Range (LORA) technology is included in a plan. The use of Lora networks can be used to provide benefits to companies with a wide range of distances, low bitrate and low power consumption. Today, the use of Lora for basic applications of everyday human life is one of the most widely discussed topics. Consequently, the focus of this paper will be on applying Lora as a primary hunter protection technology, which will have many features such as pressure, temperature, longitude and latitude. Whether the cellular signal reaches the shore or the territorial field, hunters can use a specialized communication system. Since the signal quality of the telephone network cannot be accurately monitored, it will not be effective if they use the mobile phone as a communication system without additional hardware. In addition, the Lora unit has a range of 5-10 km from the sea. The device consists of the following components: 1) GPS NEO-6M; 2) GPS NEO-6M; And 3) GPS NEO 2) Lora Module 3) BMP 180 Pressure + Temperature Sensor 4) OLED Display (12C) 5) Arduino UNO Microcontroller Board. Here are three features of the proposed system:

This machine can be considered as a tracking unit for hunters.

Temperature and weather

It is possible to determine the pressure at sea level.

CHAPTER-2

LITERATURE SURVEY

Title: Design and implementation of open LoRa for IOT

Author: Q. Zhou, K. Zheng, L. Hou, J. Xing and R. Xu

Energy wide area networks (LPWAs) on the Long Range Grid (LORA) are the most promising, as it allows the deployment of power tools over large areas to demonstrate the availability of equal areas. Regardless, the mobilization of a practical and adaptable Lora network is already in progress. This paper aims to explore a potential planning and implementation plan that will enable clients to effectively build the Lora Network for various IoT applications. To get started, some common Laura network implementation scenarios are discussed. Each component is then provided with the Lora System Engineering utility. We are responsible for the design and deployment of Lora Gateway equipment, which is the link between Lora Hubs and Lora Network staff. This paper contributes in particular by proposing an improved programming architecture for Lora Network staff with Git Hub source codes. According to engineering, the Lora network operator is divided into four separate units and uses a consulting system based on data flow for unit collaboration, ensuring compatibility and compatibility. Finally, intensive inquiries are aimed at assessing the performance of Lora Networks in everyday situations.

Design and implementation of Loravan-based monitoring wireless network devices

Authors J. Wang, S. Yi, d. Han An and W. Ng Hong.

We focus on identifying the Lora (Long Range) Small Scale Improved Regulatory Sensing System based on the Lora (Long Range), which provides a meaningful continuous remote monitoring framework. Heltech WiFi is used as a corridor and gateway in the Lora 32 system. It uses the ESP32 processor as a microcontroller.

In the market, there is a lot of low-power implementation. The platform includes both the Lora (SX1278) and WiFi modules, enabling the system, via TCP/IP network connections, to connect the long distance transmission and Loras low power communication . Our platform has an easy-to-use front end that facilitates continuous customer monitoring of the framework. To meet our daily inspection and disaster warning needs, we use exceptional self-coordinated engagement agreements.

The status of the Botanical Garden stool as a Lora-based water quality metering station

Authors: B. Ngom, M. Diallo, B. Guay, and N. Marilyn.

The Internet of Things (IoT) has made it easy to create a wide range of applications. Honestly, I tried IoT monitoring or remote detection. Systems can send different sensor axes with management capabilities to create a dedicated or continuous monitoring device. On the one hand, UCAD physicists are using traditional methods to data on water quality from a botanical garden reservoir for staff, together with on-site calculations. The lake is used for hydroponics as well as for concentrating amphibians. In this article we present a method of monitoring water quality using a Lora transmitter. It is a low voltage system that includes a remote station for continuous data collection and a network platform for representation and violence. We perform several performance evaluations to determine the reliability and efficiency of the framework and the results are displayed.

[4] Title: Optimal Lora Network Configuration in Smart Cities

The author of this piece is Gopika Primeshankar. Bison Ghadar (Bison Ghadar) Slabecki, Marius Mario di Francisco is an Italian actor.

Long Range (Lora) is a remote communication standard specially designed for IoT devices requiring assets. Lora has a low-power long-range network as a potential solution for city applications.. Due to the ease of its operational and organizational structures in unlicensed

radio groups, the number of Lora-based companies is increasing. Regardless, compatibility is an added benefit.

3

As the number of distributed devices increases, the number of such companies increases. Growing dissent and resistance in the unlicensed Lora radio communities is hurting the company's implementation. As a result, there are more connections that have fallen and, as a result, there are unreliable interactions with the company. However, by properly maintaining the radio boundaries of each station, network performance can be improved. We therefore offer a full range of directory programming models with the aim of configuring Lora Hubs with ideal limitations that all tools can reliably display data while using minimum resources. We evaluate the performance of our responses using different structured versions while considering different affordable arrangements. We believe that our solution achieves a higher transmission ratio (8% higher) than the leading edge when using very few resources. This is achieved through a large number of hubs, resulting in a fair distribution of radio features. Finally, robust work arrangements are obtained in a shorter period of time and are much faster than the best in the classroom. As a result, network administrators use our solution to quickly select the best configuration. nts for their IoT organizations, bringing about improved organization unwavering quality.

CHAPTER-3

AIM OF THE PROJECT:

The main objective of this project is to solve the problem of connection and protection of fishermen. The Lora module solves the connection problem caused by the network. Fishermen's protection problem can be solved by using the GPS module to obtain data about the boat's temperature, pressure and position, and then transmit the coordinates through the Lora module.

SCOPE OF THE PROJECT:

This product can be used to determine the temperature, species and location of fishing vessels. This machine transfers data over long distances using Lora technology and is displayed on the OLED panel next to the data hunter. Fishermen's lives can be monitored with this machine, especially when the weather is bad, and the situation can be determined by pressure and temperature.

CHAPTER-4

4.1 HARDWARE REQUIREMENTS:

5 GPS NEO-6M

Pressure Sensor Arduino

LoRa module SX1278

12C OLED display

BMP 180 Barometric UNO

BLOCK DIAGRAM:




Fig:1.1 Block Diagram

4.2 LORA MODULE:

This product can be used to determine the temperature, species and location of fishing vessels. This machine transfers data over long distances using Lora technology and is displayed on the OLED panel next to the data hunter. Fishermen's lives can be monitored with this machine, especially when the weather is bad, and the situation can be determined by pressure and temperature.




Fig:1.1.2 Lora Module

Campaign control All options for transmission speed (BW), amplitude factor (SF) and error modulation rate maximum compatibility (CR).

4.3 Features: This section provides a sophisticated interface for the SX1278's most standard low power utility phone. Improved square diagram for SX1278 as shown in the diagram.

Lora also adopts tweet penetration, which the company claims preserves low-power features while extending connectivity. While Twitter has long been used in military and space communications, Lora operates most directly for commercial use. End-to-end

correspondence between two parties End-to-end correspondence




Fig1.1.3:Features of lora module

Components and portlets are separated by several repeating networks.

The SX1278 is a half-duplex low frequency smartphone. LNA was the first to upgrade the received RF signal. The LNA entries are completed one by one to keep the external BoM small and the design is easy. Minor RF front-end and automatic state limits can be fully configured via the SPI interface that accepts SX1278 order records. This circuit activates the auto mode sequencer, which specifies the transition and game plan in the SX1278 between shorthand actions to be executed in the shortest time available.

Both basic FSK and Lora modems are included in the SX1278. Depending on the mode selected, the normal OOK balance, FSK or Lora spread that comes with the modem can be used. The Lora modem uses a method called blocked campaign series update. Instead of using old-fashioned balancing methods, this step allows to increase the monetary alignment of the device and increase immunity to range barriers.

At the same time, the recurring capability requirements of the gem reference oscillator have been eliminated, which allows for better input and reduced device costs.

SX1278 performs common conversion methods in FSK / OOK format, including OOK, FSK, GFSK, MSK and GMSK. The low IF structure and basic AFC versatility of the SX1278 are ideal for reducing band message. Compared to traditional FSK or OOK based balance, the Lora modem uses promotional band balance and forward error correction techniques to increase the amplitude and strength of radio messaging links. The table below summarizes examples of possible rendering optimizations for some different scenarios. Circulation factor and error review rate are two variables that allow the constructor to strike a balance between transmission power, perception rate, change of interface cost and barrier resistance.

Another important feature of the Lora modem is the increased impedance resistance. The Lora modem handles up to 20 dB of co-channel GMSK splitting. This impedance tolerance simply integrates lora-controlled systems into groups of heavy dummy use or into half-strain correspondence networks that use lora when genetically modified plans fail.

Digital interface for Lora 4.4:

The Lora modem has three types of advanced interfaces: static order registers, state records and FIFO data support. All can be accessed via SPI gui on the SX1278; Detailed descriptions for each type of record are given below.

Configuration Recordings Laura

SPI is used to access transaction logs. Both application modes, including sleep, have understandable records. Either way, it should be displayed in sleep and standby modes. Keep in mind that the updated base level sequencer (TLS modes) is not available in Lora mode unless it is very problematic. FSK / OOK mode is used to store the content of Lora order records.

4.5 Principles of operation

Due to the dual port architecture it is possible to transmit storage and receive data in support of FIFO data at the same time. Similarly, in the case of nutrient operation, the record describes the location on the data pad where data is generated in terms of acquisition activity.

When needed, the device is programmed to boot so that most of the available memory is allocated to the receiver.

Regardless, the primary positions of the transmitter and receiver are fully configured around the 256-byte memory area, thanks to the FIFO Knowledge Bearer's tactile concept. Each index can be placed on its own anywhere in the first. The FIFO information reference is fully utilized in each mode by setting a rule that monitors RegFifoTxBaseAddr and RegFifoRxBaseAddr at the bottom of the memory to exploit the largest FIFO information pad size in sending or receiving mode (0x00).

When the system goes into SLEEP mode, support for FIFO data is cleared, but permission to support FIFO data is not available in the rest of the mode. Regardless, the data in the FIFO dashboard is stored when trading through multiple Lora trigger modes, allowing the regulator to manually replay the received parcel with minimal details. Auxiliary data is not FIFO auto-clearing (unless the device is in standby mode), and data can be "erased" if another data setting is configured in the included memory area.

The RegFifoAddrPtr Location Index defines a FIFO user-defined support field that can be read or written using the SPI interface. Consequently, it is important to set this index to the corresponding source value before starting any reading or writing operation. Reading or being in close contact with FIFO Knowledge Support (Regfifo) can enhance the position pointer.

4.6 Laura interrupts the style

In Lora mode, two r Exists are used to monitor IRO: ReglrqFlagsMask which is used to cover frustration and ReglrqFlags that display IRO-inspired ones. Setting the '1' section in the ReglrqFlagsMask registry protects against interference, which means that this block is disabled. The very interruption is obvious. The number "1" in the ReglrqFlags registry indicates that a specific IRO has been turned on and the IRO can be cleared by creating another "1".

4.7 Lora modem operating instructions

Enabling Lora Mode gives you access to Lora Modem working technologies.

The following table provides access and logging scope based on specific operating mode:

Table 1.1.2 OPERATION OF THE LoRa MODEM

Operating Mode	Description
SLEEP	Low-power mode. In this mode only SPI and configuration registers are accessible. Lora FIFO is not accessible. Note that this is the only mode permissible to switch between FSK/OOK mode and LoRa mode.
STANDBY	both Crystal oscillator and Lora baseband blocks are turned on. RF part and PLLs are disabled
FSTX	This is a frequency synthesis mode for transmission. The PLL selected for transmission is locked and active at the transmit frequency. The RF part is off.
FSRX	This is a frequency synthesis mode for reception. The PLL selected for reception is locked and active at the receive frequency. The RF part is off.
TX	When activated the SX1276/77/78/79 powers all remaining blocks required for transmit, ramps the PA, transmits the packet and returns to Standby mode.
RXCONTINUOUS	When activated the SX1276/77/78/79 powers all remaining blocks required for reception, processing all received data until a new user request is made to change operating mode.
RXSINGLE	When activated the SX1276/77/78/79 powers all remaining blocks required for reception, remains in this state until a valid packet has been received and then returns to Standby mode.
CAD	When in CAD mode, the device will check a given channel to detect LoRa preamble signal

It is possible to switch from one mode to another by adjusting the value in the RegOpMode record.

Energy supply strategy

The SX1278 takes advantage of an internal voltage directive diagram, which ensures a constant working voltage and, consequently, an ambient mechanical temperature and operating voltage range. This increases the RF output power by +17 dBm

From 1.8V to 3.7V, and from 2.4V to 3.7V, +20 dBm was maintained.

VBAT ANA, VBAT RF and VBAT DIG pins can be used to power SX1278 from any low voltage source. To ensure proper operation of the explosion voltage regulators, the disconnectors must be connected to the VR PA, VR DIG and VR ANA pins as shown in the instruction plan for the Applications section of this registry.

Low Battery Detector (4.8)

On the other hand, the low battery locator allows to determine the lifetime of the violation signal by a backup voltage drop below the programmable edge that can be set by the reglobot register.

Frequency synthesis

Basic alignment guide of the jewelry oscillator SX1278. It serves as a clock signal for all high-level processes and a guide to the PLL repeat mix.

The electrical properties of the pearl guide used determine the initial period of the TS OSC useful diamond oscillator. For more details on the electrical determination of the gemstone on the XTA and XTB pins, attach the Pearl Pierce Oscillator. The SX1278 shortens the start time and, as a result, activates the PLL when the oscillator signal is stable.

Alternatively, the gem oscillator can be replaced with an external clock. It usually appears as a precious stone oscillator with temperature compensation with proximal enclosure (TCXO). When using an external clock source the Reg Reg Tixo piece should be set to 1 and the external clock in the XTA should be left open. The maximum amplitude of the data marker peak should not exceed 1.8 eV. The CLKOUT signal is used to monitor precise programming that prevents the Secret Mission Stone. Remember to limit the current usage of the SX1278, if not too complicated, disable the CLKOUT signal when not needed.

RC OSCILLATOR (4.9 RC)

The two coordination tasks take place in the upper level low power sleep state, which depends on the accuracy of the internal RC oscillator. Therefore, this oscillator can be adjusted at device startup without the need for customer feedback.

The current warranty group monitors radio frequency load conditions. It has the added advantage of saving battery science with limited current capacity and reducing the use of PA in calculating battery life in the most extreme conditions. The estimate of the current limit is calculated by the following formulas, which are limited to the OcpTrim bits in RegOcp:

Table:1.1.3 OVER CURRENT PROTECTION

<i>OcpTrim</i>	I_{MAX}	<i>I</i> _{max} Formula
0 to 15	45 to 120 mA	$45 + 5 * OcpTrim$ [mA]
16 to 27	130 to 240 mA	$-30 + 10 * OcpTrim$ [mA]
27+	240 mA	240 mA

RECEIVER DESCRIPTION

After blocking LNA-mixers, the SX1278 presents a computerized recipient with a simple and sophisticated editing system that manages directly. The low IF recipient removes the MSK amendment regardless of the Lora marshalling pan. Disassembly, restoration, acquisition control, synchronization and parcel management are all subtly implemented to allow highly programmable compatibility. Similarly, the receiver is pre-programmed

Adjusting increases the accuracy of the RSSI count and improves image rejection

Two requirements for facilities are described in the complex operation mode. The receiver has been in "Beneficiary Enabled" state since switching to batch mode for the first time. In this case, the aggregator expects the customer to be fulfilled by the defined lead of RSSI placement model.

4.10 Temperature measurement

In all but one mode, a single temperature estimate block is used to determine the temperature. It will be activated automatically. The post-assessment effect is taken into account. The maximum accuracy of the result due to contact differences is ± 10 C. High accuracy requires temperature controlled correction technique. The effect of this change reaction is shown in the following diagram.

Tab:1.2.1 Correction Factor

Correction Factor			
15			
Actual Temp [Celsius]	RegTemp [Dec]	Temp before calibration [°C]	Temp after calibration [°C]
85	181	74	89
75	190	65	80
65	201	54	69
55	211	44	59
45	222	33	48
35	232	23	38
25	245	10	25
15	0	0	15
5	10	-10	5
-5	21	-21	-6
-15	33	-33	-18
-25	44	-44	-29
-35	56	-56	-41
-40	63	-63	-48

4.11 RESET OF CHIP

When turned on, the SX1278 power reset will begin. 7 pin control can also be used for hard reset. For applications that do not really separate the VDD, the SX1278 can be reset manually. Pin 7 can be pulled to less than 100 for before plugging. Using the chip also allows the user to control everything for Sms.

4.12 BMP180 (DIGITAL PRESSURE SENSOR)




Fig:1.2.1 BMP180 Sensor Module




Fig:1.2.2 BMP180 Sensor Pinout

TYPICAL APPLICATIONS

Improved GPS route (ultimate revenge, slope detection, etc.) entry and exit route

Events and leisure

Vertical speed indicator in weather forecast (height / sink speed)

Electrical Properties 4.13

Anti-pressure sensor, forward-to-line primary switch, control unit with E2PROM and post I2C controller are included in the BMP180. Corrective rating of crushing fraction and temperature is approved by BMP180. E2PROM handled 176 different pieces of workflow data. It is used to replace sensor balance, temperature sensitivity and other limitations.

Table:1.3.1

ABSOLUTE MAXIMUM RATINGS


Parameter	Condition	Min	Max	Units
Storage temperature		-40	+85	°C
Supply voltage	all pins	-0.3	+4.25	V
ESD rating	HBM, R - .str , C - 100pF		±2	kV
Overpressure			10,000	hPa

Table:1.3.2

4.14 OPERATION

The BMP180 is designed to be clearly connected to a wireless controller using an I2C transmission. E2PROM calibration details for BMP180 cover pressure factor and temperature data.

Anti-pressure sensor, forward-to-line primary switch, control unit with E2PROM and post I2C controller are included in the BMP180. Corrective rating of crushing fraction and temperature is approved by BMP180. E2PROM handled 176 different pieces of workflow data. It is used to replace sensor balance, temperature sensitivity and other limitations.



UP = pressure data (16 to 19 piece) UT = temperature data (16 cycle)

Fig :1.3 Regular circuit

4.15 CALCULATING OF TEMPERATURE , PRESSURE

The Bosch SensorTech contains the ANSI C code for all the tests discussed here. To enable pressure factor or temperature prediction, the microcontroller sends an initial game plan. Can be used to check score grading (UP or UT, respectively) after the I2C interface changes over time. Details Adjustment details should be used to determine the temperature fraction in C and the pressure fraction in hPa. The BMP180 E2PROM can be removed using the I2C module when fitting programming.

The viewing rate can be raised to 128 samples per second for dynamic evaluation (standard mode). The temperature must now be calculated once per second for all pressure factors ratings during the same duration and utilised as driving force.




Fig:1.4Measurement flow BMP180

4.16 HARDWARE PRESSURE SAMPLING ACCURACY MODES

The best trade-off between power use, pace, and aim can be chosen by using different modes, as seen in the table below.

Table:1.3.3

Mode	Parameter <i>oversampling_setting</i>	Internal number of samples	Conversion time pressure max. [ms]	Avg. current @ 1 sample/s typ. [μA]	RMS noise typ. [hPa]	RMS noise typ. [m]
ultra low power	0	1	4.5	3	0.06	0.5
standard	1	2	7.5	5	0.05	0.4
high resolution	2	4	13.5	7	0.04	0.3
ultra high resolution	3	8	25.5	12	0.03	0.25

Both modes are implemented at rates as high as several times per second at the standard rate, while at the same time moderately expanding the current utilization of the sample rate.

4.12.1 Pressure and temperature calculation

The pattern increment setting vector (0, 1, 2, 3) can be used in the C symbol to define the mode (very low power, normal, large, very important parameter).

Calculate the actual temperature and pressure fraction in 1 Pa increments (= 0.01hPa = 0.01mbar), as well as the temperature in 0.1 ° C increments. The following diagram illustrates

Detailed pressure factor and temperature estimation calculations.

Calculation of pressure and temperature for BMP180




Fig : 1.5 Calculation for pressing factor and temperature estimation

4.17 PIN CONFIGURATION

The gadget is seen in top view in the picture. Gadget pins are shown here solely for the purpose of guidance.




Fig: 1.6 pin diagram

MOUNTING AND ASSEMBLY RECOMMENDATIONS

When installing a pressure factor sensor on a printed circuit board (PCB), the following recommendations should be considered in order to achieve a predetermined implementation of your plan and "maintain, packaging and install BMP180":

BMP180 has the following features: 4.18

BMP180 Advantages:

The BMP180 is compatible with cells, personal digital assistants (PDAs), the Global Positioning System (GPS) and other PDAs due to its very low power and voltage strategy.

Low-altitude noise and I2C connections, fast
response

4.19 GPS(NEO-6)




Fig:2.1 GPS Module

The GPS module NEO-6M is a well-known, low-cost and up-to-date unit with a radio cable for fixing pots, internal memory module and spare battery, which can be used with a wide range of microcontrollers. GY-GPS6MV2 and GY-GPSV3-NEO are two NEO-6M GPS modules that are very popular these days.

The GPS NEO-6M used in these units is really good with a lot of impact power for indoor applications. EEPROM is also available to store a viable MS621FE battery and configuration settings for backup. GPS units are based on the U-Blocks NEO-6M GPS engine, which works great with DC input in the 3.3 to 5-V range. When using a repaired radio cable, it must be set according to the geographical horizon. The receiving wire should provide a complete view of the horizon, ensuring instant visibility of the largest satellites visible under the conditions.

4.20 PIN

VCC, RX, TX and GND are the four terminals on the NEO-6M GPS card. Since the unit communicates with Arduino via a series of TX and RX pins, the connection is not easy.

Raw GPS data

To get approximate GPS results, run serial software correspondence with the GPS unit in a straight line.

Arduino NEO-6M GPS module wires are required to test this model.

Theory in diagrams

Follow the diagram below to attach the NEO-6M GPS module to the Arduino.





Fig:2.1.1 Connection of NEO-6M and Arduino

If your unit default body rate is not 9600 bps, you must change the code on the following line:

This chart hears data from the GPS module on the serial port and sends it to the serial display.

Open the serial monitor at 9600 baud.



```
$GPRMC,191550.00,A,4,N,00831.54551,W,0.041,,030118,,A*66
$GPVTG,,T,,M,0.041,N,0.076,K,A*27
$GPGGA,19,N,00831.54551,W,1,08,0.95,122.6,M,50.1,M,,*43
$GPGSA,A,3,24,12,15,29,19,25,32,14,,,,,1.61,0.95,1.30*0B
$GPGSV,4,1,13,02,04,104,,06,04,075,12,10,17,257,,12,78,015,26*75
$GPGSV,4,2,13,14,17,317,16,15,17,161,31,17,02,029,,18,09,228,20*7F
$GPGSV,4,3,13,19,18,040,33,24,57,087,32,25,55,251,31,29,16,181,29*7F
$GPGSV,4,4,13,32,37,308,25*42
$GPGLL,4,N,00831.54551,W,191550.00,A,A*71
$GPRMC,191551.00,A,4,N,00831.54550,W,0.024,,030118,,A*6A
$GPVTG,,T,,M,0.024,N,0.044,K,A*25
$GPGGA,19,N,00831.54550,W,1,08,0.95,122.6,M,50.1,M,,*4C
$GPGSA,A,3,24,12,15,29,19,25,32,14,,,,,1.61,0.95,1.30*0B
$GPGSV,4,1,13,02,04,104,,06,04,075,11,10,17,257,,12,78,015,26*76
$GPGSV,4,2,13,14,17,317,17,15,17,161,30,17,02,029,,18,09,228,20*7F
$GPGSV,4,3,13,19,18,040,33,24,57,087,32,25,55,251,31,29,16,181,29*7F
$GPGSV,4,4,13,32,37,308,25*42
$GPGLL,4,N,00831.54550,W,191551.00,A,A*7E
```

Fig:2.1.2

You can get a lot of information in NMEA which is the standard language of GPS. Each line in the synchronization display corresponds to the NMEA statement.

NMEA stands for National Marine Electronics Association, and is a common cognitive system adhered to by GPS manufacturers.

Get location information

You can change the GPS information approximately or you can save the text progress as a variable and turn NMEA messages into an understandable and important link. To do this we use the TinyGPS ++ library.

This library makes it easy to get useful and clear data instantly in the enterprise.

```
# Add 'TinyGPS ++. h> 'TinyGPS ++. h> 'TinyGPS ++. h #include 'SoftwareSerial.h>
SoftwareSerial.h> 'SoftwareSerial.h>

TinyGPSPlus GPS; Constant constant RXPin = 4, TXPin = 3; Static constant uint32_t
GPSBaud = 9600; TinyGPSPlus GPS; TinyGPSPlus GPS; TinyGPSPlus GPS;
TinyGPSPlus GPS; TinyGPSPlus GPS; TinyGP
```

Software serial ss (RXPin, TXPin) is the serial link for GPS.

```
Serial.Begin (9600); ss.begin (GPSBaud); Null setup ()
```

Null Loop () Displays the graphic details when the new sentence is encoded correctly. if (gps.location.isUpdated ()) if (ss.available ()> 0) gps.encode (ss.read ());

```
Serial.println (gps.location.lng (), 6); Serial.print ("latitude ="); Serial.print (gps.location.lat
(), 6); Serial.print ("longitude ="); Serial.print (gps.location.lng (), 6); To enable TinyGPS
++ playback, you can use encoding () technology to guide characters multiple times from
the GPS module.
```

```
while (ss.available() > 0){  
  gps.encode(ss.read());  
}
```

Next, to see if any data fields have been modified, inquire about the GPS object:

```
}
```

The location is as easy to reach in latitude and length as `gps.location.lat ()` and `gps.location.lng ()`.

This area will appear on the Chronograph computer when you upload the code to your Arduino. Wait a few moments after the code has been sent, while the unit changes the conditions to obtain more precise data.




Fig:3.1

ADVANTAGES OF NEO-6M:

It can monitor 22 satellites at 50 stations and achieve as simple impact scalability as 161 dB tracking in the industry, using only 45 mA of current stock.

Unlike other GPS units, it can perform up to 5 area revisions per second with a horizontal positioning accuracy of 2.5 m.

4.20 OLED screen

As shown in the diagram below, the natural light-emitting diode (OLED) display has a 0.96-inch screen with a resolution of 128x64 pixels.



Fig:4.1 OLED DISPLAY

The OLED display does not require backlighting, resulting in an interesting high light in low light. Also, since pixels only consume power when running, the OLED display consumes less power compared to other screens.

The model we use has four pins and communicates through the I2C protocol with Arduino. Many versions have an additional PIN. There are also other OLED displays using SPI connectivity. Since the I2C communication protocol is used for the OLED display, cable operation is easy. Join them is all you have to do.




Fig: 4.2

5 CHAPTER

TRANSMITTER CIRCUIT:




Fig:5.1

4.20.1 TRANSMITTER CODE:

Transmittercode

<pre> #include <SPI.h> #include <LoRa.h> #include <Adafruit_GFX.h> #include <Adafruit_SSD1306.h> #define DHT11 #define SCREEN_WIDTH 128 // OLED display width, in pixels #define SCREEN_HEIGHT 64 // OLED display height, in pixels // Declaration for DHT11 Adafruit_DHT dht(DHT11, 2); // Declaration for SSD1306 Adafruit_SSD1306 display(SCREEN_WIDTH, SCREEN_HEIGHT, &Wire); // Declaration for LoRa LoRa LoRaModule = LoRa(433, 433); // Declaration for SPI SPI spi(SPI_SS_PIN); // Declaration for DHT11 DHT@dht(DHT11); // Declaration for display display.begin(SSD1306_SWITCHCAPVCC, 0x3C); display.clearDisplay(); display.setTextSize(2); display.setTextColor(WHITE); display.setCursor(0,0); display.print(F("Pkt No:")); display.print(counter); display.setCursor(0,20); display.print(F("Tem:")); display.print(t); display.print(F("Hum:")); display.print(h); display.print(F("%")); display.display(); // send packet LoRa.beginPacket(); LoRa.print(F("Pkt No:")); LoRa.print(counter); LoRa.print(F("Temp: ")); LoRa.print(F("Hum: ")); LoRa.print(h); LoRa.print(F("%")); counter++; </pre>	<pre> Serial.println(F("SSD1306 allocation failed")); for(;;); // Don't proceed, loop forever while (!Serial); Serial.println("LoRa Sender"); LoRa.setPins(ss, rst, dio0); if (!LoRa.begin(433E6)) { Serial.println("Starting LoRa failed!"); delay(100); } float h = dht.readHumidity(); float t = dht.readTemperature(); if (isnan(h) isnan(t)) return; Serial.print("Temperature: "); Serial.print(t); Serial.print(" degrees Celcius, Humidity: "); Serial.print(h); Serial.println(); </pre>	<pre> display.clearDisplay(); display.setTextSize(2); // Normal 1:1 pixel scale display.setTextColor(WHITE); // Draw white text display.setCursor(0,0); // Start at top-left corner display.print(F("Pkt No:")); display.print(counter); display.setCursor(0,20); display.print(F("Tem:")); display.print(t); display.print(F("Hum:")); display.print(h); display.print(F("%")); display.display(); // send packet LoRa.beginPacket(); LoRa.print(F("Pkt No:")); LoRa.print(counter); LoRa.print(F("Temp: ")); LoRa.print(F("Hum: ")); LoRa.print(h); LoRa.print(F("%")); counter++; </pre>
---	--	---

4.21 RECEIVER CIRCUIT:

Fig:5.2

4.21.1 RECEIVER CODE:

Code for Receiver

```
#include <SPI.h>
#include <LoRa.h>

#define ss 15
#define rst 16
#define dio0 4

void setup() {
  Serial.begin(115200);
  while (!Serial);

  Serial.println("LoRa Receiver Callback");

  LoRa.setPins(ss, rst, dio0);

  if (!LoRa.begin(470E6)) {
    Serial.println("Starting LoRa failed!");
    while (1);
  }

  // register the receive callback
  LoRa.onReceive(onReceive);

  // put the radio into receive mode
  LoRa.receive();

  void loop() {
    // do nothing

    void onReceive (int packetSize) {
      // received a packet
      Serial.println("Received packet");

      // read packet
      for (int i = 0; i < packetSize; i++) {
        Serial.print((char)LoRa.read());
      }
    }
  }
}
```

CHAPTER-5

5 OUTPUT OF THE TRANSMITTER:



Fig:6.1

5.1 OUTPUT OF THE RECEIVER:

```
Received packet with Time of 12787 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100568, end
LoRa Receiver
Received packet with Time of 713 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100576, end
receive packet with Time of 2276 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100573, end
Received packet with Time of 5229 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100571, end
Received packet with Time of 6606 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100572, end
Received packet with Time of 7943 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100575, end
Received packet with Time of 9360 with RSSI -114 with received data : %, 12.785254, 80.456314, 29.60, 100575, end
Received packet with Time of 10737 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100571, end
Received packet with Time of 1190 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100577, end
Received packet with Time of 13117 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100574, end
Received packet with Time of 15228 with RSSI -115 with received data : %, 12.785254, 80.456314, 29.60, 100567, end
```

CHAPTER-6

CONCLUSION

Trapper position, race and temperature are calculated using a GPS and barometric pressure sensor and sent to the base station via the Lora module.

The location of the hunter is determined using GPS NEO-6M. As a result, it has become easier and smarter to track hunters. It helps to determine the status of the hunter from time to time.

The sensors used in the project provide the hunter with information about noise, temperature and location.

The Fishermen's Control System helps reduce cases of fishermen missing in bad weather.

Finally, the most important finding is that the protection of the hunter is mainly determined by its location, breed and temperature. These parameters can be sent through the base station and tracked with sensors.

REFERENCES

1. Bharat Chaudhari, Marco Zennaro and Suresh Borkar, "LPWAN Technologies: Emerging Application Characteristics Requirements and Design Considerations", *Future Internet*, vol. 12, pp. 46, 2020.
- Q. Zhou, K. Zheng, L. Hou, J. Xing and R. Xu, "Design and Implementation of Open LoRa for IoT", *IEEE Access*, vol. 7, pp. 100649-100657, 2019
- A. Zourmand, A. L. Kun Hing, C. Wai Hung and M. AbdulRehman, "Internet of Things (IoT) using LoRa technology", 2019 IEEE International Conference on Automatic Control and Intelligent Systems (I2CACIS), pp. 324-330, 2019.
- .Kais Mekki, Eddy Bajic, Frederic Chaxel and Fernand Meyer, A comparative study of LPWAN technologies for large-scale IoT deployment, vol. 5, pp. 1-7, 2019.
- J. Wang, S. Yi, D. Zhan and W. Zhang, "Design and Implementation of small monitoring wireless network system based on LoRa", 4th Advanced Information Technology Electronic and Automation Control Conference (IAEAC), pp. 296-299, 2019
- B. Ngom, M. Diallo, B. Gueye and N. Marilleau, "Lora-based measurement station for water quality monitoring: Case of botanical garden pool", 2019 IEEE Sensors Applications Symposium (SAS). IEEE, pp. 1-4, 2019.
- .T. Addabbo, A. Fort, A. Mecocci, M. Mugnaini, S. Parrino, A. Pozzebon, et al., "A Lora-based IoT sensor node for waste management based on a customized ultrasonic transceiver", 2019 IEEE Sensors Applications Symposium (SAS). IEEE, pp. 1-6, 2019.
- Dunlop, H. Nguyen, R. Barton and J. Henry, "Interference analysis for LoRa chirp spread spectrum signals", *Proc. IEEE Canadian Conf. of Electr. and Comput. Engin. (CCECE)*, May 2019
- A. Mahmood, E. Sisinni, L. Guntupalli, R. Rondon, S. A. Hassan and M. Gidlund, "Scalability analysis of a LoRa network under imperfect orthogonality", *IEEE Trans. Ind. Informat.*, vol. 15, no. 3, pp. 1425-1436, Mar. 2019.
- .M. Ji, J. Yoon, J. Choo, M. Jang and A. Smith, "LoRa-based Visual Monitoring Scheme for Agriculture IoT", *IEEE Sensors Applications Symposium*, 2019.
- T. Elshabrawy and J. Robert, "Interleaved chirp spreading lora-based modulation", *IEEE Internet of Things Journal*, pp. 1-1, 2019.

- E. Murdyantoro, I. Rosyadi and H. Septian, "Studi Performansi Jarak Jangkauan Lora-Dragino Sebagai Infrastruktur Konektifitas Nirkabel Pada WP-LAN", *Din. Rekayasa*, vol. 15, no. 1, pp. 47, 2019.
- .P. Devi, D. Istianti, S. Y. Prawiro, N. Bogi, A. Karna and I. A. Nursafa, "Analisis Performansi Teknologi Akses LPWAN LoRa Antares Untuk Komunikasi Data End Node", *Citee* 2019, pp. 24-25, 2019.
- .D. Croce, M. Gucciardo, S. Mangione, G. Santaromita and I. Tinnirello, "Impact of lora imperfect orthogonality: Analysis of link-level performance", *IEEE Commun. Lett.*, vol. 22, no. 4, pp. 796-799, April 2018.
- L. Feltrin, C. Buratti, E. Vinciarelli, R. D. Bonis and R. Verdone, "Lorawan: Evaluation of link- and system-level performance", *IEEE Internet Things J.*, vol. 5, no. 3, pp. 2249-2258, June 2018.
- 13.P. Gotthard and T. Jankech, "Low-cost car park localization using RSSI in supervised LoRa mesh networks", 2018 15th Workshop on Positioning Navigation and Communications (WPNC). IEEE, pp. 1-6, 2018.

DESIGN OF FISHERMAN SAFETY COMMUNICATION DEVICE USING LORA TECHNOLOGY

ORIGINALITY REPORT

5%

SIMILARITY
INDEX

3%

INTERNET
SOURCES

2%

PUBLICATIONS

1%

STUDENT PAPERS

PRIMARY SOURCES

1

[randomnerdtutorials.com](https://www.randomnerdtutorials.com)

Internet Source

2

"Advances and Applications in Computer Science, Electronics and Industrial Engineering", Springer Science and Business Media LLC, 2021

Publication

3

Yoshihiro Higashiura, Hiroshi Yamamoto. "Large-scale farm sensing system using UAV and long-distance wireless communication", 2021 International Conference on Information Networking (ICOIN), 2021

Publication

4

Christos Bouras, Apostolos Gkamas, Vasileios Kokkinos, Nikolaos Papachristos. "Real-Time Geolocation Approach through LoRa on Internet of Things", 2021 International Conference on Information Networking

(ICOIN),
2021
Publication

2%

<1%

1%

<1%

5	Kiyoshy Nakamura, Pietro Manzoni, Marco Zennaro, Juan-Carlos Cano, Carlos T. Calafate. "Chapter 21 Integrating an MQTT Proxy in a LoRa-Based Messaging System for Generic Sensor Data Collection", Springer Science and Business Media LLC, 2020	<1%
6	Publication researchr.org	<1%
7	Internet Source Submitted to University of Florida	<1%
8	Student Paper Submitted to Scotch College	<1%
9	Student Paper www.lypelaw.com	<1%
10	Internet Source Jianing Wang, Shiyu Yi, Donglin Zhan, Weihua Zhang. "Design and Implementation of small monitoring wireless network system based on LoRa", 2019 IEEE 4th Advanced Information Technology, Electronic and Automation Control Conference (IAEAC), 2019	<1%
11	Publication www.gradesaver.com	<1%
12	Internet Source csc.sjtu.edu.cn	<1%

13

research.aalto.
fi

Internet Source

<1%

Exclude quotes

☐

Exclude bibliography

☐

n

Exclude matches

Off

DESIGN OF FISHERMAN SAFTEY COMMUNICATION DEVICE USING LORA TECHNOLOGY

GRADEMARK REPORT

FINAL
GRADE

/0

GENERAL COMMENTS

Instructor

PAGE 1

PAGE 2

PAGE 3

PAGE 4

PAGE 5

PAGE 6

PAGE 7

PAGE 8

PAGE 9

PAGE 10

PAGE 11

PAGE 12

PAGE 13

PAGE 14

PAGE 15

PAGE 16

PAGE 17

PAGE 18

PAGE 19

PAGE 20

PAGE 21

PAGE 22

PAGE 23

PAGE 24

PAGE 25

PAGE 26

PAGE 27

PAGE 28

PAGE 29

PAGE 30

PAGE 31

PAGE 32

PAGE 33

PAGE 34

PAGE 35

PAGE 36

PAGE 37

PAGE 38

PAGE 39

PAGE 40

PAGE 41